











SLAS411D - NOVEMBER 2004-REVISED FEBRUARY 2016

**DAC8811** 

# DAC8811 16-Bit, Serial Input Multiplying Digital-to-Analog Converter

#### **Features**

- ±0.5 LSB DNL
- 16-Bit Monotonic
- ±1 LSB INL
- Low Noise: 12 nV/√Hz Low Power:  $I_{DD} = 2 \mu A$
- 2.7-V to 5.5-V Analog Power Supply
- 2-mA Full-Scale Current ±20%, with  $V_{REF} = 10 \text{ V}$
- 50-MHz Serial Interface
- 0.5-µs Settling Time
- 4-Quadrant Multiplying Reference
- Reference Bandwidth: 10 MHz
- ±10-V Reference Input
- Reference Dynamics: -105 THD
- Tiny 8-Lead 3 x 3 mm VSON and 3 x 5 mm VSSOP Packages
- Industry-Standard Pin Configuration

# **Applications**

- Automatic Test Equipment
- Instrumentation
- **Digitally Controlled Calibration**
- Industrial Control PLCs

# **Description**

The DAC8811 multiplying digital-to-analog converter (DAC) is designed to operate from a single 2.7-V to 5.5-V supply.

The applied external reference input voltage V<sub>RFF</sub> determines the full-scale output current. An internal feedback resistor (R<sub>FB</sub>) provides temperature tracking for the full-scale output when combined with an external I-to-V precision amplifier.

A serial data interface offers high-speed, three-wire microcontroller-compatible inputs using data-in (SDI), clock (CLK), and chip-select (CS).

On power-up, the DAC register is filled with zeroes, and the DAC output is at zero scale.


The DAC8811 is packaged in space-saving 8-lead VSON and VSSOP packages.

# **Device Information**(1)

PART NUMBER	PACKAGE	BODY SIZE (NOM)
DAC8811	VSSOP (8)	3.00 mm × 3.00 mm
	VSON (8)	3.00 mm × 3.00 mm

(1) For all available packages, see the orderable addendum at the end of the datasheet.

# **Simplified Schematic**





#### **Table of Contents**

1	Features 1	8.3 Feature Description 1
2	Applications 1	8.4 Device Functional Mode14
3	Description 1	8.5 Programming1
4	Revision History2	9 Application and Implementation 16
5	Device Comparison Table 4	9.1 Application Information 16
6	Pin Configuration and Functions	9.2 Typical Application10
7	Specifications	10 Power Supply Recommendations 17
′	7.1 Absolute Maximum Ratings 5	11 Layout 18
	7.2 ESD Ratings 5	11.1 Layout Guidelines 18
	7.3 Recommended Operating Conditions	11.2 Layout Example 18
	7.4 Thermal Information	12 Device and Documentation Support 19
	7.5 Electrical Characteristics 6	12.1 Documentation Support 1
	7.6 Timing Requirements	12.2 Community Resources 19
	7.7 Typical Characteristics: V <sub>DD</sub> = 5 V	12.3 Trademarks 19
	7.8 Typical Characteristics: V <sub>DD</sub> = 2.7 V	12.4 Electrostatic Discharge Caution
8	Detailed Description	12.5 Glossary1
Ü	8.1 Overview	13 Mechanical, Packaging, and Orderable
	8.2 Functional Block Diagram	Information

# 4 Revision History

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

CI	nanges from Revision C (October 2015) to Revision D
•	<ul> <li>Changed the SYNC Interrupt Facility image</li> <li>Changes from Revision B (February 2007) to Revision C</li> <li>Added ESD Ratings table, Recommended Operating Conditions table, Thermal Information table, Timing Requirements table, Feature Description section, Device Functional Modes, Application and Implementation section, Power Supply Recommendations section, Layout section, Device and Documentation Support section, and</li> </ul>
CI	
•	Requirements table, Feature Description section, Device Functional Modes, Application and Implementation section,
<u>.</u>	Changed R3' From: 50 kΩ To: 50 Ω in Figure 23
CI	nanges from Revision A (December 2004) to Revision B Page
•	Added a new paragraph to the Description , "On power-up,"
•	Changed the Simplified Schematic to include the Power-On Reset




CI	hanges from Original (November 2004) to Revision A	Page
•	Removed the Product Preview label	1
•	Added information to the Features	1
•	Added Output leakage current Data = 0000h, T <sub>A</sub> = T <sub>MAX</sub> in the Electrical Characteristics	6
•	Added Input high voltage for V <sub>DD</sub> = 2.7 V and 2.5 V in the Electrical Characteristics	6
•	Changed the values of the Power Requirements and the AC characteristics section in the Electrical Characteristics	6




# 5 Device Comparison Table

PART NUMBER	INL (LSB)	DNL (LSB)
DAC8811ICDGK	±1	±1
DAC8811IBDGK	±2	±1
DAC8811ICDRB	±1	±1
DAC8811IBDRB	±2	±1

# 6 Pin Configuration and Functions





## **Pin Functions**

PIN	N	TYPE	DESCRIPTION		
NAME	NO.	ITPE	DESCRIPTION		
CLK	1	I	Clock input; positive edge triggered clocks data into shift register		
SDI	2	1	Serial register input; data loads directly into the shift register MSB first. Extra leading bits are ignored.		
R <sub>FB</sub>	3	0	Internal matching feedback resistor. Connect to external op amp output.		
V <sub>REF</sub>	4	1	C reference input pin. Establishes DAC full-scale voltage. Constant input resistance versus e.		
I <sub>OUT</sub>	5	0	DAC current output. Connects to inverting terminal of external precision I/V op amp.		
GND	6	G	Analog and digital ground.		
$V_{DD}$	7	I	Positive power supply input. Specified operating range of 2.7 V to 5.5 V.		
CS	8	I	Chip-select; active low digital input. Transfers shift register data to DAC register on rising edge. See Table 1 for operation.		



# 7 Specifications

## 7.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted) (1)

		MIN	MAX	UNIT
Input voltage	V <sub>DD</sub> to GND	-0.3	7	V
	V (I <sub>OUT</sub> ) to GND	-0.3	$V_{DD} + 0.3$	٧
Digital input voltage	GND	-0.3	$V_{DD} + 0.3$	٧
Reference voltage, V <sub>REF</sub>	R <sub>FB</sub> to GND	-25	25	V
Operating temperature		-40	105	°C
Junction temperature, T <sub>J</sub>			125	°C
Storage temperature, T <sub>stg</sub>		-65	150	

<sup>(1)</sup> Stresses above those listed under absolute maximum ratings may cause permanent damage to the device. Exposure to absolute maximum conditions for extended periods may affect device reliability.

# 7.2 ESD Ratings

			MAX	UNIT
		Human body model (HBM), per ANSI/ESDA/JEDEC JS-001 (1)	±4000	
V <sub>(ES</sub>	SD) Electrostatic discharge	Charged device model (CDM), per JEDEC specification JESD22-C101 (2)	±1000	V

<sup>(1)</sup> JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.

# 7.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

	,			
		MIN	NOM MAX	UNIT
Supply voltage to GND		2.7	5.5	V
Operating ambient temperature, T <sub>A</sub>		-40	125	°C

#### 7.4 Thermal Information

		DAC	DAC8811		
	THERMAL METRIC <sup>(1)</sup>	DGK (VSSOP)	DRB (VSON)	UNIT	
		8 PINS	8 PINS		
$R_{\theta JA}$	Junction-to-ambient thermal resistance	169.6	46.7	°C/W	
R <sub>0JC(top)</sub>	Junction-to-case (top) thermal resistance	64.2	61.3	°C/W	
$R_{\theta JB}$	Junction-to-board thermal resistance	90.3	22	°C/W	
$\Psi_{JT}$	Junction-to-top characterization parameter	7.7	1.1	°C/W	
ΨЈВ	Junction-to-board characterization parameter	88.8	22.1	°C/W	
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	N/A	3.8	°C/W	

For more information about traditional and new thermal metrics, see the Semiconductor and IC Package Thermal Metrics application report, SPRA953.

<sup>(2)</sup> JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.



# 7.5 Electrical Characteristics

 $V_{DD}$  = 2.7 V to 5.5 V;  $I_{OUT}$  = Virtual GND, GND = 0 V;  $V_{REF}$  = 10 V;  $T_A$  = full operating temperature. All specifications -40°C to 85°C, unless otherwise noted.

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
STATIC PI	ERFORMANCE					
	Resolution		16			Bits
	Relative accuracy	DAC8811C			±1	LSB
	Relative accuracy	DAC8811B			±2	LSB
	Differential nonlinearity			±0.5	±1	LSB
	Output leakage current	Data = 0000h, T <sub>A</sub> = 25°C			10	nA
	Output leakage current	Data = 0000h, $T_A = T_{MAX}$			10	nA
	Full-scale gain error	All ones loaded to DAC register		±1	±4	mV
	Full-scale tempco			±3		ppm/°C
OUTPUT (	CHARACTERISTICS <sup>(1)</sup>					
	Output current			2		mA
	Output capacitance	Code dependent		50		pF
REFEREN	CE INPUT <sup>(1)</sup>					
	V <sub>REF</sub> Range		-15		15	V
	Input resistance			5		kΩ
	Input capacitance			5		pF
LOGIC INF	PUTS AND OUTPUT <sup>(1)</sup>				•	
\ /	land the second terms	$V_{DD} = 2.7V$			0.6	V
$V_{IL}$	Input low voltage	$V_{DD} = 5V$			0.8	V
\ /	land think waltana	$V_{DD} = 2.7V$	2.1			V
$V_{IH}$	Input high voltage	$V_{DD} = 5V$	2.4			V
I <sub>IL</sub>	Input leakage current				10	μΑ
C <sub>IL</sub>	Input capacitance				10	pF
POWER R	EQUIREMENTS					
$V_{DD}$			2.7		5.5	V
	I <sub>DD</sub> (normal operation)	Logic inputs = 0 V			5	μA
	V <sub>DD</sub> = 4.5 V to 5.5 V	$V_{IH} = V_{DD}$ and $V_{IL} = GND$		3	5	μΑ
	V <sub>DD</sub> = 2.7 V to 3.6 V	$V_{IH} = V_{DD}$ and $V_{IL} = GND$		1	2.5	μΑ
AC CHAR	ACTERISTICS <sup>(1)</sup> (2)				•	
BW -3 dB	Reference mutiplying BW	V <sub>REF</sub> = 5 V <sub>PP</sub> , Data = FFFFh		10		MHz
	DAC glitch impulse	V <sub>REF</sub> = 0 V to 10 V, Data = 7FFFh to 8000h to 7FFFh		2		nV/s
	Feed through error V <sub>OUT</sub> /V <sub>REF</sub>	Data = 0000h, V <sub>REF</sub> = 100 mV <sub>RMS</sub> , f = 100kHz		-70		dB
	Digital feed through	CS = 1 and f <sub>CLK</sub> = 1 MHz		2		nV/s
	Total harmonic distortion	V <sub>REF</sub> = 5 V <sub>PP</sub> , Data = FFFFh, f = 1 kHz		-105		dB
	Output spot noise voltage	f = 1 kHz, BW = 1 Hz		12		nV/√ <del>Hz</del>

Submit Documentation Feedback

Copyright © 2004–2016, Texas Instruments Incorporated

Specified by design and characterization; not production tested.

All ac characteristic tests are performed in a closed-loop system using the THS4011 I-to-V converter amplifier.



# 7.6 Timing Requirements

			MIN	NOM	MAX	UNIT
INTERF	ACE TIMING					
f <sub>CLK</sub>	Clock input frequency				50	MHz
t <sub>(CH)</sub>	Clock pulse width high		10			ns
t <sub>(CL)</sub>	Clock pulse width low		10			ns
t <sub>(CSS)</sub>	CS to Clock setup time		0			ns
t <sub>(CSH)</sub>	Clock to CS hold time		10			ns
t <sub>(DS)</sub>	Data setup time		5			ns
t <sub>(DH)</sub>	Data hold time		10			ns
AC CHA	ARACTERISTICS <sup>(1)</sup> (2)					
t <sub>s</sub> Output voltage settling time		To ±0.1% of full-scale, Data = 0000h to FFFFh to 0000h		0.3		μs
	To ±0.0015% of full-scale, Data = 0000h to FFFFh to 0000h		0.5		μs	

- (1) Specified by design and characterization; not production tested.
- (2) All ac characteristic tests are performed in a closed-loop system using the THS4011 I-to-V converter amplifier.





Figure 1. DAC8811 Timing Diagram

# TEXAS INSTRUMENTS

# 7.7 Typical Characteristics: $V_{DD} = 5 \text{ V}$

At  $T_A = 25$ °C,  $+V_{DD} = 5$  V, unless otherwise noted.




Submit Documentation Feedback

Copyright © 2004–2016, Texas Instruments Incorporated



# Typical Characteristics: $V_{DD} = 5 \text{ V (continued)}$

At  $T_A = 25$ °C,  $+V_{DD} = 5$  V, unless otherwise noted.







Figure 8. Supply Current vs Logic Input Voltage






Figure 9. Reference Multiplying Bandwidth


Figure 10. DAC Glitch

Figure 11. DAC Settling Time

## TEXAS INSTRUMENTS

# 7.8 Typical Characteristics: $V_{DD} = 2.7 \text{ V}$

At  $T_A = 25$ °C,  $+V_{DD} = 2.7$  V, unless otherwise noted.



Submit Documentation Feedback




# 8 Detailed Description

#### 8.1 Overview

The DAC8811 is a single channel current output, 16-bit digital-to-analog converter (DAC). The device includes a 3-wire serial interface to communicate with most DSPs.

#### 8.2 Functional Block Diagram



#### 8.3 Feature Description

The DAC8811 is a single channel current output, 16-bit digital-to-analog converter (DAC). The architecture, illustrated in Figure 18, is an R-2R ladder configuration with the three MSBs segmented. Each 2R leg of the ladder is either switched to GND or the  $I_{OUT}$  terminal. The  $I_{OUT}$  terminal of the DAC is held at a virtual GND potential by the use of an external I/V converter op amp. The R-2R ladder is connected to an external reference input  $V_{REF}$  that determines the DAC full-scale current. The R-2R ladder presents a code independent load impedance to the external reference of 5 k $\Omega$  ±25%. The external reference voltage can vary in a range of -15 V to 15 V, thus providing bipolar  $I_{OUT}$  current operation. By using an external I/V converter and the DAC8811  $R_{FB}$  resistor, output voltage ranges of  $V_{REF}$  to  $V_{REF}$  can be generated.




Figure 18. Equivalent R-2R DAC Circuit

When using an external I/V converter and the DAC8811  $R_{FB}$  resistor, the DAC output voltage is given by Equation 1:

$$V_{OUT} = -V_{REF} \times \frac{CODE}{65536}$$
 (1)



#### Feature Description (continued)

Each DAC code determines the 2R leg switch position to either GND or  $I_{OUT}$ . Because the DAC output impedance as seen looking into the  $I_{OUT}$  terminal changes versus code, the external I/V converter noise gain will also change. Because of this, the external I/V converter op amp must have a sufficiently low offset voltage such that the amplifier offset is not modulated by the DAC  $I_{OUT}$  terminal impedance change. External op amps with large offset voltages can produce INL errors in the transfer function of the DAC8811 due to offset modulation versus DAC code. For best linearity performance of the DAC8811, an operational amplifier (OPA277) is recommended (Figure 19). This circuit allows  $V_{REF}$  swinging from -10 V to +10 V.




Figure 19. Voltage Output Configuration

#### 8.3.1 Stability Circuit

For a current-to-voltage design (see Figure 20), the DAC8811 current output (I<sub>OUT</sub>) and the connection with the inverting node of the op amp should be as short as possible and according to correct PCB layout design. For each code change, there is a step function. If the GBP of the op amp is limited and parasitic capacitance is excessive at the inverting node then gain peaking is possible. Therefore, for circuit stability, a compensation capacitor C1 (4 pF to 20 pF typ) can be added to the design, as shown in Figure 20.




Figure 20. Gain Peaking Prevention Circuit With Compensation Capacitor

#### 8.3.2 Positive Voltage Output Circuit

As Figure 21 illustrates, in order to generate a positive voltage output, a negative reference is input to the DAC8811. This design is suggested instead of using an inverting amp to invert the output due to tolerance errors of the resistor. For a negative reference,  $V_{OUT}$  and GND of the reference are level-shifted to a virtual ground and a -2.5 V input to the DAC8811 with an op amp.

Product Folder Links: DAC8811

Copyright © 2004-2016, Texas Instruments Incorporated



#### Feature Description (continued)




Figure 21. Positive Voltage Output Circuit

#### 8.3.3 Bipolar Output Circuit

The DAC8811, as a 2-quadrant multiplying DAC, can be used to generate a unipolar output. The polarity of the full-scale output  $I_{OUT}$  is the inverse of the input reference voltage at  $V_{REF}$ .

Some applications require full 4-quadrant multiplying capabilities or bipolar output swing. As shown in Figure 22, external op amp U4 is added as a summing amp and has a gain of 2X that widens the output span to 5 V. A 4-quadrant multiplying circuit is implemented by using a 2.5-V offset of the reference voltage to bias U4. According to the circuit transfer equation given in Equation 2, input data (D) from code 0 to full scale produces output voltages of  $V_{OUT} = -2.5 \text{ V}$  to  $V_{OUT} = +2.5 \text{ V}$ .

$$V_{OUT} = \left(\frac{D}{32,768} - 1\right) \times V_{REF}$$
 (2)

External resistance mismatching is the significant error in Figure 22.




Figure 22. Bipolar Output Circuit

#### 8.3.4 Programmable Current Source Circuit

A DAC8811 can be integrated into the circuit in Figure 23 to implement an improved Howland current pump for precise voltage to current conversions. Bidirectional current flow and high voltage compliance are two features of the circuit. With a matched resistor network, the load current of the circuit is shown by Equation 3:

$$I_{L} = \frac{(R2 + R3)/R1}{R3} \times V_{REF} \times D$$
 (3)

The value of R3 in the previous equation can be reduced to increase the output current drive of U3. U3 can drive  $\pm 20$  mA in both directions with voltage compliance limited up to 15 V by the U3 voltage supply. Elimination of the circuit compensation capacitor C1 in the circuit is not suggested as a result of the change in the output impedance  $Z_0$ , according to Equation 4:



## **Feature Description (continued)**

$$Z_{O} = \frac{R1'R3(R1+R2)}{R1(R2'+R3')-R1'(R2=R3)}$$
(4)

As shown in Equation 4, with matched resistors,  $Z_O$  is infinite and the circuit is optimum for use as a current source. However, if unmatched resistors are used,  $Z_O$  is positive or negative with negative output impedance being a potential cause of oscillation. Therefore, by incorporating C1 into the circuit, possible oscillation problems are eliminated. The value of C1 can be determined for critical applications; for most applications, however, a value of several pF is suggested.




Figure 23. Programmable Bidirectional Current Source Circuit

#### 8.4 Device Functional Mode

Table 1. Control Logic Truth Table (1)

CLK	cs	SERIAL SHIFT REGISTER	DAC REGISTER
X	Н	No effect	Latched
<b>↑</b> +	L	Shift register data advanced one bit	Latched
X	Н	No effect	Latched
X	<b>↑+</b>	Shift register data transferred to DAC register	New data loaded from serial register

(1) ↑+ Positive logic transition; X = Don't care

Submit Documentation Feedback



#### 8.5 Programming

#### 8.5.1 DAC8811 Input Shift Register

The DAC8811 has a 3-wire serial interface ( $\overline{CS}$ , SCLK, and DIN) compatible with SPI, QSPI, and Microwire interface standards, as well as most DSPs. See Figure 1 for an example of a typical write sequence.

The input shift register is 16 bits wide, as shown in Figure 25. The write sequence begins by bringing the  $\overline{\text{CS}}$  line low. Data from the DIN line are clocked into the 16-bit shift register on each rising edge of CLK. The serial clock frequency can be as high as 50 MHz, making the DAC8811 compatible with high-speed DSPs. On the 16<sup>th</sup> rising edge of the serial clock, the last data bit is clocked in and the programmed function is executed.

At this point, the  $\overline{\text{CS}}$  line may be kept low or brought high. In either case, it must be brought high for a minimum of 20 ns before the next write sequence so that a falling edge of  $\overline{\text{CS}}$  can initiate the next write sequence.

Figure 24. Data Input Register

DB15															DB0
D15	D15	D13	D12	D11	D10	D9	D8	D7	D6	D5	D4	D3	D2	D1	D0

LEGEND: R/W = Read/Write; R = Read only; -n = value after reset




Figure 25. CS Interrupt Facility



# 9 Application and Implementation

#### NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

#### 9.1 Application Information

This design features the DAC8811 followed by a four-quadrant circuit for multiplying DACs. The circuit conditions the current output of an MDAC into a symmetrical bipolar voltage. The design uses an operational amplifier in a transimpedance configuration to convert the MDAC current into a voltage followed by an additional amplifier in a summing configuration to apply an offset voltage.

#### 9.2 Typical Application




Figure 26. Typical Application

#### 9.2.1 Design Requirements

Using a multiplying DAC requires a transimpedance stage with an amplifier with minimal input offset voltage. The tolerance of the external resistors will vary depending on the goals of the application, but for optimal performance with the DAC8811 the tolerance should be 0.1 % for all of the external resistors. The summing stage amplifier also needs low input-offset voltage and enough slew rate for the output range desired.

#### 9.2.2 Detailed Design Procedure

The first stage of the design converts the current output of the MDAC ( $I_{OUT}$ ) to a voltage ( $V_{OUT}$ ) using an amplifier in a transimpedance configuration. A typical MDAC features an on-chip feedback resistor sized appropriately to match the ratio of the resistor values used in the DAC R-2R ladder. This resistor is available using the input shown in Figure 26 called RFB on the MDAC. The MDAC reference and the output of the transimpedance stage are then connected to the inverting input of the amplifier in the summing stage to produce the output that is defined by Equation 5.

$$V_{OUT}(Code) = \left(\frac{2_{FB2}}{R_{G1}} \times \frac{V_{REF} \times Code}{2^{bits}}\right) - \left(\frac{R_{FB2}}{R_{G2}} \times V_{REF}\right)$$
(5)

Product Folder Links: DAC8811


Copyright © 2004-2016, Texas Instruments Incorporated



# **Typical Application (continued)**

#### 9.2.3 Application Curves

Figure 27 shows the output voltage vs code of this design, while Figure 28 shows the output error vs code. Keep in mind that the error gets worse as the output code increases because the contribution of the gain error increases with code.



# 10 Power Supply Recommendations

These devices can operate within the specified supply voltage range of 2.7 V to 5.5 V. The power applied to AVDD should be well-regulated and low-noise. In order to further minimize noise from the power supplies, a strong recommendation is to include a pair of 100 pF and 1 nF capacitors and a 0.1  $\mu$ F to 1  $\mu$ F bypass capacitor. The current consumption of the AVDD pin, the short-circuit current limit, and the load current for these devices are listed in the *Electrical Characteristics* table. Choose the power supplies for these devices to meet the aforementioned current requirements.



# 11 Layout

#### 11.1 Layout Guidelines

A precision analog component requires careful layout, adequate bypassing, and clean, well-regulated power supplies. The DAC8811devices offer single-supply operation, and are often used in close proximity with digital logic, microcontrollers, microprocessors, and digital signal processors. The more digital logic present in the design and the higher the switching speed, the more difficult it is to keep digital noise from appearing at the output. As a result of the single ground pin of the DAC8811, all return currents (including digital and analog return currents for the DAC) must flow through a single point. Ideally, GND would be connected directly to an analog ground plane. This plane would be separate from the ground connection for the digital components until they were connected at the power-entry point of the system. The power applied to AVDD should be wellregulated and low noise. Switching power supplies and dc-dc converters often have high-frequency glitches or spikes riding on the output voltage. In addition, digital components can create similar high-frequency spikes as their internal logic switches states. This noise can easily couple into the DAC output voltage through various paths between the power connections and analog output. As with the GND connection, AVDD should be connected to a power-supply plane or trace that is separate from the connection for digital logic until they are connected at the power-entry point. In addition, a pair of 100-pF to 1-nF capacitors and a 0.1-µF to 1-µF bypass capacitor are strongly recommended. In some situations, additional bypassing may be required, such as a 100 µF electrolytic capacitor or even a pi filter made up of inductors and capacitors - all designed essentially to provide low-pass filtering for the supply and remove the high-frequency noise.

While all the other recommendations apply to most DACs, multiplying DACs also require that the transimpedance amplifier be placed in close proximity in order to minimize non-linearity errors introduced by any resistance between the I<sub>OUT</sub> pin and V- pin of the amplifier.

#### 11.2 Layout Example




Figure 29. DAC8811 Layout Example



# 12 Device and Documentation Support

## 12.1 Documentation Support

#### 12.1.1 Related Documentation

For related documentation see the following:

- DAC8801/11EVM, SLAU151
- Interfacing the DAC8811 to the MSP430F449, SLAA238
- Topology and Noise Using Multiplying DAC, SBAA146

#### 12.2 Community Resources

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™ Online Community TI's Engineer-to-Engineer (E2E) Community. Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

**Design Support** *TI's Design Support* Quickly find helpful E2E forums along with design support tools and contact information for technical support.

#### 12.3 Trademarks

E2E is a trademark of Texas Instruments.

All other trademarks are the property of their respective owners.

# 12.4 Electrostatic Discharge Caution



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

# 12.5 Glossary

SLYZ022 — TI Glossary.

This glossary lists and explains terms, acronyms, and definitions.

# 13 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

10-Nov-2025

www.ti.com

#### PACKAGING INFORMATION

Orderable part number	Status (1)	Material type	Package   Pins	Package qty   Carrier	<b>RoHS</b> (3)	Lead finish/ Ball material	MSL rating/ Peak reflow	Op temp (°C)	Part marking (6)
DAC8811IBDGKR	Active	Production	VSSOP (DGK)   8	2500   LARGE T&R	Yes	NIPDAUAG   SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811IBDGKR.A	Active	Production	VSSOP (DGK)   8	2500   LARGE T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811IBDGKT	Active	Production	VSSOP (DGK)   8	250   SMALL T&R	Yes	NIPDAUAG   SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811IBDGKT.A	Active	Production	VSSOP (DGK)   8	250   SMALL T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811IBDGKTG4	Active	Production	VSSOP (DGK)   8	250   SMALL T&R	Yes	NIPDAUAG	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811IBDGKTG4.A	Active	Production	VSSOP (DGK)   8	250   SMALL T&R	Yes	NIPDAUAG	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811IBDRBT	Active	Production	SON (DRB)   8	250   SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811IBDRBT.A	Active	Production	SON (DRB)   8	250   SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDGKR	Active	Production	VSSOP (DGK)   8	2500   LARGE T&R	Yes	NIPDAUAG   SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDGKR.A	Active	Production	VSSOP (DGK)   8	2500   LARGE T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDGKT	Active	Production	VSSOP (DGK)   8	250   SMALL T&R	Yes	NIPDAUAG   SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDGKT.A	Active	Production	VSSOP (DGK)   8	250   SMALL T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDRBT	Active	Production	SON (DRB)   8	250   SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDRBT.A	Active	Production	SON (DRB)   8	250   SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDRBTG4	Active	Production	SON (DRB)   8	250   SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	D11
DAC8811ICDRBTG4.A	Active	Production	SON (DRB)   8	250   SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	D11

<sup>(1)</sup> Status: For more details on status, see our product life cycle.

<sup>(2)</sup> Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

<sup>(3)</sup> RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

<sup>(4)</sup> Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

<sup>(5)</sup> MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.



# **PACKAGE OPTION ADDENDUM**

www.ti.com 10-Nov-2025

(6) Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



www.ti.com 12-Aug-2025

## TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

#### QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



#### \*All dimensions are nominal

Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
DAC8811IBDGKR	VSSOP	DGK	8	2500	330.0	12.4	5.25	3.35	1.25	8.0	12.0	Q1
DAC8811IBDGKT	VSSOP	DGK	8	250	330.0	12.4	5.25	3.35	1.25	8.0	12.0	Q1
DAC8811IBDGKTG4	VSSOP	DGK	8	250	330.0	12.4	5.3	3.4	1.4	8.0	12.0	Q1
DAC8811IBDRBT	SON	DRB	8	250	180.0	12.4	3.3	3.3	1.1	8.0	12.0	Q2
DAC8811ICDGKR	VSSOP	DGK	8	2500	330.0	12.4	5.25	3.35	1.25	8.0	12.0	Q1
DAC8811ICDGKT	VSSOP	DGK	8	250	330.0	12.4	5.25	3.35	1.25	8.0	12.0	Q1
DAC8811ICDRBT	SON	DRB	8	250	180.0	12.4	3.3	3.3	1.1	8.0	12.0	Q2
DAC8811ICDRBTG4	SON	DRB	8	250	180.0	12.4	3.3	3.3	1.1	8.0	12.0	Q2



www.ti.com 12-Aug-2025



\*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
DAC8811IBDGKR	VSSOP	DGK	8	2500	366.0	364.0	50.0
DAC8811IBDGKT	VSSOP	DGK	8	250	366.0	364.0	50.0
DAC8811IBDGKTG4	VSSOP	DGK	8	250	366.0	364.0	50.0
DAC8811IBDRBT	SON	DRB	8	250	210.0	185.0	35.0
DAC8811ICDGKR	VSSOP	DGK	8	2500	366.0	364.0	50.0
DAC8811ICDGKT	VSSOP	DGK	8	250	366.0	364.0	50.0
DAC8811ICDRBT	SON	DRB	8	250	210.0	185.0	35.0
DAC8811ICDRBTG4	SON	DRB	8	250	210.0	185.0	35.0



SMALL OUTLINE PACKAGE



#### NOTES:

PowerPAD is a trademark of Texas Instruments.

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.

  2. This drawing is subject to change without notice.

  3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not
- exceed 0.15 mm per side.
- 4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
- 5. Reference JEDEC registration MO-187.



SMALL OUTLINE PACKAGE



NOTES: (continued)

- 6. Publication IPC-7351 may have alternate designs.
- 7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.
- 8. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.
- 9. Size of metal pad may vary due to creepage requirement.



SMALL OUTLINE PACKAGE



NOTES: (continued)

- 11. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
- 12. Board assembly site may have different recommendations for stencil design.





Images above are just a representation of the package family, actual package may vary. Refer to the product data sheet for package details.

4203482/L





PLASTIC SMALL OUTLINE - NO LEAD



#### NOTES:

- All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
- 2. This drawing is subject to change without notice.
- 3. The package thermal pad must be soldered to the printed circuit board for thermal and mechanical performance.



PLASTIC SMALL OUTLINE - NO LEAD



NOTES: (continued)

- 4. This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).
- 5. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.



PLASTIC SMALL OUTLINE - NO LEAD



NOTES: (continued)

6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.



#### IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale, TI's General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025