











DSLVDS1047

SNLS623-SEPTEMBER 2018

DSLVDS1047 3.3-V LVDS Quad Channel High-Speed Differential Line Driver

Features

- Designed for Signaling Rates up to 400-Mbps
- 3.3-V Power Supply Design
- 300-ps Typical Differential Skew
- 400-ps Maximum Differential Skew
- 1.7-ns Maximum Propagation Delay
- ±350-mV Differential Signaling
- Low Power Dissipation (13 mW at 3.3-V Static)
- Interoperable With Existing 5-V LVDS Receivers
- High impedance on LVDS Outputs on Power
- Flow-Through Pinout Simplifies PCB Layout
- Meets or Exceeds TIA/EIA-644 LVDS Standard
- Industrial Operating Temperature Range $(-40^{\circ}\text{C to } +85^{\circ}\text{C})$
- Available in TSSOP Package

Applications

- Multifunction Printers
- **Board-to-Board Communication**
- Test and Measurement
- **Printers**
- **Data Center Interconnect**
- Lab Instrumentation
- **Ultrasound Scanners**

3 Description

The DSLVDS1047 device is a quad CMOS flowdifferential line driver designed applications requiring ultra-low power dissipation and high data rates. The device is designed to support data rates in excess of 400 Mbps (200 MHz) using Differential Signaling technology.

The DSLVDS1047 accepts low voltage TTL/CMOS input levels and translates them to low voltage (350 mV) differential output signals. In addition, the driver supports a TRI-STATE function that may be used to disable the output stage, disabling the load current, and thus dropping the device to an ultra low idle power state of 13 mW typical. The DSLVDS1047 has a flow-through pinout for easy PCB layout.


The EN and EN* inputs are ANDed together and control the TRI-STATE outputs. The enables are common to all four drivers. The and companion line receiver (DSLVDS1048) provide a new alternative to high power psuedo-ECL devices for high speed pointto-point interface applications.

Device Information(1)

PART NUMBER	PACKAGE	BODY SIZE (NOM)
DSLVDS1047	TSSOP (16)	5.00 mm × 4.40 mm

(1) For all available packages, see the orderable addendum at the end of the data sheet.

Figure 1. Application Diagram



SNLS623 – SEPTEMBER 2018 www.ti.com



Table of Contents

1	Features 1		8.3 Feature Description	
2	Applications 1		8.4 Device Functional Modes	
3	Description 1	9	Application and Implementation	. 15
4	Revision History 2		9.1 Application Information	. 15
5	Pin Configuration and Functions 3		9.2 Typical Application	. 15
6	Specifications4	10	Power Supply Recommendations	. 18
	6.1 Absolute Maximum Ratings 4	11	Layout	. 18
	6.2 ESD Ratings		11.1 Layout Guidelines	. 18
	6.3 Recommended Operating Conditions		11.2 Layout Example	. 19
	6.4 Thermal Information	12	Device and Documentation Support	. 20
	6.5 Electrical Characteristics5		12.1 Receiving Notification of Documentation Updates	s <mark>2</mark> 0
	6.6 Switching Characteristics 6		12.2 Community Resources	. 20
	6.7 Typical Characteristics		12.3 Trademarks	. 20
7	Parameter Measurement Information9		12.4 Electrostatic Discharge Caution	. 20
8	Detailed Description 12		12.5 Glossary	. 20
•	8.1 Overview 12	13	Mechanical, Packaging, and Orderable Information	21
	8.2 Functional Block Diagram 13		IIIOIIIIauoii	. 2

4 Revision History


NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

DATE	REVISION	NOTES
September 2018	*	Initial release.

Submit Documentation Feedback

Copyright © 2018, Texas Instruments Incorporated

5 Pin Configuration and Functions



Pin Functions

	PIN	1/0	DESCRIPTION
NO.	NAME	1/0	DESCRIPTION
2	D _{IN1}		
3	D _{IN2}		Driver input his TTI /CMOS competible
6	D _{IN3}	'	Driver input pin, TTL/CMOS compatible
7	D _{IN4}		
10	D _{OUT4+}		
11	D _{OUT3+}	0	Non-investing driver output his LVDC levels
14	D _{OUT2+}		Non-inverting driver output pin, LVDS levels
15	D _{OUT1+}		
9	D _{OUT4} -		
12	D _{OUT3} -	0	Investiga driver output pin LVDC lovele
13	D _{OUT2} -		Inverting driver output pin, LVDS levels
16	D _{OUT1} -		
1	EN	1	Driver enable pin: When EN is low, the driver is disabled. When EN is high and EN* is low or open, the driver is enabled. If both EN and EN* are open circuit, then the driver is disabled.
8	EN*	I	Driver enable pin: When EN* is high, the driver is disabled. When EN* is low or open and EN is high, the driver is enabled. If both EN and EN* are open circuit, then the driver is disabled.
5	GND	_	Ground pin
4	V _{CC}	_	Power supply pin, +3.3 V ± 0.3 V

Copyright © 2018, Texas Instruments Incorporated

TEXAS INSTRUMENTS

6 Specifications

6.1 Absolute Maximum Ratings

See (1)

			MIN	MAX	UNIT	
Supply voltage (V _{CC})		-0.3	4	V		
Input voltage (D _{IN})			-0.3	$V_{CC} + 0.3$	٧	
Enable input voltage (EN, E	EN*)		-0.3	$V_{CC} + 0.3$	٧	
Output voltage (D _{OUT+} , D _{OU}	υT_)		-0.3	3.9	V	
Short-circuit duration	(D _{OUT+} , D _{OUT-})		Cont	Continuous		
Maximum package power	PW0016A package	PW0016A package		866	mW	
dissipation at +25°C	Derate PW0016A package	above +25°C		6.9	mW/°C	
Lead temperature	Soldering (4 s)			260	°C	
Maximum junction tempera	ture		150	°C		
Storage temperature, T _{stg}			-65	150	°C	

⁽¹⁾ Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under Recommended Operating Conditions. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

6.2 ESD Ratings

		VALUE	UNIT
	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001 (2)	±1200	
V _(ESD)	Charged-device model (CDM), per JEDEC specification JESD22-C101 ⁽³⁾	±200	V
	Machine Model	±1200	

⁽¹⁾ ESD Ratings:

HBM (1.5 k Ω , 100 pF) EIAJ (0 Ω , 200 pF)

- (2) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
- (3) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

	MIN	NOM	MAX	UNIT
Supply voltage, V _{CC}	3	3.3	3.6	V
Operating free air temperature, T _A	-40	25	85	ů

6.4 Thermal Information

		DSLVDS1047	
	THERMAL METRIC ⁽¹⁾	PW (TSSOP)	UNIT
		16 PINS	
$R_{\theta JA}$	Junction-to-ambient thermal resistance	114	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	51	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	59	°C/W
ΨЈТ	Junction-to-top characterization parameter	8	°C/W
ΨЈВ	Junction-to-board characterization parameter	58	°C/W

 For more information about traditional and new thermal metrics, see the Semiconductor and IC Package Thermal Metrics application report.

6.5 Electrical Characteristics

Over supply voltage and operating temperature ranges, unless otherwise specified (1)(2)(3)

	PARAMETER	TEST CONDITIONS	PIN	MIN	TYP	MAX	UNIT
V_{OD1}	Differential output voltage			250	310	450	mV
ΔV_{OD1}	Change in magnitude of V _{OD1} for complementary output states				1	35	mV
Vos	Offset voltage	$R_1 = 100 \Omega$ (Figure 18)	D _{OUT} -	1.125	1.17	1.375	V
ΔV _{OS}	Change in magnitude of V _{OS} for complementary output states	K _L = 100 ½ (Figure 10)	D _{OUT+}		1	25	mV
V _{OH}	Output high voltage				1.33	1.6	V
V _{OL}	Output low voltage			0.9	1.02		V
V_{IH}	Input high voltage			2		V_{CC}	V
V _{IL}	Input low voltage		D _{IN} ,	GND		0.8	V
I _{IH}	Input high current	V _{IN} = V _{CC} or 2.5 V	EÑ,		2	15	μΑ
I _{IL}	Input low current	V _{IN} = GND or 0.4 V	EN*		2	15	μΑ
V_{CL}	Input clamp voltage	I _{CL} = −18 mA		-1.5	-0.8		V
Ios	Output short-circuit current ⁽⁴⁾	ENABLED, D _{IN} = V _{CC} , D _{OUT+} = 0 V or D _{IN} = GND, D _{OUT-} = 0 V			-4	-8	mA
I _{OSD}	Differential output short-circuit current ⁽⁴⁾	ENABLED, V _{OD} = 0 V	D _{OUT} -		-4.2	-9	mA
I _{OFF}	Power-off leakage	$V_{OUT} = 0 \text{ V or } 3.6 \text{ V}, V_{CC} = 0 \text{ V or } 0$	D _{OUT+} -20		±1	20	μΑ
I _{OZ}	Output TRI-STATE current	EN = 0.8 V and EN* = 2.0 V V _{OUT} = 0 V or V _{CC}		-10	±1	10	μΑ
I _{CC}	No load supply current drivers enabled	D _{IN} = V _{CC} or GND			4	8	mA
I _{CCL}	Loaded supply current drivers enabled	R_L = 100 Ω all channels, D_{IN} = V_{CC} or GND (all inputs)	V _{CC}		20	30	mA
I _{CCZ}	No load supply current drivers disabled	$D_{IN} = V_{CC}$ or GND, EN = GND, EN* = V_{CC}			2.2	6	mA

Current into device pins is defined as positive. Current out of device pins is defined as negative. All voltages are referenced to ground except: V_{OD1} and ΔV_{OD1}.
 All typicals are given for: V_{CC} = 3.3 V, T_A = +25°C.
 The DSLVDS1047 is a current mode device and only functions within datasheet specifications when a resistive load is applied to the

driver outputs typical range is (90 Ω to 110 Ω).

⁽⁴⁾ Output short circuit current (I_{OS}) is specified as magnitude only, minus sign indicates direction only.

ISTRUMENTS

6.6 Switching Characteristics


 $V_{CC} = +3.3V \pm 10\%$, $T_A = -40^{\circ}C$ to $+85^{\circ}C^{(1)(2)(3)}$

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
t _{PHLD}	Differential propagation delay high to low		0.5	0.9	1.7	ns
t _{PLHD}	Differential propagation delay low to high		0.5	1.2	1.7	ns
t _{SKD1}	Differential pulse skew t _{PHLD} - t _{PLHD} ⁽⁴⁾	B 400 0 C 45 pF		0.3	0.4	ns
t _{SKD2}	Channel-to-channel skew ⁽⁵⁾	$R_L = 100 \Omega$, $C_L = 15 pF$ (Figure 19 and Figure 20)		0.4	0.5	ns
t _{SKD3}	Differential part-to-part skew ⁽⁶⁾		0		1	ns
t _{SKD4}	Differential part-to-part skew ⁽⁷⁾		0		1.2	ns
t _{TLH}	Rise time			0.5	1.5	ns
t _{THL}	Fall time			0.5	1.5	ns
t _{PHZ}	Disable time high to Z			2	5	ns
t _{PLZ}	Disable time low to Z	$R_L = 100 \Omega, C_L = 15 pF$		2	5	ns
t _{PZH}	Enable time Z to high	(Figure 21 and Figure 22)		3	7	ns
t _{PZL}	Enable time Z to low			3	7	ns
f _{MAX}	Maximum operating frequency (8)		200	250		MHz

- All typicals are given for: $V_{CC}=3.3~V,~T_A=+25^{\circ}C.$ Generator waveform for all tests unless otherwise specified: f = 1 MHz, $Z_O=50~\Omega,~t_f\leq 1~ns.$
- C₁ includes probe and jig capacitance.
- t_{SKD1} $|t_{PHLD} t_{PLHD}|$ is the magnitude difference in differential propagation delay time between the positive going edge and the negative going edge of the same channel.
- t_{SKD2} is the differential channel-to-channel skew of any event on the same device.
- t_{SKD3} , differential part-to-part skew, is defined as the difference between the minimum and maximum specified differential propagation delays. This specification applies to devices at the same V_{CC} and within 5°C of each other within the operating temperature range.
- t_{SKD4}, part to part skew, is the differential channel-to-channel skew of any event between devices. This specification applies to devices over recommended operating temperature and voltage ranges, and across process distribution. t_{SKD4} is defined as |Max - Min| differential propagation delay.
- f_{MAX} generator input conditions: $t_r = t_f < 1$ ns (0% to 100%), 50% duty cycle, 0 V to 3 V. Output criteria: duty cycle = 45% / 55%, VOD > 250 mV, all channels switching.




6.7 Typical Characteristics




TEXAS INSTRUMENTS

Typical Characteristics (continued)



Ambient Temperature

Typical Characteristics (continued)



7 Parameter Measurement Information




Figure 18. Driver V_{OD} and V_{OS} Test Circuit

Copyright © 2018, Texas Instruments Incorporated

Parameter Measurement Information (continued)




Figure 19. Driver Propagation Delay and Transition Time Test Circuit




Figure 20. Driver Propagation Delay and Transition Time Waveforms




Figure 21. Driver TRI-STATE Delay Test Circuit



Parameter Measurement Information (continued)




Figure 22. Driver TRI-STATE Delay Waveform

SNLS623 – SEPTEMBER 2018 www.ti.com

TEXAS INSTRUMENTS

8 Detailed Description

8.1 Overview

LVDS drivers and receivers are intended to be primarily used in an uncomplicated point-to-point configuration as is shown in Figure 24. This configuration provides a clean signaling environment for the fast edge rates of the drivers. The receiver is connected to the driver through a balanced media which may be a standard twisted pair cable, a parallel pair cable, or simply PCB traces. Typically, the characteristic differential impedance of the media is in the range of 100 Ω . A termination resistor of 100 Ω (selected to match the media), and is located as close to the receiver input pins as possible. The termination resistor converts the driver output current (current mode) into a voltage that is detected by the receiver. Other configurations are possible such as a multi-receiver configuration, but the effects of a mid-stream connector(s), cable stub(s), and other impedance discontinuities as well as ground shifting, noise margin limits, and total termination loading must be taken into account.

The DSLVDS1047 differential line driver is a balanced current source design. A current mode driver, generally speaking has a high output impedance and supplies a constant current for a range of loads (a voltage mode driver on the other hand supplies a constant voltage for a range of loads). Current is switched through the load in one direction to produce a logic state and in the other direction to produce the other logic state. The output current is typically 3.1 mA, a minimum of 2.5 mA, and a maximum of 4.5 mA. The current mode driver requires that a resistive termination be employed to terminate the signal and to complete the loop as shown in Figure 24. AC or unterminated configurations are not allowed. The 3.1-mA loop current develops a differential voltage of 310 mV across the $100-\Omega$ termination resistor which the receiver detects with a 250-mV minimum differential noise margin, (driven signal minus receiver threshold (250 mV - 100 mV = 150 mV). The signal is centered around +1.2 V (Driver Offset, V_{OS}) with respect to ground as shown in Figure 23.


NOTE

The steady-state voltage (V_{SS}) peak-to-peak swing is twice the differential voltage (V_{OD}) and is typically 620 mV.

The current mode driver provides substantial benefits over voltage mode drivers, such as an RS-422 driver. Its quiescent current remains relatively flat versus switching frequency. Whereas the RS-422 voltage mode driver increases exponentially in most case from 20 MHz to 50 MHz. This is due to the overlap current that flows between the rails of the device when the internal gates switch. Whereas the current mode driver switches a fixed current between its output without any substantial overlap current. This is similar to some ECL and PECL devices, but without the heavy static I_{CC} requirements of the ECL/PECL designs. LVDS requires > 80% less current than similar PECL devices. AC specifications for the driver are a tenfold improvement over other existing RS-422 drivers.

The TRI-STATE function allows the driver outputs to be disabled, thus obtaining an even lower power state when the transmission of data is not required.

8.2 Functional Block Diagram



8.3 Feature Description

8.3.1 LVDS Fail-Safe

This section addresses the common concern of fail-safe biasing of LVDS interconnects, specifically looking at the DSLVDS1047 driver outputs and the DSLVDS1048 receiver inputs.

The LVDS receiver is a high-gain, high-speed device that amplifies a small differential signal (20 mV) to CMOS logic levels. Due to the high gain and tight threshold of the receiver, take care to prevent noise from appearing as a valid signal.

The internal fail-safe circuitry of the receiver is designed to source or sink a small amount of current, providing fail-safe protection (a stable known state of HIGH output voltage) for floating, terminated, or shorted receiver inputs.

- 1. **Open Input Pins.** The DSLVDS1048 is a quad receiver device, and if an application requires only 1, 2, or 3 receivers, the unused channel(s) inputs must be left OPEN. Do not tie unused receiver inputs to ground or any other voltages. The input is biased by internal high value pullup and pulldown resistors to set the output to a HIGH state. This internal circuitry ensures a HIGH, stable output state for open inputs.
- 2. **Terminated Input.** If the DSLVDS1047 driver is disconnected (cable unplugged), or if the DSLVDS1047 driver is in a TRI-STATE or power-off condition, the receiver output is again in a HIGH state, even with the end of cable 100-Ω termination resistor across the input pins. The unplugged cable can become a floating antenna which can pick up noise. If the cable picks up more than 10 mV of differential noise, the receiver may see the noise as a valid signal and switch. To insure that any noise is seen as common-mode and not differential, a balanced interconnect must be used. Twisted pair cable offers better balance than flat ribbon cable.
- 3. **Shorted Inputs.** If a fault condition occurs that shorts the receiver inputs together, thus resulting in a 0-V differential input voltage, the receiver output remains in a HIGH state. Shorted input fail-safe is not supported across the common-mode range of the device (GND to 2.4 V). It is only supported with inputs shorted and no external common-mode voltage applied.

SNLS623 – SEPTEMBER 2018 www.ti.com

Feature Description (continued)

External lower value pullup and pulldown resistors (for a stronger bias) may be used to boost fail-safe in the presence of higher noise levels. The pullup and pulldown resistors should be in the $5-k\Omega$ to $15-k\Omega$ range to minimize loading and waveform distortion to the driver. The common-mode bias point should be set to approximately 1.2 V (less than 1.75 V) to be compatible with the internal circuitry.




Figure 23. Driver Output Levels

8.4 Device Functional Modes

Table 1 lists the functional modes DSLVDS1047.

Table 1. Truth Table

	ENABLES	INPUT	ОИТІ	PUTS
EN EN*		D _{IN}	D _{OUT+}	D _{OUT} -
	1 0	L	L	Н
П	L or Open	Н	Н	L
All other comb	pinations of ENABLE inputs	Х	Z	Z

Application and Implementation

NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

9.1 Application Information

The DSLVDS1047 has a flow-through pinout that allows for easy PCB layout. The LVDS signals on one side of the device easily allows for matching electrical lengths of the differential pair trace lines between the driver and the receiver as well as allowing the trace lines to be close together to couple noise as common-mode. Noise isolation is achieved with the LVDS signals on one side of the device and the TTL signals on the other side.

9.2 Typical Application




Figure 24. Point-to-Point Application

Copyright © 2018, Texas Instruments Incorporated

TEXAS INSTRUMENTS

Typical Application (continued)

9.2.1 Design Requirements

When using LVDS devices, it is important to remember to specify controlled impedance PCB traces, cable assemblies, and connectors. All components of the transmission media should have a matched differential impedance of about 100Ω . They should not introduce major impedance discontinuities.

Balanced cables (for example, twisted pair) are usually better than unbalanced cables (ribbon cable) for noise reduction and signal quality. Balanced cables tend to generate less EMI due to field canceling effects and also tend to pick up electromagnetic radiation as common-mode (not differential mode) noise which is rejected by the LVDS receiver.

For cable distances < 0.5 M, most cables can be made to work effectively. For distances 0.5 M \leq d \leq 10 M, CAT5 (Category 5) twisted pair cable works well, is readily available and relatively inexpensive.

DESIGN PARAMETERS	EXAMPLE VALUE			
Driver Supply Voltage (V _{CC})	3.0 to 3.6 V			
Driver Input Voltage	0 to 3.6 V			
Driver Signaling Rate	DC to 400 Mbps			
Interconnect Characteristic Impedance	100 Ω			
Termination Resistance	100 Ω			
Number of Receiver Nodes	1			
Ground shift between driver and receiver	±1 V			

Table 2. Design Requirements

9.2.2 Detailed Design Procedure

9.2.2.1 Probing LVDS Transmission Lines

Always use high impedance (> 100 k Ω), low capacitance (< 2 pF) scope probes with a wide bandwidth (1 GHz) scope. Improper probing gives deceiving results.

9.2.2.2 Data Rate vs Cable Length Graph Test Procedure

A pseudo-random bit sequence (PRBS) of 2^9-1 bits was programmed into a function generator (Tektronix HFS9009) and connected to the driver inputs through $50-\Omega$ cables and SMB connectors. An oscilloscope (Tektronix 11801B) was used to probe the resulting eye pattern, measured differentially at the input to the receiver. A $100-\Omega$ resistor was used to terminate the pair at the far end of the cable. The measurements were taken at the far end of the cable, at the input of the receiver, and used for the jitter analysis for this graph (Figure 17). The frequency of the input signal was increased until the measured jitter (t_{tcs}) equaled 20% with respect to the unit interval (t_{tui}) for the particular cable length under test. Twenty percent jitter is a reasonable place to start with many system designs. The data used was NRZ. Jitter was measured at the 0-V differential voltage of the differential eye pattern. The DSLVDS1047 and DSLVDS1048 can be evaluated using the new DS90LV047-048AEVM.

Figure 25 shows very good typical performance that can be used as a design guideline for data rate vs cable length. Increasing the jitter percentage increases the curve respectively, allowing the device to transmit faster over longer cable lengths. This relaxes the jitter tolerance of the system allowing more jitter into the system, which could reduce the reliability and efficiency of the system. Alternatively, decreasing the jitter percentage has the opposite effect on the system. The area under the curve is considered the safe operating area based on the above signal quality criteria. For more information on eye pattern testing, please see *AN-808 Long Transmission Lines and Data Signal Quality* (SNLA028).



9.2.3 Application Curve




Figure 25. Power Supply Current vs Frequency

SNLS623 – SEPTEMBER 2018 www.ti.com

TEXAS INSTRUMENTS

10 Power Supply Recommendations

Although the DSLVDS1047 draws very little power while at rest. At higher switching frequencies there is a dynamic current component which increases the overall power consumption. The DSLVDS1047 power supply connection must take this additional current consumption into consideration for maximum power requirements.

11 Layout

11.1 Layout Guidelines

- Use at least 4 PCB layers (top to bottom); LVDS signals, ground, power, TTL signals.
- Isolate TTL signals from LVDS signals, otherwise the TTL may couple onto the LVDS lines. It is best to put TTL and LVDS signals on different layers which are isolated by a power/ground plane(s).
- Keep drivers and receivers as close to the (LVDS port side) connectors as possible.


11.1.1 Power Decoupling Recommendations

Bypass capacitors must be used on power pins. Use high frequency ceramic (surface mount is recommended) 0.1- μ F and 0.001- μ F capacitors in parallel at the power supply pin with the smallest value capacitor closest to the device supply pin. Additional scattered capacitors over the printed-circuit board improves decoupling. Multiple vias must be used to connect the decoupling capacitors to the power planes. A 10- μ F (35-V) or greater solid tantalum capacitor must be connected at the power entry point on the printed-circuit board between the supply and ground.

11.1.2 Differential Traces

Use controlled impedance traces which match the differential impedance of your transmission medium (that is, cable) and termination resistor. Run the differential pair trace lines as close together as possible as soon as they leave the IC (stubs must be < 10 mm long). This helps eliminate reflections and ensure noise is coupled as common-mode. In fact, we have seen that differential signals which are 1 mm apart radiate far less noise than traces 3 mm apart since magnetic field cancellation is much better with the closer traces. In addition, noise induced on the differential lines is much more likely to appear as common-mode which is rejected by the receiver.

Match electrical lengths between traces to reduce skew. Skew between the signals of a pair means a phase difference between signals, which destroys the magnetic field cancellation benefits of differential signals and EMI, results.



Do not rely solely on the autoroute function for differential traces. Carefully review dimensions to match differential impedance and provide isolation for the differential lines. Minimize the number or vias and other discontinuities on the line.

Avoid 90° turns (these cause impedance discontinuities). Use arcs or 45° bevels.

Within a pair of traces, the distance between the two traces must be minimized to maintain common-mode rejection of the receivers. On the printed-circuit board, this distance must remain constant to avoid discontinuities in differential impedance. Minor violations at connection points are allowable.

11.1.3 Termination

Use a termination resistor which best matches the differential impedance or your transmission line. The resistor must be between 90 Ω and 130 Ω . Remember that the current mode outputs need the termination resistor to generate the differential voltage. LVDS does not work without resistor termination. Typically, connecting a single resistor across the pair at the receiver end will suffice.



Layout Guidelines (continued)

Surface mount 1% to 2% resistors are best. PCB stubs, component lead, and the distance from the termination to the receiver inputs must be minimized. The distance between the termination resistor and the receiver should be < 10 mm (12 mm maximum).

11.2 Layout Example




Figure 26. Layout Recommendation

TEXAS INSTRUMENTS

12 Device and Documentation Support

12.1 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. In the upper right corner, click on *Alert me* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

12.2 Community Resources

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™ Online Community TI's Engineer-to-Engineer (E2E) Community. Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

Design Support *TI's Design Support* Quickly find helpful E2E forums along with design support tools and contact information for technical support.

12.3 Trademarks

E2E is a trademark of Texas Instruments.

All other trademarks are the property of their respective owners.

12.4 Electrostatic Discharge Caution



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

12.5 Glossary

SLYZ022 — TI Glossary.

This glossary lists and explains terms, acronyms, and definitions.

20



13 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

www.ti.com 10-Nov-2025

PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS (3)	Lead finish/ Ball material	MSL rating/ Peak reflow	Op temp (°C)	Part marking (6)
DSLVDS1047PWR	Active	Production	TSSOP (PW) 16	2500 LARGE T&R	Yes	SN	Level-1-260C-UNLIM	-40 to 85	DSLVDS 1047
DSLVDS1047PWR.B	Active	Production	TSSOP (PW) 16	2500 LARGE T&R	Yes	SN	Level-1-260C-UNLIM	-40 to 85	DSLVDS 1047
DSLVDS1047PWT	Active	Production	TSSOP (PW) 16	250 SMALL T&R	Yes	SN	Level-1-260C-UNLIM	-40 to 85	DSLVDS 1047
DSLVDS1047PWT.B	Active	Production	TSSOP (PW) 16	250 SMALL T&R	Yes	SN	Level-1-260C-UNLIM	-40 to 85	DSLVDS 1047

⁽¹⁾ Status: For more details on status, see our product life cycle.

- (3) RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.
- (4) Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.
- (5) MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.
- (6) Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.



PACKAGE OPTION ADDENDUM

www.ti.com 10-Nov-2025

PACKAGE MATERIALS INFORMATION

www.ti.com 1-Aug-2025

TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
DSLVDS1047PWR	TSSOP	PW	16	2500	330.0	12.4	6.95	5.6	1.6	8.0	12.0	Q1
DSLVDS1047PWT	TSSOP	PW	16	250	177.8	12.4	6.95	5.6	1.6	8.0	12.0	Q1

www.ti.com 1-Aug-2025



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
DSLVDS1047PWR	TSSOP	PW	16	2500	367.0	367.0	35.0
DSLVDS1047PWT	TSSOP	PW	16	250	210.0	185.0	35.0



SMALL OUTLINE PACKAGE



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.

 2. This drawing is subject to change without notice.

 3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not
- exceed 0.15 mm per side.
- 4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
- 5. Reference JEDEC registration MO-153.



SMALL OUTLINE PACKAGE



NOTES: (continued)

- 6. Publication IPC-7351 may have alternate designs.
- 7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SMALL OUTLINE PACKAGE



NOTES: (continued)

- 8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
- 9. Board assembly site may have different recommendations for stencil design.



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale, TI's General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025