













LM5141-Q1

SNVSAJ6D - JULY 2016-REVISED DECEMBER 2017

LM5141-Q1 Wide Input Range Synchronous Buck Controller

Features

- **Qualified for Automotive Applications**
- AEC-Q100 Qualified With the Following Results:
 - Device Temperature Grade 1: -40°C to +125°C Ambient Operating Temperature
 - Device HBM ESD Classification Level 2
 - Device CDM ESD Classification Level C4B
- V_{IN}: 3.8 V to 65 V (70 V Absolute Maximum)
- Output: Fixed 3.3 V, 5 V, or Adjustable From 1.5 V to 15 V with ±0.8% Accuracy
- Fixed 2.2-MHz or 440-kHz Switching Frequency with ±5% Accuracy
- High-Side and Low-Side Gate Drive With Slew-Rate Control
- Optional Frequency Shift by Varying an Analog Voltage or RT Resistor
- Optional Synchronization to an External Clock
- Optional Spread Spectrum
- Shutdown Mode I_Q : 10 μA Typical
- Low Standby Mode Io: 35 µA Typical
- 75-mV Current Limit Threshold with ±0.9% Accuracy
- External Resistor or DCR Current Sensing
- Output Enable Logic Input
- Hiccup Mode for Sustained Overload
- **Power-Good Indication Output**
- Selectable Diode Emulation or Forced Pulse-Width Modulation
- 24-pin VQFN Package With Wettable Flanks
- Create a Custom Design Using the LM5141-Q1 With the WEBENCH® Power Designer

2 Applications

- Automotive Applications Including:
 - Infotainment Systems
 - Instrumentation Clusters
 - Advanced Driver Assistance Systems (ADAS)

3 Description

The LM5141-Q1 is a synchronous buck controller, intended for high voltage wide V_{IN} step-down converter applications. The control method is peak current mode control. Current mode control provides inherent line feed-forward, cycle-by-cycle current and ease-of-loop compensation. LM5141-Q1 features slew rate control to simplify the compliance with CISPR and automotive EMI requirements.

The LM5141-Q1 has two selectable switching frequencies: 2.2 MHz and 440 kHz. Gate drivers with slew rate Control that can be adjusted to reduce EMI.


In light or no-load conditions, the LM5141-Q1 operates in skip cycle mode for improved low power efficiency. The LM5141-Q1 has a high voltage bias regulator with automatic switch-over to an external bias to reduce the I_O current from V_{IN}. Additional features include frequency synchronization, cycle-bycycle current limit, hiccup mode fault protection for sustained overload, and power good output.

Device Information⁽¹⁾

PART NUMBER	PACKAGE	BODY SIZE (NOM)
LM5141-Q1	VQFN (24)	4.00 mm × 4.00 mm

(1) For all available packages, see the orderable addendum at the end of the data sheet.

Simplified Schematic





T	้ล	h	le	of	Co	nte	nts
	ч	_		U I	\mathbf{v}		


1	Features 1		7.3 Feature Description	13
2	Applications 1	8	Application and Implementation	
3	Description 1		8.1 Application Information	
4	Revision History2		8.2 Typical Application	22
5	Pin Configuration and Functions 3	9	Power Supply Recommendations	35
6	Specifications4	10	Layout	
	6.1 Absolute Maximum Ratings 4		10.1 Layout Guidelines	
	6.2 ESD Ratings 5		10.2 Layout Examples	
	6.3 Recommended Operating Conditions 5	11	Device and Documentation Support	
	6.4 Thermal Information		11.1 Custom Design With WEBENCH® Tools	
	6.5 Electrical Characteristics		11.2 Receiving Notification of Documentation Upda	
	6.6 Switching Characteristics 8		11.3 Community Resources	
	6.7 Typical Characteristics9		11.4 Trademarks	
7	Detailed Description 12		11.5 Electrostatic Discharge Caution	
	7.1 Overview	40	11.6 Glossary	39
	7.2 Functional Block Diagram 12	12	Mechanical, Packaging, and Orderable Information	39
	Revision History ges from Revision C (February 2017) to Revision D			Page
Α	dded top navigator icon for TI Design reference design			1
	hanged "CDS18534Q5A" to "CSD18534Q5A" to fix typo			
	hanged "+" to "x" in Equation 56			
	nanged + to x in Equation 56			32
han	nges from Revision B (January 2017) to Revision C			Page
С	hanged the FBD with updates in the CS pin area			12
	pdated I _{STEP} definition in Equation 28			
han	ges from Revision A (July 2016) to Revision B			Page
	dded 'Systems' to the ADAS bullet in Applications			
	hanged Description text From: 'conducted EMI' To: 'EMI'			
С	hanged test conditions for RT parameter from: OSC = VDD	to: OS	C = GND	8
	hanged equation unit From: '0.815 Apk' To: '0.815 A'			
С	hanged equation unit From: '6.41 Apk' To: '6.41 A'			24
	hanged equation unit From: '8.81 Apk' To: '8.81 A'			
	hanged equation unit From: '0.235 A _{RMS} ' To: '0.235 A'			26
	hanged text From: 'a capacitance value greater than filter ca			
	mes the filter capacitor C _{IN} '			
	hanged equation text From: '6 ² A' and '105 nc' To: '(6A) ² ' and			
Α	dded G _{CS} to equation definition list			31

Changes from Original (July 2016) to Revision A

Page



5 Pin Configuration and Functions



Connect Exposed Pad on bottom to AGND and PGND on the PCB.

Pin Functions

Not to scale

	PIN	TVDE	DESCRIPTION			
NO.	NAME	TYPE	DESCRIPTION			
1	DEMB	I	Diode emulation pin. Connect the DEMB pin to AGND to enable diode emulation. If it is connected to VDDA the LM5141-Q1 operates in forced PWM (FPWM) mode with continuous conduction at light loads. The DEMB pin can also be used as a synchronization input, to synchronize the internal oscillator to an external clock.			
2	VDDA	Р	Internal analog bias regulator output. Connect a capacitor from the VDDA pin to AGND.			
3	AGND	G	Analog ground connection. Ground return for the internal voltage reference and analog circuits.			
4	RT	I	A resistor from the RT pin to ground shifts the oscillator frequency up or down from 2.2 MHz (1.8 MHz to 2.53 MHz), or 440 kHz (300 kHz to 500 kHz). An analog voltage can be applied to the RT pin (through a resistor) to shift the oscillator frequency.			
5	DITH	0	A capacitor connected between the DITH pin and AGND is charged and discharged with a 20 µA current source. If Dither is enabled, the voltage on the DITH pin ramps up and down modulating the oscillator frequency between –5% and +5% of the internal oscillator. Connecting DITH to VDDA disables the dithering feature. DITH is ignored if an external synchronization clock is used.			
6	osc	ı	Frequency selection pin. Connecting the OSC pin to VDDA sets the oscillator frequency to 2.2 MHz. Connecting the OSC pin to AGND sets the frequency to 440 kHz.			
7	LOL	0	Low-side gate driver turnoff output.			
8	LO	0	Low-side gate driver turnon output.			
9	PGND	G	Power ground connection pin for low-side NMOS gate driver.			
10	VCC	Р	VCC bias supply pin. Connect a capacitor from the VCC pin to PGND.			
11	HB	Р	High-side driver supply for bootstrap gate drive.			
12	SW		Switching node of the buck regulator. Connect to the bootstrap capacitor, the source terminal of the high-side MOSFET and the drain terminal of the low-side MOSFET.			
13	НО	0	High-side gate driver turnon output.			
14	HOL	0	High-side gate driver turnoff output.			

Copyright © 2016–2017, Texas Instruments Incorporated



Pin Functions (continued)

PIN		TVDE	DECORPORTION
NO.	NAME	TYPE	DESCRIPTION
15	VIN	Р	Supply voltage input source for the VCC regulator
16	vccx	Р	Optional input for an external bias supply. If VCCX > 4.5 V, VCCX is internally connected to the VCC pin and the internal VCC regulator is disabled. If VCCX is unused, it should be grounded.
17	VOUT	I	Current sense amplifier input. Connect this pin to the output side of the current sense resistor.
18	CS	1	Current sense amplifier input. Make a low current Kelvin connection between this pin and the inductor side of the external current sense resistor.
19	FB	I	Connect the FB pin to VDDA for a fixed 3.3-V output or connect FB to AGND for a fixed 5-V output. Connecting the FB pin to the appropriate output divider network will set the output voltage between 1.5 V and 15 V. The regulation threshold at the FB pin is 1.2 V.
20	COMP	I	Output of the transconductance error amplifier.
21	PG	0	An open collector output which switches low if V _{OUT} is outside of the power good window.
22	SS	I	Soft-start programming pin. An external capacitor and an internal 20-µA current source set the ramp rate of the internal error amplifier reference during soft-start. Pulling SS pin below 80 mV turns-off the gate driver outputs, but all the other functions remain active.
23	EN	1	An active high logic input enables the controller.
24	RES	0	Restart timer pin. An external capacitor configures the hiccup mode current limiting. The capacitor at the RES pin determines the time the controller will remain off before automatically restarting in hiccup mode. The hiccup mode commences when the controller experiences 512 consecutive PWM cycles with cycle-by-cycle current limiting. Connecting the RES pin to VDD during power up disables hiccup mode protection.

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

		MIN	MAX	UNIT
	VIN	-0.3	70	V
	SW to PGND	-0.3	70	V
Input voltage	SW to PGND (20 ns transient)	- 5		V
	HB to SW	-0.3	6.5	V
	HB to SW (20 ns transient)	- 5		V
	HO, HOL to SW	-0.3	HB + 0.3	V
	HO, HOL to SW (20 ns transient)	- 5	- 5	
	LO, LOL to PGND	-0.3	VCC + 0.3	V
	LO, LOL to PGND (20 ns transient)	-1.5		V
	OSC, SS, COMP, RES, DEMB, RT, DITH	-0.3	VDD + 0.3	V
	EN to PGND	-0.3	70	V
	VCC, VCCX, VDD, PG, FB	-0.3	6.5	V
	VOUT, CS	-0.3	15.5	V
PGND to AGND		-0.3	0.3	V
Operating junction temperature (2)	·	-40	150	°C
Storage temperature, T _{stg}	·	-65	150	°C

⁽¹⁾ Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under Recommended Operating Conditions. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

Submit Documentation Feedback

Copyright © 2016–2017, Texas Instruments Incorporated

⁽²⁾ High junction temperatures degrade operating lifetimes. Operating lifetime is de-rated for junction temperatures greater than 125°C.



6.2 ESD Ratings

				VALUE	UNIT
		Human-body model (HBM), per AEC Q100-002 ⁽¹⁾		±2000	
V _(ESD)	Electrostatic discharge	Charged-device model (CDM), per AEC	All pins except 1,6,7,12,13,18,19, and 24	±500	V
(===)		Q100-011	Pins 1,6,7,12,13,18,19, and 24	±750	

⁽¹⁾ AEC Q100-002 indicates that HBM stressing shall be in accordance with the ANSI/ESDA/JEDEC JS-001 specification.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)(1)

			MIN	NOM	MAX	UNIT
		VIN	3.8		65	V
		SW to PGND	-0.3		65	V
		HB to SW	-0.3	5	5.25	V
		HO, HOL to SW	-0.3		HB + 0.3	V
V _{IN}	Input voltage	LO, LOL to PGND	-0.3	5	5.25	V
VIIN	Input voltage	FB, PG, OSC, SS, RES, DEMB, VCCX	-0.3		5	V
		EN to PGND	-0.3		65	V
		VCC, VDD	-0.3	5	5.25	V
		VOUT, CS	1.5	5	15	V
	PGND to AGND		-0.3		0.3	V
	Operating junction temperature (2)		-40		150	°C

⁽¹⁾ Recommended Operating Conditions are conditions under which the device is intended to be functional. For specifications and test conditions, see *Electrical Characteristics*.

6.4 Thermal Information

		LM5141-Q1	
	THERMAL METRIC ⁽¹⁾	RGE (QFN)	UNIT
		24 PINS	
$R_{\theta JA}$	Junction-to-ambient thermal resistance	34.1	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	36.8	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	12.1	°C/W
ΨЈТ	Junction-to-top characterization parameter	0.5	°C/W
ΨЈВ	Junction-to-board characterization parameter	12.2	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	2.9	°C/W

For more information about traditional and new thermal metrics, see the Semiconductor and IC Package Thermal Metrics application report.

Product Folder Links: LM5141-Q1

⁽²⁾ High junction temperatures degrade operating lifetimes. Operating lifetime is de-rated for junction temperatures greater than 125°C.



6.5 Electrical Characteristics

 $T_J = -40^{\circ}\text{C}$ to +125°C, Typical values $T_J = 25^{\circ}\text{C}$, $V_{IN} = 12$ V, VCCX = 5 V, $V_{OUT} = 5$ V, EN = 5 V, OSC = VDD, $F_{SW} = 2.2$ MHz, no-load on the drive outputs (HO, HOL, LO, and LOL outputs), over operating free-air temperature range (unless otherwise noted)⁽¹⁾⁽²⁾

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
VIN SUPPLY	VOLTAGE					
I _{SHUTDOWN}	Shutdown mode current	V _{IN} = 8–18 V, EN = 0 V, VCCX = 0 V		10	12.5	μΑ
	Ctoodhy ourrent	EN = 5 V, FB = VDD, V _{OUT} in regulation, no-load, not switching, DEMB = GND.		35	45	
^I STANDBY	Standby current	EN = 5 V, FB = 0 V, V _{OUT} in regulation, no-load, not switching, VCCX = 5 V, DEMB = GND.		42	55	μΑ
VCC REGUL	ATOR					
VCC _(REG)	VCC regulation voltage	$V_{IN} = 6 \text{ to } 18 \text{ V}, 0 \text{ to } 75 \text{ mA}, \text{ VCCX} = 0 \text{ V}$	4.75	5	5.25	V
VCC _(UVLO)	VCC undervoltage threshold	VCC rising, VCCX = 0 V	3.25	3.4	3.55	V
VCC _(HYST)	VCC hysteresis voltage	VCCX = 0 V		175		mV
I _{CC(LIM)}	VCC sourcing current limit	VCCX = 0 V	85	125		mA
VDDA			1			
VDDA _(REG)	Internal bias supply power	VCCX = 0 V	4.75	5	5.25	V
VDDA _(UVLO)		VCC rising, VCCX = 0 V	3.1	3.2	3.3	V
VDDA _(HYST)		VCCX = 0 V		125		mV
R _{VDDA}		VCCX = 0 V		55		Ω
VCCX			1			
VCCX _(ON)		VCC rising	4.1	4.3	4.4	V
VCCX _(HYST)				80		mV
R _(VCCX)		VCCX = 5 V		2		Ω
OSCILLATO	R SELECT THRESHOLDS		•			
	Oscillator select threshold 2.2 MHz	(OSC pin)	2.0			V
	Oscillator select threshold 440 kHz	(OSC pin)			0.8	V
CURENT LIN	ИІТ				·	
V _(CS)	Current limit threshold	ILSET = VDDA, measure from CS to V _{OUT}	68	75	82	mV
t_{dly}	Current sense delay to output			40		ns
	Current sense amplifier gain		11.4	12	12.6	V/V
ICS _(BIAS)	Amplifier input bias				10	nA
RES						
I _(RES)	RES current source			20		μΑ
V _(RES)	RES threshold			1.2		V
T _{imer}	Timer hiccup mode fault			512		cycles
R _{DS(ON)}	RES pulldown			4		Ω
OUTPUT VO	LTAGE REGULATION					
	3.3 V	V _{IN} = 3.8 to 42 V	3.273	3.3	3.327	V
	5 V	V _{IN} = 5.5 to 42 V	4.96	5.0	5.04	V
FEEDBACK					1	
	V _{OUT} select threshold 3.3 V		VDD - 0.3			V
	Regulated feedback voltage		1.193	1.2	1.207	V

⁽¹⁾ All minimum and maximum limits are specified by correlating the electrical characteristics to process and temperature variations and applying statistical process control.

Submit Documentation Feedback

Copyright © 2016–2017, Texas Instruments Incorporated

⁽²⁾ The junction temperature (T_J in ${}^{\circ}$ C) is calculated from the ambient temperature (T_A in ${}^{\circ}$ C) and power dissipation (P_D in Watts) as follows: $T_J = T_A + (P_D \times R_{\theta,JA})$ where $R_{\theta,JA}$ (in ${}^{\circ}$ C/W) is the package thermal impedance provided in the *Thermal Information* section.



Electrical Characteristics (continued)

 $T_J = -40^{\circ}\text{C}$ to +125°C, Typical values $T_J = 25^{\circ}\text{C}$, $V_{IN} = 12$ V, VCCX = 5 V, $V_{OUT} = 5$ V, EN = 5 V, OSC = VDD, $F_{SW} = 2.2$ MHz, no-load on the drive outputs (HO, HOL, LO, and LOL outputs), over operating free-air temperature range (unless otherwise noted)⁽¹⁾⁽²⁾

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
FB _(LOWRES)	Resistance to ground on FB for FB = 0 detection				500	Ω
FB _(EXTRES)	Thevenin equivalent resistance at FB for external regulation detection	FB < 2 V	5			kΩ
TRANSCON	DUCTANCE AMPLIFIER					
Gm	Gain	Feedback to COMP	1010	1200		μS
	Input bias current				15	nA
	Transconductance amplifier source current	COMP = 1 V, FB = 1 V		100		μΑ
	Transconductance amplifier sink current	COMP = 1 V, FB = 1.4 V		100		μΑ
POWER GO	OD				,	
PG _(UV)	PG undervoltage trip levels	Falling with respect to the regulation voltage	90%	92%	94%	
PG _(OVP)	PG overvoltage trip levels	Rising with respect to the regulation voltage	108%	110%	112%	
PG _(HYST)				3.4%		
PG _(VOL)	PG	Open collector, Isink = 2 mA			0.4	V
PG _(rdly)	OV filter time	V _{OUT} rising		25		μs
PG _(fdly)	UV filter time	V _{OUT} falling		30		μs
HO GATE D	RIVER					
V _{OLH}	HO Low-state output voltage	I _{HO} = 100 mA		0.05		V
V _{OHH}	HO High-state output voltage	$I_{HO} = -100 \text{ mA}, V_{OHH} = V_{HB} - V_{HO}$		0.07		V
t _{rHO}	HO rise time (10% to 90%)	C _{LOAD} = 2700 pf		4		ns
t _{fHO}	HO fall time (90% to 10%)	C _{LOAD} = 2700 pf		3		ns
Іонн	HO peak source current	V _{HO} = 0 V, SW = 0 V, HB = 5 V, VCCX = 5 V		3.25		Apk
I _{OLH}	HO peak sink current	VCCX = 5 V		4.25		Apk
	UVLO	HO falling		2.5		V
$V_{(BOOT)}$	Hysteresis	-		110		mV
I _(BOOT)	Quiescent current			3		μA
LO GATE D		1		-		ı:
V _{OLL}	LO Low-state output voltage	I _{I O} = 100 mA		0.05		V
V _{OHL}	LO High-state output voltage	$I_{LO} = -100 \text{ mA}, V_{OHL} = VCC - V_{LO}$		0.07		V
t _{rLO}	LO rise time (10% to 90%)	C _{LOAD} = 2700 pf		4		ns
t _{fLO}	LO fall time (90% to 10%)	C _{LOAD} = 2700 pf		3		ns
I _{OHL}	LO peak source current	VCCX = 5 V		3.25		Apk
I _{OLL}	LO peak sink current	VCCX = 5 V		4.25		Apk
	DEAD TIME CONTROL			1.20		, ipit
V _(GS-DET)	VGS detection threshold	VGS falling, no load		2.5		V
v(GS-DET) tdly1	HO off to LO on dead time	. Co family, no load		20	40	ns
tdly2	LO off to HO on dead time			20	38	
DIODE EMU				20	30	ns
	DEMB input low threshold				0.8	V
V _{IL}			2		0.8	V
V _{IH}	FPWM input high threshold					
SW	Zero cross threshold			– 5		mV



Electrical Characteristics (continued)

 $T_J = -40$ °C to +125°C, Typical values $T_J = 25$ °C, $V_{IN} = 12$ V, VCCX = 5 V, $V_{OUT} = 5$ V, EN = 5 V, OSC = VDD, $F_{SW} = 2.2$ MHz, no-load on the drive outputs (HO, HOL, LO, and LOL outputs), over operating free-air temperature range (unless otherwise noted)⁽¹⁾⁽²⁾

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
ENABLE II	NPUT		'			
V _{IL}	Enable input low threshold	VCCX = 0 V			0.8	V
V _{IH}	Enable input high threshold	VCCX = 0 V	2.0			V
I _{lkg}	Leakage	EN logic input only		1		μΑ
SYN INPU	Γ (DEMB pin)					
V_{IL}	DEMB input low threshold				8.0	V
V_{IH}	DEMB input high threshold		2			V
	DEMB input low frequency range 440 kHz		350		550	kHz
	DEMB input high frequency range 2.2 MHz		1800		2600	kHz
DITHER			<u> </u>			
I _{DITHER}	Dither source/sink current			20		μΑ
V _{DITHER}	Dither high threshold			1.26		V
	Dither low threshold			1.14		V
SOFT-STA	RT		·			
I _{SS}	Soft-Start current		16	22	28	μΑ
R _{DS(ON)}	Soft-Start pull-down resistance			3		Ω
THERMAL						
	TSD Thermal Shutdown			175		°C
	Thermal shutdown hysteresis			15		°C

6.6 Switching Characteristics

over operating free-air temperature range (unless otherwise noted)

	PARAMET	ER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
	Oscillator Fre	quency 2.2 MHz	OSC = VDDA, V _{IN} = 8–18 V	2100	2200	2300	kHz
	Oscillator Fre	quency 440 kHz	OSC = GND, V _{IN} = 8–18 V	420	440	460	kHz
	Adjustment	Minimum	OSC = VDD, $RT_{MIN} = 61.9 \text{ k}\Omega$	1710	1800	1890	kHz
RT	Range	Typical	OSC = VDD, $RT_{TYP} = 49.9 \text{ k}\Omega$	2100	2200	2300	kHz
	2.2 MHz	Maximum	$\begin{array}{cccccccccccccccccccccccccccccccccccc$	2655	kHz		
RT	Adjustment	Minimum	OSC = GND, RT _{MIN} = 73.2 k	285	300	315	kHz
	Range	Typical	OSC = GND, $RT_{TYP} = 49.9 \text{ k}\Omega$	420	440	460	kHz
	440 kHz	Maximum	OSC = GND, $RT_{MAX} = 44.2 \text{ k}\Omega$	475	500	525	kHz
RT	Response time	RT= 61.9–43.2 kΩ			2		μs
RT	Response time	RT = 43.2–61.9 kΩ			3.5		μs
RT	Response time				16		μs
t _{on}	Minimum on-t	ime			45	66	ns
t _{off}	Minimum off-time					100	ns


Submit Documentation Feedback

Copyright © 2016–2017, Texas Instruments Incorporated



6.7 Typical Characteristics


At $T_A = 25^{\circ}$ C, unless otherwise noted





Typical Characteristics (continued)


At $T_A = 25^{\circ}C$, unless otherwise noted





Typical Characteristics (continued)

At $T_A = 25^{\circ}C$, unless otherwise noted






7 Detailed Description

7.1 Overview

The LM5141-Q1 is a switching controller that features all of the functions necessary to implement a high-efficiency buck power supply that can operate over a wide input-voltage range. The LM5141-Q1 is configured to provide a single fixed 3.3-V or 5-V output, or an adjustable output between 1.5 V to 15 V. This easy-to-use controller integrates high-side and low-side MOSFET drivers capable of sourcing 3.25 A and sinking 4.25 A peak. The control method is current mode control, which provides inherent line feed-forward, cycle-by-cycle current limiting, and ease-of-loop compensation. With the OSC pin connected to VDD, the default oscillator frequency is 2.2 MHz. With the OSC pin grounded, the oscillator frequency is 440 kHz. The LM5141-Q1 can be synchronized by applying an external clock to the DEMB pin. Fault protection features include current limiting, thermal shutdown, and remote shutdown capability.

The LM5141-Q1 incorporates features that simplify compliance with the CISPR and automotive EMI requirements. The LM5141-Q1 has optional spread spectrum to reduce the peak EMI and gate drivers with slew-rate control. The QFN-24 package features an exposed pad to aid in thermal dissipation.

7.2 Functional Block Diagram



Copyright © 2016, Texas Instruments Incorporated



7.3 Feature Description

7.3.1 High Voltage Start-up Regulator

The LM5141-Q1 contains an internal high voltage VCC bias regulator that provides the bias supply for the PWM controller and the gate drivers for the external MOSFETs. The input pin (VIN) can be connected directly to an input voltage source up to 65 V. The output of the VCC regulator is set to 5 V. When the input voltage is below the VCC set-point level, the VCC output will track VIN with a small voltage drop. In high voltage applications extra care should be taken to ensure the VIN pin does not exceed the absolute maximum voltage rating of 70 V including line or load transients. Voltage ringing on the VIN pin that exceeds the absolute maximum ratings can damage the IC. Use a high quality bypass capacitor between VIN and ground to minimize ringing.

7.3.2 VCC Regulator

The VCC regulator output current limit is 75 mA (minimum). At power-up, the regulator sources current into the capacitors connected to the VCC pin. When the voltage on the VCC pin exceeds 3.4 V the output is enabled and the soft-start sequence begins. The output remains active unless the voltage on the VCC pin falls below the VCC_(UVLO) threshold of 3.2 V (typical) or the enable pin is switched to a low state. The recommended range for the VCC capacitor is $2.2~\mu\text{F}$ to $4.7~\mu\text{F}$

An internal 5-V linear regulator generates the VDDA bias supply. Bypass VDDA with a 100-nF or greater ceramic capacitor to ensure a low noise internal bias rail. Normally VDDA is 5 V, but there are two operating conditions where it regulates at 3.3 V. The first is in skip cycle mode with VOUT of 3.3 V. The second is when V_{IN} is less than 5 V. Under these conditions both VCC and VDD drop below 5 V. Internal power dissipation in the VCC Regulator can be minimized by connecting the VCCX pin to a 5-V output or to an external 5-V supply. If VCCX > 4.5 V, VCCX is internally connected to VCC and the internal VCC regulator is disabled. If VCCX is unused, it should be grounded. Never connect the VCCX pin to a voltage greater than 6.5 V.

7.3.3 Oscillator

The LM5141-Q1 has an internal trimmed oscillator with two frequency options: 2.2 MHz, or 440 kHz. With the OSC pin connected to VDDA the oscillator frequency is 2.2 MHz. With the OSC pin grounded, the oscillator frequency is 440 kHz. The state of the OSC pin is read and latched during VCC power-up and cannot be changed until VCC drops below the VCC_(UVI O) threshold.

The oscillator frequency can be modulated up or down from the nominal oscillator frequency (2.2 MHz or 440 kHz) on demand by connecting a resistor from the RT pin to ground (refer to Figure 19). To disable the frequency modulation option, the RT pin can be grounded or left open. If the RT pin is connected to ground during power-up the frequency modulation option is latch-off and cannot be changed unless VCC is allowed to drop below the VCC_(UVLO) threshold. If the RT pin is left open during power-up the frequency modulation option will be disabled, but it can be enabled at a later time by switching in a valid RT resistor. When the frequency modulation option is disabled, the LM5141-Q1 will operate at the internal oscillator frequency (2.2 MHz or 440 kHz).

On power up, after soft-start is complete and the output voltage is in regulation, a 16-µs timer is initiated. If a valid RT resistor is connected, the LM5141-Q1 will switch to the frequency set by the RT resistor n the completion of the 16-µs time delay.

The modulation range for 2.2 MHz is 1.8 MHz to 2.53 MHz (refer to Table 1). If an RT resistor value > 95 k Ω (typical) is placed on the RT pin, the LM5141-Q1 controller will assume that the RT pin is open, and will use the internal oscillator. If an RT resistor < 27 k Ω (typical) is connected, the controller will use the internal oscillator. To calculate an RT resistor for a specific oscillator frequency, use Equation 1 for the 2.2 MHz frequency range or Equation 2 for the 440 kHz frequency range.

$$RT_{2.2 \text{ MHz}} = \frac{\frac{1}{\text{Fsw}} - 0.0216}{0.0086}$$

where

• RT is $k\Omega$ and Fsw is in MHz

(1)



Feature Description (continued)

$$RT_{440 \text{ kHz}} = \frac{\frac{1}{\text{Fsw}} - 1.38 \times 10^{-5}}{4.5 \times 10^{-5}}$$


where

RT is in kΩ and Fsw is in kHz

(2)


Table 1. RT Resistance vs Oscillator Frequency

S 1	S 2	RT RESISTANCE (TYPICAL) 2.2 MHz	2.2 MHZ OSCILLATOR RANGE (TYPICAL)	RT RESISTANCE (TYPICAL) 440 kHz	440 kHz OSCILLATOR RANGE (TYPICAL)
X	X	> 95 kΩ	internal oscillator	> 95 kΩ	internal oscillator
OFF	OFF	61.98 kΩ total	1.8 MHz	73.8 kΩ total	300 kHz
OFF	ON	50.18 kΩ total	2.2 MHz	50.1 kΩ total	440 kHz
ON	OFF	43.2 kΩ	2.53 MHz	44.2 kΩ	500 kHz
Х	Χ	< 27 kΩ	internal oscillator	< 27 kΩ	internal oscillator



Copyright © 2016, Texas Instruments Incorporated

Figure 19. RT Connection Circuit, 2.2 MHz




Copyright © 2016, Texas Instruments Incorporated

Figure 20. RT Connection Circuit, 440 kHz



An alternative method to modulate the oscillator frequency is to use an analog voltage connected to the RT pin through a resistor. See Figure 21. An analog voltage of 0.0 V to 0.6 V modulates the oscillator frequency between 1.8 MHz to 2.53 MHz (OSC at 2.2 MHz), or 300 kHz to 500 kHz (OSC at 440 kHz). The analog voltage source must be able to sink current.



Copyright © 2016, Texas Instruments Incorporated

Figure 21. Analog Voltage Control of the Oscillator Frequency

When the LM5141-Q1 is in the low I_Q standby mode, the controller sets the RT pin to a high impedance state and ignores the RT resistor. After coming out of standby mode, the controller will monitor the RT pin. If a valid resistor is connected, and there have been 16 μ s of continuous switching without a zero-crossing event, the LM5141-Q1 will switch to the frequency set by the RT resistor.

7.3.4 Synchronization

To synchronize the LM5141-Q1 to an external source, apply a logic level clock signal to the DEMB pin. The synchronization range is 350 kHz to 550 kHz when the internal oscillator is set to 440 kHz. When the internal oscillator is set to 2.2 MHz, the synchronization range is 1.8 MHz to 2.6 MHz. If there is a valid RT resistor and a synchronization signal, the LM5141-Q1 with ignore the RT resistor and synchronize the controller to the external clock. Under low V_{IN} conditions, when the minimum toff time is reached (100ns), the synchronization clock will be ignored to allow the frequency to drop to maintain output voltage regulation.


7.3.5 Frequency Dithering (Spread Spectrum)

The LM5141-Q1 provides a frequency dithering option that is enabled by connecting a capacitor from the DITH pin to AGND. A triangular waveform centered at 1.2 V is generated across the C_{DITH} capacitor. Refer to Figure 22. The triangular waveform modulates the oscillator frequency by ±5% of the nominal frequency set by the OSC pin or by an RT resistor. The C_{DITH} capacitance value sets the rate of the low frequency modulation. A lower C_{DITH} capacitance will modulate the oscillator frequency at a faster rate than a higher capacitance. For the dithering circuit to effectively reduce the peak EMI, the modulation rate must be less than the oscillator frequency (F_{SW}). Equation 3 calculates the DITH pin capacitance required to set the modulation frequency, F_{MOD} .

$$C_{DITH} = \frac{20 \ \mu A}{2 \times F_{MOD} \times 0.12 \text{V}} \tag{3}$$

If the DITH pin is connected to VDDA during power-up the dither feature is latch-off and cannot be changed unless VCC is allowed to drop below the $VCC_{(UVLO)}$ threshold. If the DITH pin is connected to ground on power up, dither will be disabled, but it can be enabled by raising the DITH pin voltage above ground and connecting it to C_{DITH} . When the LM5141 is synchronized to an external clock, Dither is disabled.





Copyright © 2016, Texas Instruments Incorporated

Figure 22. Dither Operation

7.3.6 Enable

The LM5141-Q1 has an enable input EN for start-up and shutdown control of the output. The EN pin can be connected to a voltage as high as 70 V. If the enable input is greater than 2 V the output is enabled. If the enable pin is pulled below 0.8 V, the output will be in shutdown, and the LM5141-Q1 is switched to a low I_Q shutdown mode, with a 10- μ A typical current drawn from the VIN pin. It is not recommended to leave the EN pin left floating.

7.3.7 Power Good

The LM5141-Q1 includes an output voltage monitoring function to simplify sequencing and supervision. The power-good function can be used to enable circuits that are supplied by the output voltage rail or to turn on sequenced supplies. The PG pin switches to a high impedance state when the output voltage is in regulation. The PG signal switches low when the output voltage drops below the lower power good threshold (92% typical) or rises above the upper power good threshold (110% typical). A 25- μ s deglitch filter prevents any false tripping of the power good signal due to transients. TI recommends a pullup resistor of 10 k Ω from the PG pin to the relevant logic rail. Power good is asserted low during soft start and when the buck converter is disabled by EN.

7.3.8 Output Voltage

The LM5141-Q1 output can be configured for one of the two fixed output voltages with no external feedback resistors, or the output can be adjusted to the desired voltage using an external resistor divider. V_{OUT} can be configured as a 3.3-V output by connecting the FB pin to VDDA, or a 5-V output by connecting the FB pin to ground with a maximum resistance of 500 Ω . The FB connections (either VDDA or GND) are detected during power up.

The configuration setting is latched and cannot be changed until the LM5141-Q1 is powered down with VCC falling below VCC_(UVLO) (3.4 V typical) and then powered up again.

Alternatively the output voltage can be set using an external resistive dividers from the output to the FB pin. The output voltage adjustment range is between 1.5 V and 15 V. The regulation threshold at the FB pin is 1.2 V (V_{REF}). To calculate R_{FB1} and R_{FB2} use Equation 4. Refer to Figure 23:

$$R_{FB2} = \left(\frac{V_{OUT}}{V_{REF}} - 1\right) \times R_{FB1} \tag{4}$$

The recommend starting point is to select R_{FB1} between 10 k Ω to 20 k Ω .

The Thevenin equivalent impedance of the resistive divider connected to the FB pin must be greater than 5 k Ω for the LM5141-Q1 to detect the divider and set the controller to the adjustable output mode. Refer to Equation 5.

$$R_{TH} = \frac{R_{FB1} \times R_{FB2}}{R_{FB1} + R_{FB2}} > 5k\Omega$$
(5)

Submit Documentation Feedback

Copyright © 2016–2017, Texas Instruments Incorporated



If a low I_Q mode is required, take care when selecting the external resistors. The extra current drawn from the external divider is added to the LM5141-Q1 $I_{STANDBY}$ current (35 μ A typical). The divider current reflected to VIN is divided down by the ratio of V_{OUT}/V_{IN} . For example, if V_{IN} is 12 V and V_{OUT} is set to 5.5 V with R_{FB1} 10 k Ω , and R_{FB2} = 35.7 k Ω , the input current at VIN required to supply the current in the feedback resistors is:

$$I_{DIVIDER} = \frac{V_{OUT}}{R_{FB1} + R_{FB2}} \times \frac{V_{OUT}}{V_{IN}} = \frac{5.5 \, V}{10 \, k + 35.7 \, k} \times \frac{5.5 \, V}{12 \, V} = 55.16 \, \mu A$$

where

•
$$V_{IN} = 12 \text{ V}$$
 (6)

The total input current in this condition is:

$$I_{VIN} \approx I_{STANDBY} + I_{DIVIDER} \approx 35 \,\mu\text{A} + 55.16 \,\mu \approx 90.16 \,\mu\text{A}$$
 (7)




Figure 23. Voltage Feedback

7.3.8.1 Minimum Output Voltage Adjustment

There are two limitations to the minimum output voltage adjustment range: the LM5141-Q1 voltage reference of 1.2 V and the minimum switch node pulse width, t_{SW} .

The minimum controllable on-time at the switch node (t_{SW}) limits the voltage conversion ratio (V_{OUT}/V_{IN}). For fixed-frequency PWM operation, the voltage conversion ratio should meet the following condition:

$$\frac{V_{OUT}}{V_{IN}} > t_{sw} \times Fsw$$

where

t_{SW} is 70 ns (typical)

If the desired voltage conversion ratio does not meet the above condition, the controller transitions from fixed frequency operation into a pulse skipping mode to maintain regulation of the output voltage.

For example if the desired output voltage is 3.3 V with a V_{IN} of 20 V and operating at 2.2 MHz, the voltage conversion ratio test is satisfied:

$$\frac{3.3 \text{ V}}{20 \text{ V}} > 70 \text{ns} \times 2.2 \text{MHz}$$

$$0.165 > 0.154$$
(9)

For wide V_{IN} applications and lower output voltages, an alternative is to use the LM5141-Q1 with a 440-kHz oscillator frequency. Operating at 440 kHz, the limitation of the minimum t_{SW} time is less significant. For example, if a 1.8-V output is required with a V_{IN} of 50 V:

$$\frac{1.8\,\text{V}}{50\,\text{V}} > 70\,\text{ns} \times 440\,\text{kHz} \tag{10}$$

0.036 > 0.0308



7.3.9 Current Sense

There are two methods to sense the inductor current of the buck converter. The first is using current sense resistor in series with the inductor and the second is to use the dc resistance of the inductor (DCR sensing). Figure 24 shows inductor current sensing using a current-sense resistor. This configuration continuously monitors the inductor current providing accurate current-limit protection. For the best current-sense accuracy and overcurrent protection, use a low inductance ±1% tolerance current-sense resistor between the inductor and output, with a Kelvin connection to the LM5141-Q1 sense amplifier.

If the peak differential current signal sensed from CS to VOUT exceeds 75 mV, the current limit comparator immediately terminates the HO output for cycle-by-cycle current limiting.

$$R_{SENSE} = \frac{V_{(CS)}}{\left(I_{OUT(MAX)} + \frac{\Delta I}{2}\right)}$$

where

•
$$V_{(CS)} = 75 \text{ mV}$$
 (11)

 $I_{OUT(MAX)}$ is the overcurrent setpoint, which is set higher than the maximum load current to avoid tripping the over current comparator during load transients. ΔI is the peak-peak inductor ripple current.




Figure 24. Current Sense

7.3.10 DCR Current Sensing

For high-power applications which do not require high accuracy current-limit protection, DCR sensing may be preferable. This technique provides lossless and continuous monitoring of the output current using an RC sense network in parallel with the inductor. Using an inductor with a low DCR tolerance, the user can achieve a typical current limit accuracy within the range of ±10% to ±15% at room temperature.

Components R_{CS} and C_{CS} in Figure 25 create a low-pass filter across the inductor to enable differential sensing of the voltage drop across inductor DCR. When $R_{CS} \times C_{CS}$ is equal to L_{OUT}/R_{DCR} , the voltage developed across the sense capacitor, C_{CS} , is a replica of the inductor DCR voltage waveform. Choose the capacitance of C_{CS} to be greater than 0.1 μF to maintain a low impedance sensing network, thus reducing the susceptibility of noise pickup from the switch node. Carefully observe the PCB layout guidelines to ensure the noise and DC errors do not corrupt the differential current-sense signals applied across the CS and VOUT pins.

The voltage drop across C_{CS} :

$$V_{CS}(s) = \frac{1 + \frac{sL_{OUT}}{R_{DCR}}}{1 + sR_{CS}C_{CS}} lpk \times R_{DCR}$$
(12)






Figure 25. DCR Current Sensing

 $R_{CS}C_{CS} = L_{OUT}/R_{DCR} \rightarrow accurate DC and AC current sensing$

If the RC time constant is not equal to the L_{OUT}/L_{DRC} time constant there will be an error

 $R_{CS}C_{CS} > L_{OUT}/R_{DCR} \rightarrow DC$ level still correct, the AC amplitude will be attenuated

 $R_{CS}C_{CS} < L_{OUT}/R_{DCR} \rightarrow DC$ level still correct, the AC amplitude will be amplified

7.3.11 Error Amplifier and PWM Comparator

The LM5141-Q1 has a high-gain transconductance amplifier that generates an error current proportional to the difference between the feedback voltage and an internal precision reference (1.2 V). The output of the transconductance amplifier is connected to the COMP pin allowing the user to provide external control loop compensation. Generally for current mode control a type II network is recommended.

7.3.12 Slope Compensation

The LM5141-Q1 provides internal slope compensation to ensure stable operation with a duty cycle greater than 50%. To correctly use the internal slope compensation, the inductor value must be calculated based on the following guidelines (Equation 12 assumes an inductor ripple current of 30%):

$$L_{OUT} \ge \frac{V_{OUT}}{Fsw \times (0.3 \times I_{OUT})}$$
(13)

- Lower inductor values increase the peak-to-peak inductor current, which minimizes size and cost and improves transient response at the cost of reduced efficiency due to higher peak currents.
- Higher inductance values decrease the peak-to-peak inductor current typically increases efficiency by reducing the RMS current at the cost of requiring larger output capacitors to meet load-transient specifications.

7.3.13 Hiccup Mode Current Limiting

The LM5141-Q1 includes an optional hiccup mode protection function that is enabled when a capacitor is connected to the RES pin. In normal operation the RES capacitor is discharged to ground. If 512 consecutive cycles of cycle-by-cycle current limiting occur, the SS pin capacitor is pulled low and the HO and LO outputs are disabled (refer to Figure 26). A 20- μ A current source begins to charge the RES capacitor.

When the RES pin charges to 1.2 V, the RES pin is pulled low, and the SS capacitor begins to charge. The 512 cycle hiccup counter is reset if 4 consecutive switching cycles occur without exceeding the current limit threshold. The controller is in forced PWM (FPWM) continuous conduction mode when the DEMB pin is connected to VDDA. In this mode the SS pin is clamped to a level 200 mV above the feedback voltage to the internal error amplifier. This ensures that SS can be pulled low quickly during a brief overcurrent event and prevent overshoot of VOUT when the overcurrent condition is removed.

Copyright © 2016–2017, Texas Instruments Incorporated

If DEMB = 0 V, the controller operates in diode emulation with light loads (discontinuous conduction mode) and the SS pin is allowed to charge to VDDA. This reduces the quiescent current of the LM5141-Q1. If 32 or more cycle-by-cycle current limit events occur, the SS pin is clamped to 200 mV above the feedback voltage to the internal error amplifier until the hiccup counter is reset. Thus, if a momentary overload occurs that causes at least 32 cycles of current limiting, the SS capacitor voltage will be slightly higher than the FB voltage and will control VOUT during overload recovery.




Figure 26. Hiccup Mode

7.3.14 Standby Mode

The LM5141-Q1 operates with peak current mode control such that the compensation voltage is proportional to the peak inductor current. During no-load or light load conditions, the output capacitor will discharge very slowly. As a result the compensation voltage will not demand a driver output pulses on a cycle-by-cycle basis. When the LM5141-Q1 controller detects that there have been 16 missing switching cycles, it enters standby mode and switches to a low IQ state to reduce the current drawn from VIN. For the LM5141-Q1 to go into a standby mode, the controller must be programmed for diode emulation (DEMB pin < 0.4 V). The typical IQ in standby mode is $35~\mu\text{A}$ with VOUT regulating at 3.3~V.

7.3.15 Soft Start

The soft-start feature allows the controller to gradually reach the steady state operating point, thus reducing start-up stresses and surges. The LM5141-Q1 regulates the FB pin to the SS pin voltage or the internal 1.2-V reference, whichever is lower. At the beginning of the soft-start sequence when SS = 0 V, the internal 20 μA soft-start current source gradually increases the voltage on an external soft-start capacitor connected to the SS pin, resulting in a gradual rise of the FB and output voltages. The controller is in the forced PWM (FPWM) mode when the DEMB pin is connected to VDDA. In this mode, the SS pin is clamped at 200 mV above the feedback voltage. This ensures that SS will be pulled low quickly when FB falls during brief over-current events to prevent overshoot of VOUT during recovery. SS can be pulled low with an external circuit to stop switching, but this is not recommended. Pulling SS low results in COMP being pulled down internally as well. If the controller is operating in FPWM mode (DEMB = VDDA), LO remains on, and the low-side MOSFET discharges the VOUT capacitor resulting in large negative inductor current. In contrast when the LM5141-Q1 pulls SS low internally due to a fault condition, the LO gate driver is disabled.

7.3.16 Diode Emulation

A fully synchronous buck controller implemented with a free-wheel MOSFET rather than a diode has the capability to sink negative current from the output in certain conditions such as light load, over-voltage, and prebias start-up. The LM5141-Q1 provides a diode emulation feature that can be enabled to prevent reverse (drain to source) current flow in the low-side free-wheel MOSFET. The diode emulation feature is configured with the DEMB pin. To enable diode emulation, connect the DEMB pin to ground. When configured for diode emulation, the low-side MOSFET is disabled when reverse current flow is detected. The benefit of this configuration is lower power loss at no load or light load conditions and the ability to turn on into a pre-biased output without discharging the output. The negative effect of diode emulation is degraded light load transient response times. Enabling the diode emulation feature is recommended to allow discontinuous conduction operation. If continuous conduction operation is desired, the DEMB pin should be tied to VDDA.



Tabl	۵2	DEM	R Pi	n Ma	aahr

DEMB PIN	MODE
1	FPWM
0	DEMB
CLK	FPWM

7.3.17 High- and Low-Side Drivers

The LM5141-Q1 contains N-channel MOSFET gate drivers and an associated high-side level shifter to drive the external N-channel MOSFETs. The high-side gate driver works in conjunction with an external bootstrap diode D_{BST} , and bootstrap capacitor C_{BST} (refer to Figure 27). During the on-time of the low-side MOSFET, the SW pin voltage is approximately 0 V, and C_{BST} is charged from VCC through the D_{BST} . A 0.1- μ F or larger ceramic capacitor, connected with short traces between the HB and SW pin is recommended.

The LO and HO outputs are controlled with an adaptive dead-time methodology which ensures that both outputs (HO and LO) are never enabled at the same time, preventing cross conduction. When the controller commands LO to be enabled, the adaptive dead-time logic first disables HO and waits for the HO-SW voltage to drop below 2.5 V typical. LO is then enabled after a small delay (HO falling to LO rising delay). Similarly, the HO turn-on is delayed until the LO voltage has dropped below 2.5 V. HO is then enabled after a small delay (LO falling to HO rising delay). This technique ensures adequate dead-time for any size N-channel MOSFET device or parallel MOSFET configurations. Caution is advised when adding series gate resistors, as this may decrease the effective dead-time. Each of the high and low-side drivers have independent driver source and sink output pins. This allows the user to adjust drive strength to optimize the switching losses for maximum efficiency and to control the slew rate for reduced EMI. The selected N-channel high-side MOSFET determines the appropriate boost capacitance values C_{BST} in Figure 27 according to Equation 14.

$$C_{BST} = \frac{Q_G}{\Delta V_{BST}}$$

where

- Q_G is the total gate charge of the high-side MOSFET
- ΔV_{BST} is the voltage variation allowed on the high-side MOSFET driver after turnon

Choose ΔV_{BST} such that the available gate-drive voltage is not significantly degraded when determining C_{BST} . A typical range of ΔV_{BST} is 100 mV to 300 mV. The bootstrap capacitor should be a low-ESR ceramic capacitor. A minimum value of 0.1 μF to 0.47 μF is best in most cases. The gate threshold of the high-side and low-side MOSFETs should be a logic level variety appropriate for 5-V gate drive.




Figure 27. Drivers

Submit Documentation Feedback

(14)



8 Application and Implementation

NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

The LM5141-Q1 is a synchronous buck controller used to convert a higher input voltage to a lower output voltage. The following design procedure can be used to select external component values. Alternately, the WEBENCH® software may be used to generate a complete design. The WEBENCH software uses an iterative design procedure and accesses a comprehensive database of components when generating a design. This section presents a simplified design process. In addition to the WEBENCH software the LM5141ADESIGN-CALC.xls quick-start Excel calculator is available at www.ti.com.

8.2 Typical Application




Figure 28. Typical Application Schematic



Typical Application (continued)

8.2.1 Design Requirements

For this design example, the intended input, output, and performance parameters are shown in Table 3.

Table 3. Design Requirements

DESIGN PARAMETER	EXAMPLE VALUE
Input voltage range (steady state)	8 V to 18 V
V _{IN} maximum (transient)	42 V
V _{IN} minimum (cold crank)	3.8 V
Output voltage	3.3 V
Output current	6 A
Operating frequency	2.2 MHz
Output voltage regulation	±1%
Standby current, one output enabled, no-load	< 35 μΑ
Shutdown current	10 μΑ

8.2.2 Detailed Design Procedure

8.2.2.1 Custom Design With WEBENCH® Tools

Click here to create a custom design using the LM5141-Q1 device with the WEBENCH® Power Designer.

- 1. Start by entering the input voltage (V_{IN}), output voltage (V_{OUT}), and output current (I_{OUT}) requirements.
- 2. Optimize the design for key parameters such as efficiency, footprint, and cost using the optimizer dial.
- 3. Compare the generated design with other possible solutions from Texas Instruments.

The WEBENCH Power Designer provides a customized schematic along with a list of materials with real-time pricing and component availability.

In most cases, these actions are available:

- Run electrical simulations to see important waveforms and circuit performance
- Run thermal simulations to understand board thermal performance
- Export customized schematic and layout into popular CAD formats
- Print PDF reports for the design, and share the design with colleagues

Get more information about WEBENCH tools at www.ti.com/WEBENCH.

- · Buck Inductor value
- · Calculate the peak inductor current
- Current Sense resistor value
- · Output capacitor value
- Input filter
- MOSFET selection
- Control Loop design



8.2.2.2 Inductor Calculation

For peak current mode control, sub-harmonic oscillation occurs with a duty cycle greater than 50% and is characterized by alternating wide and narrow pulses at the SW pin. By adding a slope compensating ramp equal to at least one-half the inductor current down-slope, any tendency toward sub-harmonic oscillation is damped within one switching cycle. For design simplification, the LM5141-Q1 has an internal slope compensation ramp added to the current sense signal.

For the slope compensation ramp to dampen sub-harmonic oscillation, the inductor value should be calculated based on the following guidelines (Equation 15 assumes an inductor ripple current 30%):

$$L_{OUT} \ge \frac{V_{OUT}}{Fsw \times (0.3 \times I_{OUT})}$$
(15)

- Lower inductor values increase the peak-to-peak inductor current, which minimizes size and cost and improves transient response at the expense of reduced efficiency due to higher peak currents.
- Higher inductance values decrease the peak-to-peak inductor current, which typically increases efficiency by reducing the RMS current but requires larger output capacitors to meet load-transient specifications.

$$\begin{split} L_{OUT} &\geq \frac{3.3 \, \text{V}}{2.2 \text{MHz} \times \left(0.3 \times 6 \, \text{A}\right)} \\ L_{OUT} &\geq 0.833 \mu \text{H} \end{split} \tag{16}$$

A standard inductor value of 1.5 µH was selected

$$D_{MAX} = \frac{V_{OUT}}{V_{IN(MIN)}} = \frac{3.3 \,\text{V}}{8 \,\text{V}} = 0.413 \tag{17}$$

$$D_{MIN} = \frac{V_{OUT}}{V_{IN(MAX)}} = \frac{3.3 \,\text{V}}{18 \,\text{V}} = 0.183 \tag{18}$$

The peak-to-peak inductor current is:

$$\Delta I = \frac{V_{IN(MAX)} - V_{OUT}}{L_{OUT}} \times \frac{D_{MIN}}{Fsw}$$
(19)

$$\Delta I = \frac{18 \text{ V} - 3.3 \text{ V}}{1.5 \mu \text{H}} \times \frac{0.183}{2.2 \text{MHz}} = 0.815 \text{ A}$$
(20)

$$lpk = l_{OUT} + \frac{\Delta l}{2}$$
 (21)

$$lpk = 6A + \frac{0.815}{2} = 6.41A \tag{22}$$



8.2.2.3 Current Sense Resistor

When calculating the current sense resistor, the maximum output current capability (I_{OUT(MAX)}) must be at least 20% higher than the required full load current to account for tolerances, ripple current, and load transients. For this example, 120% of the 6.41-A peak inductor current calculated in Inductor Calculation (Ipk) is 7.69 A. The current sense resistor value can be calculated using:

$$R_{SENSE} = \frac{V_{(CS)}}{I_{OUT(MAX)}}$$

$$R_{SENSE} = \frac{75\text{mV}}{7.69\text{A}} = 0.00975\Omega$$
(23)

where

The R_{SENSE} value selected is 9 m Ω .

Carefully observe the PCB layout guidelines to ensure that noise and DC errors do not corrupt the differential current sense signals between the CS and VOUT pins. Place the sense resistor close to the devices with short, direct traces, creating Kelvin-sense connections between the current-sense resistor and the LM5141-Q1.

The propagation delays through the current limit comparator, logic, and external MOSFET gate drivers allow the peak current to increase above the calculated current limit threshold. For a propagation delay of t_{div}, the worstcase peak current through the inductor with the output shorted can be calculated from:

$$Ipk_{SCKT} = \frac{V_{(CS)}}{R_{SENSE}} + \frac{V_{IN(MAX)} \times t_{dly}}{L_{OUT}}$$
(25)

From *Electrical Characteristics*,
$$t_{dly1}$$
 is typically 40 ns.
$$lpk_{SCKT} = \frac{75mV}{0.009\Omega} + \frac{18V \times 40ns}{1.5\mu H} = 8.81A \tag{26}$$

Once the peak current and the inductance parameters are known, the inductor can be chosen. Select an inductor with a saturation current greater than Ipk_{SCKT} (8.81 Apk).

8.2.2.4 Output Capacitor

In a switch mode power supply, the minimum output capacitance is typically selected based on the capacitor ripple current rating and the load transient requirements. The output capacitor must be large enough to absorb the inductor energy and limit over voltage when transitioning from full-load to no-load, and to limit the output voltage undershoot during no-load to full load transients. The worst-case load transient from zero to full load occurs when the input voltage is at the maximum value and a current switching cycle has just finished. The total output voltage drop ΔV_{OUT} is the sum of the voltage drop while the inductor is ramping up to support the full load and the voltage drop before the next pulse can occur.

The output capacitance required to maintain the minimum output voltage drop (ΔV_{OLT}) can be calculated as follows:

$$\begin{split} C_{OUT(MIN)} &= \frac{L_{OUT} \times I_{STEP}^2}{2 \times \Delta V_{OUT} \times D_{MAX} \times \left(V_{IN(MIN)} - V_{OUT}\right)} \\ C_{OUT(MIN)} &= \frac{1.5 \, \mu H \times 4 \, A^2}{2 \times 33 \, mV \times 0.413 \times (8 \, V - 3.3 \, V)} = 186 \, \mu F \end{split} \tag{27}$$

where

I_{STEP} (the transient step load current for this example) = 4 A

•
$$\Delta V_{OUT} = 1\% \text{ of } 3.3 \text{ V, or } 33 \text{ mV}$$
 (28)

For this example a total of 211 μF of capacitance is used, two 82-μF aluminum capacitors for energy storage and one 47-μF low ESR ceramic capacitor to reduce high frequency noise.



Generally, when sufficient capacitance is used to satisfy the undershoot requirement, the overshoot during a full-load to no-load transient will also be satisfactory. After the output capacitance has been selected, calculate the output ripple current and verify that the ripple current is within the capacitor ripple current ratings.

$$I_{OUT(RMS)} = \frac{\Delta I}{\sqrt{12}}$$
 (29)

$$I_{OUT(RMS)} = \frac{0.815 \,A}{\sqrt{12}} = 0.235 \,A \tag{30}$$

8.2.2.5 Input Filter

A power supply input typically has a relatively high source impedance at the switching frequency. Good-quality input capacitors are necessary to limit the ripple voltage at the VIN pin while supplying most of the switch current during the buck switch on-time. When the buck switch turns on, the current drawn from the input capacitor steps from zero to the valley of the inductor current waveform, then ramps up to the peak value, and then drops to the zero at turn-off.

Average input current can be calculated from the total input power required to support the load at V_{OUT}:

$$P_{IN} = \frac{V_{OUT} \times I_{OUT}}{\eta}$$
(31)

The efficiency (η) is assumed to be 83% for this design example, yielding a total input power:

$$P_{IN} = \frac{3.3 \text{ V} \times 6 \text{ A}}{0.83} = 23.86 \text{ W}$$
 (32)

$$I_{avg} = \frac{P_{IN}}{V_{IN(MIN)}} \tag{33}$$

$$I_{avg} = \frac{28.6 \,\text{W}}{8 \,\text{V}} = 3.58 \,\text{A} \tag{34}$$

The input capacitors should be selected with sufficient RMS current rating and the maximum voltage rating.

$$I_{IN(RMS)} = \sqrt{\left(Ipk - I_{avg}\right)^2 + \frac{\Delta I^2}{12}} xD_{MAX} + (I_{avg}^2 \times (1 - D_{MAX}))$$
(35)

$$I_{IN(RMS)} = \sqrt{\left(6.41A - 3.58A\right)^2 + \frac{0.815^2}{12} \times 0.413 + \left(3.58A^2 \times (1 - 0.413)\right)} = 2.93A \tag{36}$$



8.2.2.5.1 EMI Filter Design

EMI Filter Design Steps:

- Calculate the required attenuation
- Capacitor C_{IN} represents the existing capacitor at the input of the switching converter (10 μF was used for this application)
- Inductor LF is usually selected between 1 μH and 10 μH (1.8 μH was used for this application), but can be smaller to reduce losses in a high current design
- Calculate capacitor C_F




Figure 29. Input EMI Filter

By calculating the first harmonic current from the Fourier series of the input current waveform and multiplying it by the input impedance (the impedance is defined by the existing input capacitor C_{IN}), a formula can be derived to obtain the required attenuation:

$$|\text{Attn}| = 20 \times log \left[\frac{\frac{lpk}{\pi^2 \times F_{SW} \times C_{IN}} \times sin(\pi \times D_{MAX})}{1 \, \mu V} \right] - V_{MAX}$$

$$|\text{Attn}| = 20 log \left[\frac{\frac{6.41 \, A}{\pi^2 \times 2.2 \, MHz \times 10 \, \mu F} \times sin(\pi \times 0.413)}{1 \, \mu V} \right] - 45 \, dB \, \mu V = 44.07 \, dB$$

$$(38)$$

 V_{MAX} is the allowed dB μV noise level for the particular EMI standard. C_{IN} is the existing input capacitors of the Buck converter, for this application 10 μF was selected. D_{MAX} is the maximum duty cycle, lpk is the inductor current, the current at the input can be modeled as a square wave, F_{SW} is the switching frequency.

$$C_{F} = \frac{1}{L_{F}} \left[\frac{10^{\frac{|Attn|}{40}}}{2 \times \pi \times F_{SW}} \right]^{2}$$

$$C_{F} = \frac{1}{1.8 \,\mu\text{H}} \left(\frac{10^{\frac{44.07}{40}}}{2 \times \pi \times 2.2 \,\text{MHz}} \right)^{2} = 0.47 \,\mu\text{F}$$
(40)

For this application, C_F was chosen to be 1 μ F. Adding an input filter to a switching regulator modifies the control-to output transfer function. The output impedance of the filter must be sufficiently small such that the input filter does not significantly affect the loop gain of the buck converter. The impedance of the filter peaks at the filter resonant frequency.

$$F_{R} = \frac{1}{2 \times \pi \sqrt{L_{F}C_{IN}}} \tag{41}$$

$$F_{R} = \frac{1}{2 \times \pi \sqrt{1.8 \,\mu \text{H} \times 10 \,\mu \text{F}}} = 37.53 \,\text{kHz}$$
(41)



Referring to Figure 29, the purpose of R_D is to reduce the peak output impedance of the filter at the cutoff frequency. The capacitor C_D blocks the dc component of the input voltage, and avoids excessive power dissipation on R_D . The capacitor C_D should have lower impedance than R_D at the resonant frequency, with a capacitance value greater than 5 times the filter capacitor C_{IN} . This will prevent it from interfering with the cutoff frequency of the main filter. Added damping is needed when the output impedance is high at the resonant frequency (Q) of filter formed by C_{IN} and L_F is too high):

An electrolytic cap C_D can be used as damping device, with value:

$$R_{D} = \sqrt{\frac{L_{F}}{C_{IN}}}$$
(43)

For this design $C_D = 47 \mu F$ was selected

$$R_{D} = \sqrt{\frac{1.8\,\mu\text{H}}{10\,\mu\text{F}}} = 0.424\,\Omega \tag{44}$$

8.2.2.5.2 MOSFET Selection

The LM5141-Q1 gate drivers are powered by the internal 5-V VCC bias regulator. To reduce power dissipation in the controller and improve efficiency, the VCCX pin should be connected to the 5-V output or an external 5 V bias supply. The MOSFETs used with the LM5141-Q1 require a logic-level gate threshold with $R_{DS(ON)}$ specified with $V_{GS} = 4.5$ V or lower.

The MOSFETs must be chosen with a V_{DS} rating to withstand the maximum V_{IN} voltage plus supply voltage transients and spikes (ringing). For automotive applications, the maximum V_{IN} occurs during a load dump and the voltage can surge up to 42 V under some conditions. A MOSFET with a V_{DS} rating of 60 V would meet most application requirements. The N-channel MOSFETs must be capable of delivering the load current plus peak ripple current during switching.

The high-side MOSFET losses are associated with the R_{DS(ON)} of the MOSFET and the switching losses.

$$P_{D(HS)} = \left(I_{OUT}^{2} \times R_{DS(ON)} \times D_{MAX}\right) + \frac{1}{2} \times V_{IN} \times (t_{r} + t_{f}) \times I_{OUT} \times F_{SW}$$

$$P_{D(HS)} = \left((6 \text{ A})^{2} \times 0.026 \Omega \times 0.413\right) + \frac{1}{2} \times 12 \text{ V} \times (17 \text{ ns} + 17 \text{ ns}) \times 6 \text{ A} \times 2.2 \text{ MHz} = 2.69 \text{ W}$$
(45)

where

•
$$tr = ts = 17 \text{ ns}$$
 (46)

The losses in the low side MOSFET include: $R_{\rm DS(ON)}$ losses, dead time losses, and losses in the MOSFETs internal body diode. The body diode conducts the inductor current during the dead time before the rising edge of the switch node; minority carriers are injected into and stored in the diode PN junction when forward biased. As the high side FET starts to turn-on, a negative current must first flow through the diode to remove the stored charge before the diode can block a reverse voltage. During this time, the high side drain-source voltage remains at $V_{\rm IN}$ until all the diode minority carriers are removed. Then, the diode begins to block negative voltage and the reverse current continues to flow to charge the body diode depletion capacitance. The total charge involved in this period is called reverse-recovery charge Qrr.

$$P_{D(LO)} = \left(I_{OUT}^{2} \times R_{DS(ON)} \times (1 - D_{MAX})\right) + \left(I_{OUT} \times (t_{dr} + t_{df})\right) \times F_{SW} \times V_{D(FET)} + \left(D_{Qrr} \times F_{SW} \times V_{IN}\right)$$

$$\tag{47}$$

$$P_{D(LO)} = \left((6A)^2 \times 26 \text{m}\Omega \times \left(1 - 0.413 \right) \right) + \left(6A \times \left(20 \text{ns} + 20 \text{ns} \right) \right) \times 2.2 \text{MHz} \times 0.8 \, \text{V} \\ + \left(105 \text{nC} \times 2.2 \text{MHz} \times 12 \, \text{V} \right) = 3.744 \, \text{W} \times 12 \, \text{MHz} + 20 \, \text{MHz} + 2$$

where

- t_{dr} and t_{df} are the switch node voltage rise and fall times (20 ns)
- V_{D(FET)} is the forward voltage drop across the low-side MOSFET internal body diode (0.8 V)
- D_{Qrr} is the internal body diodes reverse recovery charge (105 nC)
- $R_{DS(ON)}$ is the on resistance of the MOSFETs (26 m Ω at T_J = 125°C) (48)

Submit Documentation Feedback

Copyright © 2016–2017, Texas Instruments Incorporated



Table 4 provides parameters for several MOSFETs that have tested in the LM5141-Q1 evaluation module.

		SFFTs

MANUFACTURER	PART NUMBER	V _{DS} (V)	I _D (A)	$Q_{g(MAX)}$ (nC) $V_{GS} = 4.5 \text{ V}$	$V_{GS} = 4.5 \text{ V } (\Omega)$	C _{OSS(MAX)} (pF)	APPLICATION
VISHAY	SQJ850EP	60	24	30	32	215	Automotive high power
VISHAY	SQ7414EN	60	5.6	25	36	175	Automotive low power
Texas Instruments	CSD18534Q5A	60	13	11.1	12.4	217	Industrial

8.2.2.5.3 Driver Slew-Rate Control

Figure 30 shows the high current driver outputs with independent source and current sink pins for slew-rate control. Slew-rate control enables the user to adjust the switch node rise and fall times which can reduce the conducted EMI in the FM radio band (30 MHz to 108 MHz). Using the LM5141-Q1 EVM, conducted emissions were measured in accordance with CISPR 25 Class 5. Figure 31 shows the measured results without slew-rate control.

The conducted EMI results with slew-rate control are shown in Figure 32, a 10-dB reduction in conduction emissions in the FM band is attained by using slew-rate control. This can help reduce the size and cost of the EMI filters.




Figure 30. Drivers With Slew-Rate Control




Figure 31. EMI Measurements CISPR 25 Class 5, Without Slew-Rate Control

Submit Documentation Feedback

Product Folder Links: LM5141-Q1






Figure 32. EMI Measurements CISPR 25 With Slew-Rate Control

8.2.2.5.4 Frequency Dithering

Figure 33 shows the CISPR 25 Class 5 conducted emission test run on the LM5141-Q1EVM, without the dither feature enabled. The first harmonic (peak measurement) is 48 dB μ V, Figure 34 shows the conducted emissions test results with the dither feature enabled. With the dither featured enabled, the first harmonic (peak measurement) was lowered to 40 dB μ V, an 8-dB reduction.




Figure 33. CISPR 25 Class 5 Conducted EMI, Without Dither






Figure 34. CISPR 25 Class 5 With Dither

8.2.2.6 Control Loop

The open loop gain is defined as the product of modulator transfer function and feedback transfer function. When plotted on a dB scale, the open loop gain is shown as the sum of modulator gain and feedback gain.

DC modulator gain is:

$$AM = \frac{R_{LOAD}}{\left(R_{SENSE} + R_{DCR}\right) \times G_{CS}}$$
(49)

The modulator gain plus power stage transfer function with an embedded current loop is show in Equation 50. The equation includes the sample gain at F_{SW} /2 (ω_n), which is caused by sampling effect of current mode control.

$$\frac{\hat{V}_{OUT}}{\hat{V}_{C}\left(s\right)} = AM \times \frac{\left(1 + \frac{s}{\omega_{Z}}\right)}{\left(1 + \frac{s}{\omega_{P}}\right) \times \left(1 + \frac{s}{\omega_{n}Q} + \frac{s^{2}}{\omega_{n}^{2}}\right)}$$

where

•
$$s = 2 \times \pi \times F_{SW}$$

$$Q = \frac{1}{\pi (K - 0.5)}$$

$$\omega_Z = \frac{1}{C_{ESR} \times C_{OUT}}$$

$$\omega_{p} = \frac{1}{R_{LOAD} \times C_{OUT}}$$

$$\omega_{n} = \pi \times F_{SW}$$

K = 1

G_{CS} is the current sense amplifier gain which is 12

(50)



Because the loop crossover frequency is well below sample gain effects, Equation 50 can be simplified as one pole and a one zero system as shown in Equation 51.

$$\frac{\hat{V}_{OUT}(s)}{\hat{V}_{C}(s)} = AM \times \frac{\left(1 + \frac{s}{\omega_{Z}}\right)}{\left(1 + \frac{s}{\omega_{p}}\right)}$$
(51)

R_{LOAD} is the load resistance

 R_{DCR} is the dc resistance on the output inductor which is 8.1 m Ω

 R_{SENSE} is the current sense resistance which is 9 m Ω

8.2.2.6.1 Feedback Compensator

A type II compensator using an transconductance error amplifier (EA), Gm, is shown in Figure 35. The dominant pole of the EA open-loop gain is set by the EA output resistance, R_{AMP} , and effective bandwidth-limiting capacitance, C_{O} , as follows:

$$G_{EA(openloop)}(s) = -\frac{GmR_{AMP}}{1 + sR_{AMP}C_O}$$
(52)

The EA high frequency pole is neglected in the above expression. The compensator transfer function from output voltage to COMP, including the gain contribution from the feedback resistor divider network is:

$$G_{C}(s) = \frac{\hat{V}_{C}(s)}{\hat{V}_{OUT}(s)} = -\frac{V_{REF}}{V_{OUT}} \times Gm \times Z_{EAOUT}(s)$$
(53)

$$\frac{R_{LOWER}}{R_{LOWER} + R_{UPPER}} = \frac{V_{REF}}{V_{OUT}}$$
(54)

where

$$Z_{\text{EAOUT}}(s) = Gm \times \left(R_{\text{AMP}} \left\| \left(R_{\text{COMP}} + \frac{1}{sC_{\text{COMP}}}\right) \right\| \frac{1}{sC_{\text{HF}}} \left\| \frac{1}{sC_{\text{O}}} \right) \right\}$$
(55)

Which simplifies to:

$$Z_{EAOUT}(s) = R_{AMP} \frac{1 + \frac{s}{\omega_{zEA}}}{\left(1 + \frac{s}{\omega_{pEA1}}\right) \times \left(1 + \frac{s}{\omega_{pEA2}}\right)}$$

$$R_{UPPER} \downarrow V_{REF} \downarrow C_{OUT} \downarrow C_{OUT} \downarrow C_{OUT}$$

$$R_{LOWER} \downarrow C_{COMP} \downarrow C_{COMP} \downarrow C_{HF} \downarrow C_{ESR}$$

$$R_{LOWER} \downarrow C_{COMP} \downarrow C_{CO$$

Figure 35. Transconductance Amplifier



$$\omega_{\text{zEA}} = \frac{1}{R_{\text{COMP}} \times C_{\text{COMP}}}$$
(57)

$$\omega_{\text{pEA1}} = \frac{1}{\left(R_{\text{AMP}} + R_{\text{COMP}}\right)\left(C_{\text{COMP}} + C_{\text{HF}} + C_{\text{O}}\right)} \cong \frac{1}{R_{\text{AMP}} \times C_{\text{COMP}}} \tag{58}$$

$$\omega_{\text{pEA2}} = \frac{1}{R_{\text{COMP}} \left(C_{\text{COMP}} \| \left(C_{\text{HF}} + C_{\text{O}} \right) \right)} \cong \frac{1}{R_{\text{COMP}} \times C_{\text{HF}}}$$
(59)

Typically $R_{COMP} \ll R_{AMP}$ and $C_{COMP} \gg (C_{HF} + C_O)$ so the approximations are valid.

where

V_{REF} is the feedback voltage reference (1.2 V)

G_m is the error amplifier gain transconductance (1200 μs)

 R_{AMP} is the error amplifier output impedance (2.5 M Ω)

The error amplifier compensation components create a pole at the origin, a zero, and a high frequency pole.

The procedure for choosing compensation components for a stable closed loop is:

- Select the desired open loop gain crossover frequency (fc); for this application 30 kHz was chosen
- Calculate the R_{COMP} resistor for the gain crossover frequency at 30 kHz

$$R_{COMP} = fc \frac{V_{OUT}}{V_{REF}} \times \frac{2 \times \pi \times C_{OUT} \times (R_{SENSE} + R_{DCR}) \times G_{CS}}{Gm}$$
(60)

$$R_{COMP} = 30 \, KHz \times \frac{3.3 \, V}{1.2 \, V} \times \frac{2 \times \pi \times 293 \, \mu F \times \left(0.009 \Omega + 0.0081 \Omega\right) \times 12}{1200 \times 10^{-6} \, \mu S} = 25927 \, \Omega \tag{61}$$

The value selected for R_{COMP} is 22.6 k Ω .

where

 $R_{DCR} = 0.0081 \Omega$

• Calculate the C_{COMP} capacitor value to create a zero that cancels the pole ω_p ($\omega_p = 1/R_{LOAD} \times C_{OUT}$)

$$C_{COMP} = \frac{R_{LOAD} \times C_{OUT}}{R_{COMP}}$$
(62)

$$C_{COMP} = \frac{0.477\Omega \times 290\,\mu\text{F}}{22.6\text{k}\Omega} = 6\text{nF} \tag{63}$$

The value selected for C_{COMP} is 10 nF.



8.2.3 Application Curves

The Bode plots of the modulator and plus power stage are shown in refer to Figure 36. The results of the total loop gain crossover frequency are 40 kHz with 112° of phase margin, (see Figure 37).




Figure 36. (V_{OUT}/V_C) Modulator Gain and Phase




Figure 37. Loop Gain and Phase

Submit Documentation Feedback

Copyright © 2016–2017, Texas Instruments Incorporated



9 Power Supply Recommendations

The LM5141-Q1EVM is designed to operate over an input voltage supply range between 5.5 V and 42 V. The input supply must be well regulated. If the power source is located more than a few inches from the LM5141-Q1 EVM, additional bulk capacitance and ceramic bypass capacitors may be required at the power supply input. An electrolytic capacitor with a value of 47 μ F is typically a good choice.

10 Layout

10.1 Layout Guidelines

Careful PCB layout is critical to achieve low EMI and stable power supply operation. Make the high frequency current loops as small as possible, and follow these guidelines of good layout practices:

- 1. Keep the high-current paths short. This is essential for stable, jitter-free operation.
- 2. Keep the power traces and load connections short. This is essential for high efficiency. Using 2 oz or thicker copper can enhance full load efficiency.
- 3. Minimize current-sensing errors by routing CS and VOUT using a kelvin sensing directly across the current sense resistor (R_{SENSE}).
- 4. Route high-speed switching nodes (HB, HO, LO, and SW) away from sensitive analog signals (FB, CS, and VOUT).

10.1.1 Layout Procedure

Place the power components first, with ground terminals adjacent to the low-side FET.

- Mount the controller IC as close as possible to the high and low-side MOSFETs. Make the grounds and high
 and low-sided drive gate drive lines as short and wide as possible. Place the series gate drive resistor as
 close to the MOSFET as possible to minimize gate ringing.
- Locate the gate drive components (D1 and C12) together and near the controller IC; refer to Figure 38. Be aware that peak gate drive currents can be as high as 4 A. Average current up to 75 mA can flow from the VCC pin to the V_{CC} capacitor through the bootstrap diode to the bootstrap capacitor. Size the traces accordingly.
- Figure 39 shows the high frequency loops of the synchronous buck converter. The high frequency current flows through Q1 and Q2, through the power ground plane and back to V_{IN} through the ceramic capacitors C6, C7, and C8. This loop must be as small as possible to minimize EMI. Refer to Figure 41 and Figure 42 for the recommended PCB layout.
- Make the PGND and AGND connections to the LM5141-Q1 controller as shown in Figure 40. Create a power grounds directly connected to all high-power components and an analog ground plane for sensitive analog components. The analog ground plane (AGND) and power ground plane (PGND) must be connected at a single point directly under the IC (at the die attach pad or DAP).

Product Folder Links: LM5141-Q1

pyright © 2016–2017, Texas instruments incorporated



10.2 Layout Examples




Figure 38. EVM Top Side




Figure 39. EVM Bottom Layer, High Frequency Current Loop



Layout Examples (continued)




Figure 40. AGND and PGND Connections

Figure 41 and Figure 42 show the top and bottom layer of the LM5141-Q1 EVM.




Figure 41. EVM Top Layer

Copyright © 2016–2017, Texas Instruments Incorporated

Submit Documentation Feedback



Layout Examples (continued)




Figure 42. EVM Bottom Layer



11 Device and Documentation Support

11.1 Custom Design With WEBENCH® Tools

Click here to create a custom design using the LM5141-Q1 device with the WEBENCH® Power Designer.

- 1. Start by entering the input voltage (V_{IN}), output voltage (V_{OUT}), and output current (I_{OUT}) requirements.
- 2. Optimize the design for key parameters such as efficiency, footprint, and cost using the optimizer dial.
- 3. Compare the generated design with other possible solutions from Texas Instruments.

The WEBENCH Power Designer provides a customized schematic along with a list of materials with real-time pricing and component availability.

In most cases, these actions are available:

- Run electrical simulations to see important waveforms and circuit performance
- Run thermal simulations to understand board thermal performance
- · Export customized schematic and layout into popular CAD formats
- Print PDF reports for the design, and share the design with colleagues

Get more information about WEBENCH tools at www.ti.com/WEBENCH.

11.2 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. In the upper right corner, click on *Alert me* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

11.3 Community Resources

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™ Online Community TI's Engineer-to-Engineer (E2E) Community. Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

Design Support *TI's Design Support* Quickly find helpful E2E forums along with design support tools and contact information for technical support.

11.4 Trademarks

E2E is a trademark of Texas Instruments.

WEBENCH is a registered trademark of Texas Instruments.

All other trademarks are the property of their respective owners.

11.5 Electrostatic Discharge Caution

Copyright © 2016-2017, Texas Instruments Incorporated



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

11.6 Glossary

SLYZ022 — TI Glossary.

This glossary lists and explains terms, acronyms, and definitions.

12 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

Draduot Folder Linker I ME4

www.ti.com 10-Nov-2025

PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS (3)	Lead finish/ Ball material	MSL rating/ Peak reflow	Op temp (°C)	Part marking (6)
LM5141QRGERQ1	Active	Production	VQFN (RGE) 24	3000 LARGE T&R	Yes	NIPDAU SN	Level-2-260C-1 YEAR	-40 to 150	LM5141 RGEQ1
LM5141QRGERQ1.A	Active	Production	VQFN (RGE) 24	3000 LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 150	LM5141 RGEQ1
LM5141QRGETQ1	Active	Production	VQFN (RGE) 24	250 SMALL T&R	Yes	NIPDAU SN	Level-2-260C-1 YEAR	-40 to 150	LM5141 RGEQ1
LM5141QRGETQ1.A	Active	Production	VQFN (RGE) 24	250 SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 150	LM5141 RGEQ1
LM5141QURGERQ1	Active	Production	VQFN (RGE) 24	3000 LARGE T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 150	5141Q RGEU
LM5141QURGERQ1.A	Active	Production	VQFN (RGE) 24	3000 LARGE T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 150	5141Q RGEU

⁽¹⁾ Status: For more details on status, see our product life cycle.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

⁽³⁾ RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

⁽⁴⁾ Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

⁽⁵⁾ MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

⁽⁶⁾ Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

PACKAGE OPTION ADDENDUM

www.ti.com 10-Nov-2025

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF LM5141-Q1:

Catalog: LM5141

NOTE: Qualified Version Definitions:

Catalog - TI's standard catalog product

PACKAGE MATERIALS INFORMATION

www.ti.com 3-Jun-2022

TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
LM5141QRGERQ1	VQFN	RGE	24	3000	330.0	12.4	4.25	4.25	1.15	8.0	12.0	Q2
LM5141QRGETQ1	VQFN	RGE	24	250	180.0	12.4	4.25	4.25	1.15	8.0	12.0	Q2
LM5141QURGERQ1	VQFN	RGE	24	3000	330.0	12.4	4.3	4.3	1.1	8.0	12.0	Q2

PACKAGE MATERIALS INFORMATION

www.ti.com 3-Jun-2022



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
LM5141QRGERQ1	VQFN	RGE	24	3000	367.0	367.0	35.0
LM5141QRGETQ1	VQFN	RGE	24	250	210.0	185.0	35.0
LM5141QURGERQ1	VQFN	RGE	24	3000	367.0	367.0	38.0



Images above are just a representation of the package family, actual package may vary. Refer to the product data sheet for package details.

4204104/H








NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
 2. This drawing is subject to change without notice.
- 3. The package thermal pad must be soldered to the printed circuit board for thermal and mechanical performance.





NOTES: (continued)

- 4. This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).
- 5. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.






NOTES: (continued)

6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.








NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
 2. This drawing is subject to change without notice.
- 3. The package thermal pad must be soldered to the printed circuit board for thermal and mechanical performance.






NOTES: (continued)

- 4. This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).
- 5. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.






NOTES: (continued)

6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.






NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
- 2. This drawing is subject to change without notice.
- 3. The package thermal pad must be soldered to the printed circuit board for optimal thermal and mechanical performance.






NOTES: (continued)

- 4. This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).
- 5. Vias are optional depending on application, refer to device data sheet. If any vias are implemented, refer to their locations shown on this view. It is recommended that vias under paste be filled, plugged or tented.





NOTES: (continued)

6. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale, TI's General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025