

TLV2721 Advanced CMOS, Rail-to-Rail, Very Low-Power, Single Operational Amplifier

1 Features

- Output swing includes both supply rails
- Low noise: $38nV/\sqrt{Hz}$ (typical) at f = 1kHz
- Low input bias current: 1pA (typical)
- Fully specified for single-supply 3V and 5V operation
- Very low power: 110µA (typical)
- Common-mode input voltage range includes negative rail
- Wide supply voltage range: 2.7V to 10V

2 Applications

- PC PSU and game console unit
- Merchant DC/DC
- Flow transmitter
- Pressure transmitter
- Merchant battery charger
- **Electricity meter**

3 Description

The TLV2721 is a single low-voltage operational amplifier available in the SOT-23 package. The TLV2721 offers a compromise between the ac performance and output drive of the TLV2731 and the micropower TLV2711. The device consumes only 150µA (max) of supply current and is an excellent choice for battery-powered applications. The device exhibits rail-to-rail output performance for increased dynamic range in single or split-supply applications.


The TLV2721 is fully characterized at 3V and 5V and is optimized for low-voltage applications. The TLV2721, exhibiting high input impedance and low noise, is excellent for small-signal conditioning for high-impedance sources, such as piezoelectric transducers. Because of the micropower dissipation levels combined with 3V operation, these devices work well in battery operated monitoring and remotesensing applications. In addition, the rail-to-rail output feature with single or split supplies makes this family a great choice when interfacing with analog-to-digital converters (ADCs).

With a total area of 5.6mm², the SOT-23 package only requires one third the board space of the standard 8-pin SOIC package. This ultra-small package allows designers to place single amplifiers very close to the signal source, minimizing noise pick-up from long PCB traces.

Package Information

PART NUMBER	PACKAGE ⁽¹⁾	PACKAGE SIZE ⁽²⁾
TLV2721	DBV (SOT-23, 5)	2.9mm × 2.8mm

- For all available packages, see Section 10.
- The package size (length × width) is a nominal value and includes pins, where applicable.



Difference Amplifier With RES11A-Q1



Table of Contents

1 Features1	6.1 Overview	. 13
2 Applications1	7 Application and Implementation	
3 Description1	7.1 Application Information	. 13
4 Pin Configuration and Functions2	8 Device and Documentation Support	. 15
5 Specifications3	8.1 Receiving Notification of Documentation Updates	
5.1 Absolute Maximum Ratings3	8.2 Support Resources	. 15
5.2 Recommended Operating Conditions3		
5.3 Thermal Information3	8.4 Electrostatic Discharge Caution	.15
5.4 Electrical Characteristics V _S = 3V4	8.5 Glossary	15
5.5 Electrical Characteristics V _S = 5V6	9 Revision History	. 15
5.6 Typical Characteristics8	10 Mechanical, Packaging, and Orderable	
6 Detailed Description13	Information	. 16

4 Pin Configuration and Functions




Figure 4-1. DBV Package, 5-Pin SOT-23 (Top View)

Table 4-1. Pin Functions

PIN		TYPE	DESCRIPTION
NAME	NO.	IIPE	DESCRIPTION
-IN	4	Input	Inverting input
+IN	3	Input	Noninverting input
OUT	1	Output	Output
V-	5	Power	Negative supply
V+	2	Power	Positive supply

Product Folder Links: TLV2721



5 Specifications

5.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

			MIN	MAX	UNIT
V _{DD}	Supply voltage, $(V_{DD+}) - (V_{DD-})^{(2)}$	Supply voltage, $(V_{DD+}) - (V_{DD-})^{(2)}$		12	V
V _{ID}	Differential input voltage ⁽³⁾			$\pm V_{DD}$	V
VI	Input voltage ⁽²⁾	Input voltage ⁽²⁾		V_{DD}	V
I _I	Input current (each input)			±5	mA
Io	Output current	Output current		±50	mA
		Into V _{DD+}		±50	mA
	Total current into supply pins	Into V _{DD} _		±50	IIIA
	Duration of short-circuit current (at o	r less than 25°C) ⁽⁴⁾	Unlimited		
TJ	Junction temperature			150	°C
T _{stg}	Storage temperature		-65	150	°C
	Lead temperature, 1.6mm (1/16 inch	n) from case for 10 seconds (DBV package)		260	°C

- (1) Operation outside the Absolute Maximum Ratings may cause permanent device damage. Absolute Maximum Ratings do not imply functional operation of the device at these or any other conditions beyond those listed under Recommended Operating Conditions. If used outside the Recommended Operating Conditions but within the Absolute Maximum Ratings, the device may not be fully functional, and this may affect device reliability, functionality, performance, and shorten the device lifetime
- (2) All voltage values, except differential voltages, are with respect to V_{DD}.
- (3) Differential voltages are at the noninverting input with respect to the inverting input. Excessive current flows when input is brought below (V_{DD}) 0.3V.
- (4) Temperature and/or supply voltages must be limited so that the maximum dissipation rating is not exceeded.

5.2 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

				MIN	NOM MAX	UNIT
V _{DD}	Supply voltage, (V _{DD+}) – (V _{DD})			2.7	10	V
VI	Input voltage		V _{DD} _	(V _{DD+}) – 1.3	V	
V _{IC}	Common-mode input voltage		V_{DD-}	(V _{DD+}) – 1.3	V	
T _A	Operating free-air temperature	TLV2721C		0	70	°C
	Operating free-all temperature	TLV2721I		-40	85	

5.3 Thermal Information

		TLV2721	
	THERMAL METRIC(1)	DBV (SOT5-23)	UNIT
		5 PINS	
R _{0JA}	Junction-to-ambient thermal resistance	192.1	°C/W
R _{0JC(top)}	Junction-to-case (top) thermal resistance	113.6	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	60.5	°C/W
ΨЈТ	Junction-to-top characterization parameter	37.2	°C/W
ΨЈВ	Junction-to-board characterization parameter	60.3	°C/W
R _{θJC(bot)}	Junction-to-case (bottom) thermal resistance	_	°C/W

(1) For more information about traditional and new thermal metrics, see the Semiconductor and IC Package Thermal Metrics application report.

Product Folder Links: TLV2721



5.4 Electrical Characteristics $V_S = 3V$

at T_A = 25°C, V_{DD} = 3V, R_L = 2k Ω connected to mid-supply, and V_{IC} = V_{OUT} = V_{DD} / 2 (unless otherwise noted).

	PARAMETER	TEST COND	DITIONS	MIN	TYP	MAX	UNIT	
OFFSET	VOLTAGE							
		TLV2721C, T _A = 0°C to 70°C			±0.5	±3		
V _{IO}	Input offset voltage	TLV2721I, T _A = -40°C to +85°C			±0.5	±3	mV	
	Input offset voltage	TLV2721C, T _A = 0°C to 70°C			±1			
dV _{IO} /dT	drift	TLV2721I, T _A = -40°C to +85°C			±1		μV/°C	
				70	95			
PSRR	Power supply rejection	V+ = 2.7V to 8V, no load	TLV2721C T _A = 0°C to 70°C	66			dB	
	ratio		TLV2721I T _A = -40°C to +85°C	66				
INPUT B	SIAS CURRENT							
,					±1	±60		
I _{IB}	Input bias current(1)	TLV2721C, T _A = 0°C to 70°C				±150	pA	
.5		TLV2721I, T _A = -40°C to +85°C				±150	·	
					±0.5	±60		
I _{IO}	Input offset current ⁽¹⁾	TLV2721C, T _A = 0°C to 70°C				±150	pА	
-10		TLV2721I, T _A = -40°C to +85°C				±150	P	
NOISE		1212121, 1 _M 10 2 10 20 2						
		f = 10Hz			120			
V _n	Input voltage noise	f = 1kHz			38		nV/√ Hz	
	Peak-to-peak	f = 0.1Hz to 1Hz			3			
V_{NPP}	equivalent input noise	f = 0.1Hz to 10Hz			6		μV	
_	voltage	T = 0.1HZ to 10HZ						
In	Input current noise				2		fA/√Hz	
			$V_0 = 1V \text{ to } 2V, f = 20kHz,$	G = 1		2.52		
THD +	Total harmonic	$R_L = 2k\Omega$ to 1.5V	G = 10		7.01		- %	
N	distortion plus noise	$V_0 = 1V \text{ to } 2V, f = 20kHz,$	G = 1		0.076			
		$R_L = 2k\Omega$ to 0V	G = 10		0.147			
INPUT V	OLTAGE RANGE							
				0 to 2 -0	.3 to +2.2			
V _{IC}	Common-mode input voltage	V _{IO} ≤ 5mV	TLV2721C T _A = 0°C to 70°C	0 to 1.7			V	
			TLV2721I $T_A = -40^{\circ}\text{C to } +85^{\circ}\text{C}$	0 to 1.7				
				58	77			
CMRR	Common-mode rejection ratio	V _{IC} = 0V to 1.7V	TLV2721C T _A = 0°C to 70°C	55			dB	
	rojection ratio		TLV2721I T _A = -40°C to +85°C	55				
INPUT C	APACITANCE							
	Innut regist	Differential			540 ⁹			
	Input resistance	Common-mode			10 ¹²		Ω	
C _{ic}	Common-mode input capacitance	f = 10kHz			6		pF	

 $\label{eq:copyright} \mbox{ @ 2025 Texas Instruments Incorporated} \\ \mbox{ Product Folder Links: } \mbox{ $TLV2721$}$

5.4 Electrical Characteristics $V_S = 3V$ (continued)

at T_A = 25°C, V_{DD} = 3V, R_L = 2k Ω connected to mid-supply, and V_{IC} = V_{OUT} = V_{DD} / 2 (unless otherwise noted).

	PARAMETER	TEST COND	ITIONS	MIN	TYP	MAX	UNIT
OPEN-	LOOP GAIN						
				2	3		
A_VD	Large-signal	$V_O = 1V$ to 2V, $R_L = 2k\Omega$	TLV2721C T _A = 0°C to 70°C	1			\(\lambda \)
	differential voltage amplification		TLV2721I T _A = -40°C to +85°C	1			V/mV
		$V_O = 1V$ to 2V, $R_L = 10k\Omega$			250		
FREQU	JENCY RESPONSE						
GBW	Gain bandwidth product	$f = 1kHz$, $C_L = 100pF$, $R_L = 2k\Omega$			480		kHz
Вом	Maximum output- swing bandwidth	V _O = 1V _{PP} , G = 1, C _L = 100pF, R _L = 2	2kΩ		30		kHz
SR	Slew rate	$G = 1, C_L = 100pF, R_L = 2k\Omega$			0.25		V/ms
t_	Settling time	$G = -1$, 1V to 2V step, $R_L = 2k\Omega$,	0.1%		4.5		μs
t _S	Settling time	C _L = 100pF	0.01%		6.8		
Θм	Phase margin at unity gain	$R_L = 2k\Omega$, $C_L = 100pF$			53		٥
G _M	Gain margin	$R_L = 2k\Omega$, $C_L = 100pF$			12		dB
OUTPL	JT		,			'	
		To positive rail, I _L = –100μA			2.97		
					2.88		
		To positive rail, I _L = -400µA	TLV2721C T _A = 0°C to 70°C	2.6			V
Vo		Voltage autout quier		TLV2721I T _A = -40°C to +85°C	2.6		
v _O	Voltage output swing	To negative rail, I _L = 50µA			15		
					150		
		To negative rail, I _L = 500μA	TLV2721C T _A = 0°C to 70°C			500	mV
			TLV2721I T _A = -40°C to +85°C			500	
Z _O	Closed-loop output impedance	f = 10kHz, G = 10			90		Ω
POWE	R SUPPLY						
					100	150	
I _{DD}	Supply current	No load	TLV2721C T _A = 0°C to 70°C			200	μА
			TLV2721I T _A = -40°C to +85°C			200	

⁽¹⁾ Specification established from device population bench system measurements across multiple lots.



5.5 Electrical Characteristics $V_S = 5V$

at T_A = 25°C, V_{DD} = 5V, R_L = 2k Ω connected to mid-supply, and V_{IC} = V_{OUT} = V_{DD} / 2 (unless otherwise noted).

	PARAMETER	TEST COND	DITIONS	MIN	TYP	MAX	UNIT	
OFFSET	VOLTAGE							
		TLV2721C, T _A = 0°C to 70°C			±0.5	±3		
V _{IO}	Input offset voltage	TLV2721I, T _A = -40°C to +85°C TLV2721C. T _A = 0°C to 70°C			±0.5	±3	mV	
	Input offset voltage drift	TLV2721C, T _A = 0°C to 70°C			±1			
dV _{OS} /dT		TLV2721I, T _A = -40°C to +85°C			±1		μV/°C	
				80	95			
PSRR	Power supply rejection ratio	V _{DD} = 4.4V to 8V, no load	TLV2721C T _A = 0°C to 70°C	80			dB	
	Tallo		TLV2721I T _A = -40°C to +85°C	80				
INPUT B	IAS CURRENT							
					±1	±60		
I _{IB}	Input bias current ⁽¹⁾	TLV2721C, T _A = 0°C to 70°C				±150	pA	
		TLV2721I, T _A = -40°C to +85°C			,	±150		
					±0.5	±60		
I _{IO}	Input offset current(1)	TLV2721C, T _A = 0°C to 70°C			,	±150	pA	
		TLV2721I, T _A = -40°C to +85°C			,	±150		
NOISE	1					'		
	t t	f = 10Hz			120		nV/√ Hz	
V _n	Input voltage noise	f = 1kHz			38		nv/√Hz	
V _{NPP} equivalent	Peak-to-peak	f = 0.1Hz to 1Hz			3			
	equivalent input noise voltage	f = 0.1Hz to 10Hz			6		μV	
In	Input current noise				2		fA/√ Hz	
		V _O = 1V to 3.5V,	G = 1		2.45			
THD +	Total harmonic	$f = 20kHz$, $R_L = 2k\Omega$ to 2.5V	G = 10		5.54		%	
N	distortion plus noise $V_O = 1V$	V _O = 1V to 3.5V,	G = 1		0.142			
		$f = 20kHz$, $R_L = 2k\Omega$ to $0V$	G = 10		0.257			
INPUT V	OLTAGE RANGE					'		
				0 to 4 -	0.3 to 4.2			
V _{IC}	Common-mode input voltage	V _{IO} ≤ 5mV	TLV2721C T _A = 0°C to 70°C	0 to 3.5			V	
	Vollage		TLV2721I T _A = -40°C to +85°C	0 to 3.5				
				70	85			
CMRR	Common-mode rejection ratio	V _{IC} = 0V to 2.7V, V _O = 1.5V	TLV2721C T _A = 0°C to 70°C	65			dB	
	,		TLV2721I T _A = -40°C to +85°C	65				
INPUT C	APACITANCE							
	Innut regist	Differential			540 ⁹			
	Input resistance	Common-mode			10 ¹²		Ω	
C _{ic}	Common-mode input capacitance	f = 10kHz			6		pF	

 $\label{eq:copyright} \mbox{ @ 2025 Texas Instruments Incorporated} \\ \mbox{ Product Folder Links: } \mbox{ $TLV2721$}$

5.5 Electrical Characteristics $V_S = 5V$ (continued)

at T_A = 25°C, V_{DD} = 5V, R_L = 2k Ω connected to mid-supply, and V_{IC} = V_{OUT} = V_{DD} / 2 (unless otherwise noted).

	PARAMETER	TEST CONDI	TIONS	MIN	TYP	MAX	UNIT
OPEN-	LOOP GAIN						
				3	5		
Λ	Large-signal differential voltage	$V_O = 1V$ to 4V, $R_L = 2k\Omega$	TLV2721C T _A = 0°C to 70°C	1			V/mV
A _{VD}	amplification		TLV2721I T _A = -40°C to +85°C	1			V/IIIV
		V_O = 1V to 4V, R_L = 1M Ω			800		
FREQU	JENCY RESPONSE						
GBW	Gain bandwidth product	$f = 1kHz$, $C_L = 100pF$, $R_L = 2k\Omega$			510		kHz
B _{OM}	Maximum output- swing bandwidth	V _O = 1V _{PP} , G = 1, C _L = 100pF, R _L = 2k	κΩ		40		kHz
SR	Slew rate	$G = 1$, $V_O = 1.5V$ to 3.5V, $C_L = 100pF$,	$R_L = 2k\Omega$		0.25		V/ms
t _S	Settling time	$G = -1$, 1.5V to 3.5V step, $R_L = 2kΩ$,	0.1%		6.8		μs
ıs	Setting time	C _L = 100pF	0.01%		9.2		μο
Θ_{M}	Phase margin at unity gain	$R_L = 2k\Omega$, $C_L = 100pF$			53		٥
G _M	Gain margin	$R_L = 2k\Omega$, $C_L = 100pF$			12		dB
OUTPL	JT						
		To positive rail, $I_L = -500\mu A$		4.75	4.88		V
		To positive rail, I _L = -1mA		4.6	4.76		V
		To negative rail, I _L = 50µA			12		
Vo	Voltage output swing				120		
		To negative rail, I _L = 500μA	TLV2721C T _A = 0°C to 70°C			500	mV
			TLV2721I T _A = -40°C to +85°C			500	
Z _O	Closed-loop output impedance	f = 10kHz, G = 10			70		Ω
POWE	R SUPPLY					'	
					100	150	
I _{DD}	Supply current	No load	TLV2721C T _A = 0°C to 70°C			200	μΑ
			TLV2721I T _A = -40°C to +85°C			200	

⁽¹⁾ Specification established from device population bench system measurements across multiple lots.



5.6 Typical Characteristics

for all curves where V_{DD} = 5V, all loads are referenced to 2.5V, for all curves where V_{DD} = 3V, all loads are referenced to 1.5V, data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices




Figure 5-1.




Figure 5-3.




Figure 5-5.




Figure 5-2. Input Offset Voltage vs Common-Mode Input Voltage $(V_{DD} = 3V)$




Figure 5-4.




Figure 5-6.

Submit Document Feedback

for all curves where V_{DD} = 5V, all loads are referenced to 2.5V, for all curves where V_{DD} = 3V, all loads are referenced to 1.5V, data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices




Figure 5-7.




Figure 5-9.




Figure 5-11.




Figure 5-8.




Figure 5-10.




Figure 5-12.



for all curves where V_{DD} = 5V, all loads are referenced to 2.5V, for all curves where V_{DD} = 3V, all loads are referenced to 1.5V, data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices




Figure 5-13.




Figure 5-15.




Figure 5-17.




Figure 5-14. Common-Mode and Power Supply Rejection Ratio ($V_{DD} = 3V$)




Figure 5-16.




Figure 5-18.

for all curves where V_{DD} = 5V, all loads are referenced to 2.5V, for all curves where V_{DD} = 3V, all loads are referenced to 1.5V, data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices




Figure 5-19.




Figure 5-21.




Figure 5-23.




Figure 5-20.




Figure 5-22.




Figure 5-24. Input Voltage Noise Density (V_{DD} = 3V)



for all curves where V_{DD} = 5V, all loads are referenced to 2.5V, for all curves where V_{DD} = 3V, all loads are referenced to 1.5V, data at high and low temperatures are applicable only within the rated operating free-air temperature ranges of the various devices




Figure 5-25. 0.1Hz to 10Hz Noise




Figure 5-27.




Figure 5-26.




Figure 5-28.

Submit Document Feedback

Copyright © 2025 Texas Instruments Incorporated

6 Detailed Description

6.1 Overview

The TLV2721 is a single operational amplifier available in the small SOT-23 package. The TLV2721 offers low supply-current consumption and low noise. An advanced CMOS process enables the device to achieve excellent rail-to-rail output swing performance along with high input impedance. The combination of features make this device an excellent choice for a wide range of applications, including many battery-operated systems.

7 Application and Implementation

Note

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes, as well as validating and testing their design implementation to confirm system functionality.

7.1 Application Information

7.1.1 Driving Large Capacitive Loads

The TLV2721 is designed to drive larger capacitive loads than most CMOS operational amplifiers. Figure 5-27 and Figure 5-28 illustrate an ability to drive loads greater than 100pF while maintaining good gain and phase margins ($R_{null} = 0\Omega$).

A small series resistor (R_{null}) at the output of the device (Figure 7-1) improves the gain and phase margins when driving large capacitive loads. Figure 5-27 and Figure 5-28 show the effects of adding series resistances of 100Ω , 200Ω , 500Ω , and $1k\Omega$. The addition of this series resistor has two effects: the first effect is that the resistor adds a zero to the transfer function and the second effect is that the resistor reduces the frequency of the pole associated with the output load in the transfer function.

The zero introduced to the transfer function is equal to the series resistance times the load capacitance. To calculate the approximate improvement in phase margin, use the following equation:

$$\Delta \phi_{m1} = \tan^{-1}(2\pi \times UGBW \times R_{null} \times C_L)$$
 (1)

Where:

 $\Delta \phi_{m1}$ = Improvement in phase margin

UGBW = Unity-gain bandwidth frequency

R_{null} = Output series resistance

C_L = Load capacitance

The unity-gain bandwidth (UGBW) frequency decreases as the capacitive load increases. To use Equation 1, approximate UGBW for the given capacitive load in Figure 7-1.




Figure 7-1. Series Resistance Circuit



The TLV2721 is designed to provide better sinking and sourcing output currents than earlier CMOS rail-to-rail output devices. This device is specified to sink $500\mu A$ and source 1mA at V_{DD} = 5V at a maximum quiescent I_{DD} of $200\mu A$. This provides a greater than 80% power efficiency.

When driving heavy dc loads, such as $2k\Omega$, the positive edge under slewing conditions can experience some distortion; see also Figure 5-22. This condition is affected by three factors:

- Where the load is referenced. When the load is referenced to either rail, this condition does not occur. The
 distortion occurs only when the output signal swings through the point where the load is referenced. Figure
 5-23 illustrates two 2kΩ load conditions. The first load condition shows the distortion seen for a 2kΩ load tied
 to 2.5V. The third load condition in Figure 5-23 shows no distortion for a 2kΩ load tied to 0V.
- Load resistance. As the load resistance increases, the distortion seen on the output decreases. Figure 5-23 illustrates the difference seen on the output for a $2k\Omega$ load and a $100k\Omega$ load with both tied to 2.5V.
- Input signal edge rate. Faster input edge rates for a step input result in more distortion than with slower input edge rates.

Copyright © 2025 Texas Instruments Incorporated Product Folder Links: *TLV2721*



8 Device and Documentation Support

TI offers an extensive line of development tools. Tools and software to evaluate the performance of the device, generate code, and develop solutions are listed below.

8.1 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. Click on *Notifications* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

8.2 Support Resources

TI E2E™ support forums are an engineer's go-to source for fast, verified answers and design help — straight from the experts. Search existing answers or ask your own question to get the quick design help you need.

Linked content is provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

8.3 Trademarks

TI E2E[™] is a trademark of Texas Instruments.

All trademarks are the property of their respective owners.

8.4 Electrostatic Discharge Caution



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

8.5 Glossary

TI Glossary

This glossary lists and explains terms, acronyms, and definitions.

9 Revision History

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

C	nanges from Revision A (March 2001) to Revision B (July 2025)	ige
•	Updated the numbering format for tables, figures, and cross-references throughout the document	1
	Description, Overview, Application and Implementation, Device and Documentation Support, and Mechanic Packaging, and Orderable Information sections	_
•	Deleted TLV2721Y device and associated content from data sheet	
•	Deleted references to LinCMOS™ throughout data sheet	1
•	Deleted "Macromodel included" from Features	
•	Changed low noise from 19nV/√Hz to 38nV/√Hz in <i>Features</i>	
•	Updated note 4 in Absolute Maximum Ratings	3
•	Added Thermal Information	
•	Deleted Dissipation Ratings Table	3
•	Added ± to input offset voltage, input offset voltage drift, input bias current, and input offset current in 3V an 5V <i>Electrical Characteristics</i>	
•	Deleted input offset voltage long-term drift from 3V and 5V Electrical Characteristics	4
•	Changed power supply rejection ratio MIN from 80dB to 70dB in 3V Electrical Characteristics	4
•	Changed power supply rejection ratio (–40°C to +85°C and 0°C to 70°C) from 80dB to 66dB in 3V <i>Electrica Characteristics</i>	il 4
•	Deleted all notes from 3V and 5V Electrical Characteristics	4
•	Added note 1 to 3V and 5V Electrical Characteristics	4

Copyright © 2025 Texas Instruments Incorporated



•	Changed input voltage noise (1kHz) from 20nV/√Hz to 38nV/√Hz in 3V <i>Electrical Characteristics</i>	4
•	Changed peak to peak equivalent noise voltage units from mV to nV (typo) in all Electrical Characteristics.	4
•	Changed peak-to-peak equivalent noise voltage (0.1Hz to 1Hz) from 680nV to 3µV in 3V Electrical	
	Characteristics	4
•	Changed peak-to-peak equivalent noise voltage (0.1Hz to 10Hz) from 860nV to 6µV in 3V Electrical	
	Characteristics	4
•	Changed input current noise from 0.6fA/ $\sqrt{\text{Hz}}$ to 2fA/ $\sqrt{\text{Hz}}$ in 3V and 5V <i>Electrical Characteristics</i>	4
•	Changed common-mode rejection ratio MIN from 70dB to 58dB and TYP from 82dB to 77dB in 3V Electrical	эl
	Characteristics	4
•	Changed common-mode rejection ratio (0°C to 70°C and -40°C and +85°C) MIN from 65dB to 55dB in	
	3V Electrical Characteristics	4
•	Changed input resistance (differential) from $10^{12}\Omega$ to $540^9\Omega$ in 3V and 5V <i>Electrical Characteristics</i>	4
•	Deleted slew rate at unity gain MIN for 25°C and full range on 3V and 5V Electrical Characteristics tables	4
•	Changed input voltage noise (10Hz) from 90nV/\(\sqrt{Hz}\) to 120nV/\(\sqrt{Hz}\) in 5V Electrical Characteritics	
•	Changed input voltage noise (1kHz) from 19nV/\(\sqrt{Hz}\) to 38nV/\(\sqrt{Hz}\) in 5V Electrical Characteristics	6
•	Changed peak-to-peak equivalent noise voltage (0.1Hz to 1Hz) from 800nV to 3µV in 5V <i>Electrical</i>	
	Characteristics	6
•	Changed peak-to-peak equivalent noise voltage (0.1Hz to 10Hz) from 960nV to 6µV in 5V <i>Electrical</i>	
	Characteristics	6
•	Deleted Figures 1, 4–5, 10–14, 16–20, 27–31, 33–34, 45, 47–50, and 53–54	8
•	Updated Figures 5-2, 5-23, and 5-24	8
•	Added Figure 5-14	8
•	Deleted Macromodel Information	13

10 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

Product Folder Links: TLV2721

www.ti.com 24-Nov-2025

PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS	Lead finish/ Ball material	3		Part marking
	(1)	(2)			(3)	(4)	(5)		(6)
						()			
TLV2721CDBVR	Active	Production	SOT-23 (DBV) 5	3000 LARGE T&R	Yes	SN	Level-1-260C-UNLIM	0 to 70	VAKC
TLV2721CDBVR.A	Active	Production	SOT-23 (DBV) 5	3000 LARGE T&R	Yes	SN	Level-1-260C-UNLIM	0 to 70	VAKC
TLV2721CDBVT	Obsolete	Production	SOT-23 (DBV) 5	-	-	Call TI	Call TI	=	VAKC
TLV2721IDBVR	Active	Production	SOT-23 (DBV) 5	3000 LARGE T&R	Yes	Call TI Sn	Level-1-260C-UNLIM	-40 to 85	VAKI
TLV2721IDBVR.A	Active	Production	SOT-23 (DBV) 5	3000 LARGE T&R	Yes	Call TI Sn	Level-1-260C-UNLIM	-40 to 85	VAKI

⁽¹⁾ Status: For more details on status, see our product life cycle.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

⁽³⁾ RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

⁽⁴⁾ Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

⁽⁵⁾ MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

⁽⁶⁾ Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

PACKAGE MATERIALS INFORMATION

www.ti.com 20-Nov-2025

TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device		Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TLV2721CDBVR	SOT-23	DBV	5	3000	180.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3
TLV2721IDBVR	SOT-23	DBV	5	3000	180.0	8.4	3.2	3.2	1.4	4.0	8.0	Q3

www.ti.com 20-Nov-2025



*All dimensions are nominal

	Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)	
ı	TLV2721CDBVR	SOT-23	DBV	5	3000	210.0	185.0	35.0	
ı	TLV2721IDBVR	SOT-23	DBV	5	3000	210.0	185.0	35.0	



SMALL OUTLINE TRANSISTOR



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
 2. This drawing is subject to change without notice.
 3. Reference JEDEC MO-178.

- 4. Body dimensions do not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.25 mm per side.
- 5. Support pin may differ or may not be present.



SMALL OUTLINE TRANSISTOR



NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.

7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SMALL OUTLINE TRANSISTOR



NOTES: (continued)

- 8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
- 9. Board assembly site may have different recommendations for stencil design.



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale, TI's General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025