

SBOS056F – JANUARY 2002 – JULY 2005


High-Voltage, High-Current OPERATIONAL AMPLIFIER

FEATURES

- WIDE SUPPLY RANGE Single Supply: +8V to +60V Dual Supply: ±4V to ±30V
- HIGH OUTPUT CURRENT: 500mA Continuous
- WIDE OUTPUT VOLTAGE SWING
- FULLY PROTECTED: Thermal Shutdown Adjustable Current Limit
- OUTPUT DISABLE CONTROL
- THERMAL SHUTDOWN INDICATOR
- HIGH SLEW RATE: 6V/μs
- LOW QUIESCENT CURRENT
- PACKAGES:
 7-Lead TO-220, Zip and Straight Leads
 7-Lead DDPAK Surface-Mount

APPLICATIONS

- VALVE, ACTUATOR DRIVERS
- SYNCHRO, SERVO DRIVERS
- POWER SUPPLIES
- TEST EQUIPMENT
- TRANSDUCER EXCITATION
- AUDIO AMPLIFIERS



DESCRIPTION

The OPA547 is a low-cost, high-voltage/high-current operational amplifier ideal for driving a wide variety of loads. A laser-trimmed monolithic integrated circuit provides excellent low-level signal accuracy and high output voltage and current

The OPA547 operates from either single or dual supplies for design flexibility. In single-supply operation, the input common-mode range extends below ground.

The OPA547 is internally protected against over-temperature conditions and current overloads. In addition, the OPA547 was designed to provide an accurate, user-selected current limit. Unlike other designs which use a "power" resistor in series with the output current path, the OPA547 senses the load indirectly. This allows the current limit to be adjusted from 0mA to 750mA with a 0 to 150 μ A control signal. This is easily done with a resistor/potentiometer or controlled digitally with a voltage-out or current-out DAC.

The Enable/Status (E/S) pin provides two functions. An input on the pin not only disables the output stage to effectively disconnect the load, but also reduces the quiescent current to conserve power. The E/S pin output can be monitored to determine if the OPA547 is in thermal shutdown.

The OPA547 is available in an industry-standard 7-lead staggered and straight lead TO-220 package, and a 7-lead DDPAK surface-mount plastic power package. The copper tab allows easy mounting to a heat sink or circuit board for excellent thermal performance. It is specified for operation over the extended industrial temperature range, -40°C to +85°C.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.



ABSOLUTE MAXIMUM RATINGS(1)

Output Current	60V (V–) – 0.5V to (V+) + 0.5V
Input Shutdown Voltage Operating Temperature	
Storage Temperature Junction Temperature	
Lead Temperature (soldering 10s)(2)	

NOTES: (1) Stresses above these ratings may cause permanent damage. (2) Vapor-phase or IR reflow techniques are recommended for soldering the OPA547F surface-mount package. Wave soldering is not recommended due to excessive thermal shock and "shadowing" of nearby devices.




This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

PACKAGE/ORDERING INFORMATION

For the most current package and ordering information, see the Package Ordering Addendum at the end of this document, or see the TI website at www.ti.com.

PIN CONFIGURATIONS



ELECTRICAL CHARACTERISTICS


At T_{CASE} = +25°C, V_{S} = ±30V and E/S pin open, unless otherwise noted.


			OPA547T, F				
PARAMETER	CONDITION	MIN	TYP	MAX	UNITS		
OFFSET VOLTAGE							
Input Offset Voltage	$V_{CM} = 0, I_{O} = 0$		±1	±5	mV		
vs Temperature	$V_{CM} = 0, V_{C} = 0$ $T_{\Delta} = -40^{\circ}\text{C to } +85^{\circ}\text{C}$		±25	±3	μV/°C		
•	$V_S = \pm 4V \text{ to } \pm 30V$		10	100	μV/ C μV/V		
vs Power Supply	V _S = ±4√ t0 ±30√		10	100	μν/ν		
INPUT BIAS CURRENT ⁽¹⁾							
Input Bias Current ⁽²⁾	$V_{CM} = 0V$		-100	-500	nA		
vs Temperature			±0.5		nA/°C		
Input Offset Current	$V_{CM} = 0V$		±5	±50	nA		
NOISE							
Input Voltage Noise Density, f = 1kHz			90		nV/√Hz		
Current Noise Density, f = 1kHz			200		fA/√Hz		
INPUT VOLTAGE RANGE							
Common-Mode Voltage Range: Positive	Linear Operation	(V+) -3	(V+) -2.3		V		
Negative	Linear Operation	(V-) -0.1	(V-) -0.2		ľ		
Common-Mode Rejection	$V_{CM} = (V-) -0.1V \text{ to } (V+) -3V$	80	95		dB		
·	V _{CM} = (V) 0.11 to (V1) 3V		30		ų d		
INPUT IMPEDANCE							
Differential			10 ⁷ 6		Ω pF		
Common-Mode			109 4		Ω pF		
OPEN-LOOP GAIN					_		
Open-Loop Voltage Gain, f = 10Hz	$V_O = \pm 25V$, $R_L = 1k\Omega$	100	115		dB		
	$V_0 = \pm 25V, R_L = 50\Omega$		110		dB		
FREQUENCY RESPONSE	-						
Gain-Bandwidth Product	$R_1 = 50\Omega$		1		MHz		
Slew Rate	$G = 1,50V_{PP}, R_L = 50\Omega$		6		V/µs		
Full-Power Bandwidth	0 = 1, 30 Vpp, 1\(\(\) = 30\(\)2		See Typical Curve		kHz		
Settling Time: ±0.1%	G = -10, 50V Step		18		μs		
Total Harmonic Distortion + Noise, f = 1kHz	$R_L = 50\Omega$, $G = +3V$, 1W Power		0.004(3)		μs %		
<u> </u>	11 = 3022, G = +3V, TW T OWEI		0.004(*)		/0		
OUTPUT							
Voltage Output, Positive	$I_{O} = 0.5A$	(V+) −2.2	(V+) −1.9		V		
Negative	$I_{O} = -0.5A$	(V-) +1.6	(V-) +1.3		V		
Positive	$I_{O} = 0.1A$	(V+) -1.8	(V+) −1.5		V		
Negative	$I_{O} = -0.1A$	(V-) +1.2	(V-) +0.8		V		
Maximum Continuous Current Output: dc		±500			mA		
ac		500			mArms		
Leakage Current, Output Disabled, dc			See Typical Curve				
Output Current Limit							
Current Limit Range			0 to ±750		mA		
Current Limit Equation		$I_{LIM} = ($	5000)(4.75)/(31600	2 + R _{CL})	Α		
Current Limit Tolerance ⁽¹⁾	$R_{CL} = 31.6k\Omega (I_{LIM} = \pm 375mA),$		±10	±30	mA		
	$R_L = 50\Omega$						
Capacitive Load Drive			See Typical Curve ⁽⁴⁾)			
OUTPUT ENABLE /STATUS (E/S) PIN							
Shutdown Input Mode					1		
V _{E/S} HIGH (output enabled)	E/S Pin Open or Forced HIGH	(V-) +2.4			V		
V _{E/S} LOW (output disabled)	E/S Pin Forced LOW	(· , · = · ·		(V-) +0.8	v		
I _{E/S} HIGH (output enabled)	E/S Pin HIGH		-60	(. , . 0.0	μΑ		
I _{E/S} LOW (output disabled)	E/S Pin LOW		_65		μΑ		
Output Disable Time	2,3 1 111 20 44		1		μS		
Output Disable Time Output Enable Time			3		μs μs		
Thermal Shutdown Status Output					μ ο		
Normal Operation	Sourcing 20μA	(V-) +2.4	(V-) +3.5		V		
Thermally Shutdown	Sinking 5μA, T _J > 160°C	(V-) TZ.4	(V-) +0.35	(V-) +0.8	ľ		
Junction Temperature, Shutdown	Sinking 5μA, 1 _J > 160°C		(V-) +0.35 +160	(v-) +U.8	°C v		
Reset from Shutdown			+140		.€		
	+		T140		 		
POWER SUPPLY					1		
Specified Voltage			±30		V		
Operating Voltage Range		±4		±30	V		
Quiescent Current	I_{LIM} Connected to V-, $I_O = 0$		±10	±15	mA		
Quiescent Current, Shutdown Mode	I _{LIM} Connected to V-		<u>±</u> 4		mA		
TEMPERATURE RANGE							
Specified Range		-40		+85	°c		
Operating Range		–40		+125	l ∘c		
Storage Range		-55		+125	l ∘c		
Thermal Resistance, θ_{IC}		33		. 120	I		
7-Lead DDPAK, 7-Lead TO-220	f > 50Hz		2		°C/W		
7-Lead DDPAK, 7-Lead TO-220 7-Lead DDPAK, 7-Lead TO-220	1 > 30Hz		3		°C/W		
, Load DDI /III, / Load I O-220	l uc				I 5, vv		
Thermal Resistance A							
Thermal Resistance, $\theta_{ m JA}$ 7-Lead DDPAK, 7-Lead TO-220	No Heat Sink		65		°C/W		


NOTES: (1) High-speed test at $T_J = +25$ °C. (2) Positive conventional current flows into the input terminals. (3) See *Total Harmonic Distortion+Noise* in the Typical Characteristics section for additional power levels. (4) See *Small-Signal Overshoot vs Load Capacitance* in the Typical Characteristics section.


TYPICAL CHARACTERISTICS


At T_{CASE} = +25°C, V_{S} = ± 30 V, and E/S pin open, unless otherwise noted.




















TYPICAL CHARACTERISTICS (Cont.)


At T_{CASE} = +25°C, V_S = ±30V, and E/S pin open, unless otherwise noted.






















TYPICAL CHARACTERISTICS (Cont.)


At T_{CASE} = +25°C, V_{S} = ±30V, and E/S pin open, unless otherwise noted.


















TYPICAL CHARACTERISTICS (Cont.)

At T_{CASE} = +25°C, V_S = ± 35 V, and E/S pin open, unless otherwise noted.

SMALL SIGNAL STEP RESPONSE G = 1, $C_L = 1000 pF$



LARGE SIGNAL STEP RESPONSE $G=3,\,C_L=100pF,\,R_L=50\Omega$







APPLICATIONS INFORMATION

Figure 1 shows the OPA547 connected as a basic noninverting amplifier. The OPA547 can be used in virtually any op amp configuration.

Power-supply terminals should be bypassed with low series impedance capacitors. The technique shown, using a ceramic and tantalum type in parallel, is recommended. Power-supply wiring should have low series impedance.




FIGURE 1. Basic Circuit Connections.

POWER SUPPLIES

The OPA547 operates from single (+8V to +60V) or dual (\pm 4V to \pm 30V) supplies with excellent performance. Most behavior remains unchanged throughout the full operating voltage range. Parameters which vary significantly with operating voltage are shown in the typical characteristic curves.

Some applications do not require equal positive and negative output voltage swing. Power-supply voltages do not need to be equal. The OPA547 can operate with as little as 8V between the supplies and with up to 60V between the supplies. For example, the positive supply could be set to 55V with the negative supply at –5V, or vice-versa.

ADJUSTABLE CURRENT LIMIT

The OPA547 features an accurate, user-selected current limit. Current limit is set from 0mA to 750mA by controlling the input to the I_{LIM} pin. Unlike other designs which use a power resistor in series with the output current path, the OPA547 senses the load indirectly. This allows the current limit to be set with a 0 μ A to 150 μ A control signal. In contrast, other designs require a limiting resistor to handle the full output current (750mA in this case).

With the OPA547, the simplest method for adjusting the current limit uses a resistor or potentiometer connected between the I_{LIM} pin and V- according to the Equation 1:

$$R_{CL} = \frac{(5000)(4.75)}{I_{LIM}} - 31.6k\Omega \tag{1}$$

The low-level control signal (0 μ A to 150 μ A) also allows the current limit to be digitally controlled with a current-out or voltage-out DAC reference to V– according to the equations given in Figure 3.

Figure 3 shows a simplified schematic of the internal circuitry used to set the current limit. Leaving the I_{LIM} pin open programs the output current to zero, while connecting I_{LIM} directly to V– programs the maximum output current limit, typically 750mA.

SAFE OPERATING AREA

Stress on the output transistors is determined both by the output current and by the output voltage across the conducting output transistor, $V_S - V_O$. The power dissipated by the output transistor is equal to the product of the output current and the voltage across the conducting transistor, $V_S - V_O$. The Safe Operating Area (SOA curve, Figure 2) shows the permissible range of voltage and current.




FIGURE 2. Safe Operating Area.

The safe output current decreases as $V_S - V_O$ increases. Output short-circuits are a very demanding case for SOA. A short-circuit to ground forces the full power-supply voltage (V+ or V–) across the conducting transistor. With $T_C = 25^{\circ}C$ the maximum output current of 500mA can be achieved under most conditions. Increasing the case temperature reduces the safe output current that can be tolerated without activating the thermal shutdown circuit of the OPA547. For further insight on SOA, consult Application Bulletin SBOA022.

POWER DISSIPATION

Power dissipation depends on power supply, signal, and load conditions. For dc signals, power dissipation is equal to the product of output current times the voltage across the con-



ducting output transistor. Power dissipation can be minimized by using the lowest possible power-supply voltage necessary to assure the required output voltage swing.

For resistive loads, the maximum power dissipation occurs at a dc output voltage of one-half the power-supply voltage. Dissipation with ac signals is lower. Application Bulletin SBOA022 explains how to calculate or measure power dissipation with unusual signals and loads.

HEAT SINKING

Most applications require a heat sink to assure that the maximum junction temperature (150°C) is not exceeded. The heat sink required depends on the power dissipated and on

ambient conditions. Consult Application Bulletin SBOA021 for information on determining heat sink requirements. The internal protection circuitry was designed to protect against overload conditions. It does not activate until the junction temperature reaches approximately 160°C and was not intended to replace proper heat sinking. Continuously running the OPA547 into thermal shutdown will degrade reliability.

The tab of the DDPAK surface-mount version should be soldered to a circuit board copper area for good heat dissipation. Figure 4 shows typical thermal resistance from junction to ambient as a function of the copper area.




FIGURE 3. Adjustable Current Limit.




FIGURE 4. Thermal Resistance versus Circuit Board Copper Area.





THERMAL PROTECTION

The OPA547 has thermal shutdown that protects the amplifier from damage. Activation of the thermal shutdown circuit during normal operation is an indication of excessive power dissipation or an inadequate heat sink. Depending on load and signal conditions, the thermal protection circuit may cycle on and off. This limits the dissipation of the amplifier but may have an undesirable effect on the load.

The thermal protection activates at a junction temperature of approximately 160°C. However, for reliable operation, junction temperature should be limited to 150°C. To estimate the margin of safety in a complete design (including heat sink), increase the ambient temperature until the thermal protection is activated. Use worst-case load and signal conditions. For good reliability, the thermal protection should trigger more than 35°C above the maximum expected ambient condition of the application. This produces a junction temperature of 125°C at the maximum expected ambient condition.

ENABLE/STATUS (E/S) PIN

The Enable/Status pin provides two functions: forcing this pin low disables the output stage, or E/S can be monitored to determine if the OPA547 is in thermal shutdown. One or both of these functions can be utilized on the same device using single or dual supplies. For normal operation (output enabled), the E/S pin can be left open or pulled high (at least +2.4V above the negative rail).

Output Disable

A unique feature of the OPA547 is its output disable capability. This function not only conserves power during idle periods (quiescent current drops to approximately 4mA), but also allows multiplexing in low frequency (f<10kHz), multichannel applications. Signals that are greater than 10kHz may cause leakage current to increase in devices that are shutdown. Figure 15 shows the two OPA547s in a switched amplifier configuration. The on/off state of the two amplifiers is controlled by the voltage on the E/S pin.

To disable the output, the E/S pin is pulled low, no greater than 0.8V above the negative rail. Typically the output is shutdown in 1 μ s. Figure 5 provides an example of how to implement this function using a single supply. Figure 6 gives a circuit for dual-supply applications. To return the output to an enabled state, the E/S pin should be disconnected (open) or pulled to at least (V–) + 2.4V. It should be noted that pulling the E/S pin high (output enabled) does not disable internal thermal shutdown.




FIGURE 5. Output Disable with a Single Supply.




FIGURE 6. Output Disable with Dual Supplies.

Thermal Shutdown Status

Internal thermal shutdown circuitry shuts down the output when the die temperature reaches approximately 160°C, resetting when the die has cooled to 140°C. The E/S pin can be monitored to determine if shutdown has occurred. During normal operation the voltage on the E/S pin is typically 3.5V above the negative rail. Once shutdown has occurred this voltage drops to approximately 350mV above the negative rail.

Figure 7 gives an example of monitoring shutdown in a single-supply application. Figure 8 provides a circuit for dual supplies. External logic circuitry or an LED could be used to indicate if the output has been thermally shutdown, see Figure 13.




FIGURE 7. Thermal Shutdown Status with a Single Supply.




FIGURE 8. Thermal Shutdown Status with Dual Supplies.



Output Disable and Thermal Shutdown Status

As mentioned earlier, the OPA547's output can be disabled and the disable status can be monitored simultaneously. Figures 9 and 10 provide examples using a single supply and dual supplies, respectively.




FIGURE 9. Output Disable and Thermal Shutdown Status with a Single Supply.

OUTPUT STAGE COMPENSATION

The complex load impedances common in power op amp applications can cause output stage instability. For normal operation output compensation circuitry is not typically required. However, if the OPA547 is intended to be driven into current limit, a R/C network may be required. Figure 11 shows an output series R/C compensation (snubber) network (3 Ω in series with 0.01 μF) which generally provides excellent stability. Some variations in circuit values may be required with certain loads.

OUTPUT PROTECTION

Reactive and EMF-generating loads can return load current to the amplifier, causing the output voltage to exceed the power-supply voltage. This damaging condition can be avoided with clamp diodes from the output terminal to the power supplies, as shown in Figure 11. Schottkey rectifier diodes with a 1A or greater continuous rating are recommended.




FIGURE 11. Motor Drive Circuit.




FIGURE 10. Output Disable and Thermal Shutdown Status with Dual Supplies.





VOLTAGE SOURCE APPLICATION

Figure 12 illustrates how to use the OPA547 to provide an accurate voltage source with only three external resistors. First, the current limit resistor, R_{CL} , is chosen according to the desired output current. The resulting voltage at the I_{LIM} pin is constant and stable over temperature. This voltage, V_{CL} , is connected to the noninverting input of the op amp and used as a voltage reference, thus eliminating the need for an external reference. The feedback resistors are selected to gain V_{CL} to the desired output voltage level.

PROGRAMMABLE POWER SUPPLY

A programmable power supply can easily be built using the OPA547. Both the output voltage and output current are user-controlled. Figure 13 shows a circuit using potentiometers to adjust the output voltage and current while Figure 14 uses DACs. An LED tied to the E/S pin through a logic gate indicates if the OPA547 is in thermal shutdown.




FIGURE 12. Voltage Source.




FIGURE 13. Resistor-Controlled Programmable Power Supply.






FIGURE 14. Digitally-Controlled Programmable Power Supply.




FIGURE 15. Swap Amplifier.




FIGURE 16. Multiple Current Limit Values.

11-Nov-2025 www.ti.com

PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS	Lead finish/ Ball material	MSL rating/ Peak reflow	Op temp (°C)	Part marking
						(4)	(5)		
OPA547F/500	Active	Production	DDPAK/TO-263 (KTW) 7	500 LARGE T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 85	OPA547F
OPA547F/500.A	Active	Production	DDPAK/TO-263 (KTW) 7	500 LARGE T&R	Yes	SN Level-2-260C-1 YEAR		-40 to 85	OPA547F
OPA547FKTWT	Active	Production	DDPAK/TO-263 (KTW) 7	250 SMALL T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 85	OPA547F
OPA547FKTWT.A	Active	Production	DDPAK/TO-263 (KTW) 7	250 SMALL T&R	Yes	SN	Level-2-260C-1 YEAR	-40 to 85	OPA547F
OPA547T	Active	Production	TO-220 (KVT) 7	50 TUBE	Yes	SN	N/A for Pkg Type	-40 to 85	OPA547T
OPA547T-1	Active	Production	TO-220 (KC) 7	50 TUBE	Yes	SN	N/A for Pkg Type	-40 to 85	OPA547T
OPA547T-1.A	Active	Production	TO-220 (KC) 7	50 TUBE	Yes	SN	N/A for Pkg Type	-40 to 85	OPA547T
OPA547T.A	Active	Production	TO-220 (KVT) 7	50 TUBE	Yes	SN	N/A for Pkg Type	-40 to 85	OPA547T
OPA547TG3	Active	Production	TO-220 (KVT) 7	50 TUBE	-	Call TI	Call TI	-40 to 85	

⁽¹⁾ Status: For more details on status, see our product life cycle.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

⁽³⁾ RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

⁽⁴⁾ Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

⁽⁵⁾ MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

⁽⁶⁾ Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.



PACKAGE OPTION ADDENDUM

www.ti.com 11-Nov-2025

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

PACKAGE MATERIALS INFORMATION

www.ti.com 22-Sep-2025

TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
OPA547F/500	DDPAK/ TO-263	KTW	7	500	330.0	24.4	10.6	15.8	4.9	16.0	24.0	Q2
OPA547FKTWT	DDPAK/ TO-263	KTW	7	250	330.0	24.4	10.6	15.8	4.9	16.0	24.0	Q2

www.ti.com 22-Sep-2025



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
OPA547F/500	DDPAK/TO-263	KTW	7	500	356.0	356.0	45.0
OPA547FKTWT	DDPAK/TO-263	KTW	7	250	356.0	356.0	45.0

PACKAGE MATERIALS INFORMATION

www.ti.com 22-Sep-2025

TUBE




*All dimensions are nominal

Device	Package Name	Package Type	Pins	SPQ	L (mm)	W (mm)	T (µm)	B (mm)
OPA547T	KVT	TO-220	7	50	532.13	34.54	13340	NA
OPA547T-1	KC	TO-220	7	50	532.13	34.54	13340	NA
OPA547T-1.A	KC	TO-220	7	50	532.13	34.54	13340	NA
OPA547T.A	KVT	TO-220	7	50	532.13	34.54	13340	NA

KTW (R-PSFM-G7)

PLASTIC FLANGE-MOUNT



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

Lead width and height dimensions apply to the plated lead.


- D. Leads are not allowed above the Datum B.
- E. Stand-off height is measured from lead tip with reference to Datum B.

Lead width dimension does not include dambar protrusion. Allowable dambar protrusion shall not cause the lead width to exceed the maximum dimension by more than 0.003".

G. Cross-hatch indicates exposed metal surface.

Falls within JEDEC MO–169 with the exception of the dimensions indicated.






NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

1

KC (R-PSFM-T7)

PLASTIC FLANGE-MOUNT PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).

- B. This drawing is subject to change without notice.
- C. Lead dimensions are not controlled within this area.
- D. All lead dimensions apply before solder dip.
- E. The center lead is in electrical contact with the mounting tab.

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale, TI's General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025