


LOW POWER, 1.8/2.5/3.3-V INPUT, 3.3-V CMOS OUTPUT, 2-INPUT EXCLUSIVE-NOR GATE

Check for Samples: SN74AUP1T87

FEATURES

- Single-Supply Voltage Translator
- Output Level Up to Supply V_{CC} CMOS Level
 - 1.8 V to 3.3 V (at $V_{CC} = 3.3 \text{ V}$)
 - 2.5 V to 3.3 V (at $V_{CC} = 3.3 \text{ V}$)
 - 1.8 V to 2.5 V (at $V_{CC} = 2.5 \text{ V}$)
 - 3.3 V to 2.5 V (at $V_{CC} = 2.5 \text{ V}$
- Schmitt-Trigger Inputs Reject Input Noise and Provide Better Output Signal Integrity
- I_{off} Supports Partial Power Down (V_{CC} = 0 V)
- Very Low Static Power Consumption: 0.1 μA
- Very Low Dynamic Power Consumption: 0.9 µA
- Latch-Up Performance Exceeds 100 mA Per JESD 78, Class II
- Pb-Free Packages Available: SC-70 (DCK)
 2 x 2.1 x 0.65 mm (Height 1.1 mm)

- More Gate Options Available at www.ti.com/littlelogic
- ESD Performance Tested Per JESD 22
 - 2000-V Human-Body Model (A114-B, Class II)
 - 1000-V Charged-Device Model (C101)



DESCRIPTION/ORDERING INFORMATION

The SN74AUP1T87 performs the Boolean function $Y = \overline{A \oplus B}$ with designation for logic-level translation applications with output referenced to supply V_{CC} .

AUP technology is the industry's lowest-power logic technology designed for use in extending battery-life in operating. All input levels that accept 1.8-V LVCMOS signals, while operating from either a single 3.3-V or 2.5-V V_{CC} supply. This product also maintains excellent signal integrity (see Figure 1 and Figure 2).

The wide V_{CC} range of 2.3 V to 3.6 V allows the possibility of switching output level to connect to external controllers or processors.

Schmitt-trigger inputs ($\Delta V_T = 210$ mV between positive and negative input transitions) offer improved noise immunity during switching transitions, which is especially useful on analog mixed-mode designs. Schmitt-trigger inputs reject input noise, ensure integrity of output signals, and allow for slow input signal transition.

 I_{off} is a feature that allows for powered-down conditions ($V_{CC} = 0$ V) and is important in portable and mobile applications. When $V_{CC} = 0$ V, signals in the range from 0 V to 3.6 V can be applied to the inputs and outputs of the device. No damage occurs to the device under these conditions.

The SN74AUP1T87 is designed with optimized current-drive capability of 4 mA to reduce line reflections, overshoot, and undershoot caused by high-drive outputs.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.



ORDERING INFORMATION(1)

T _A	PACK	(AGE ⁽²⁾	ORDERABLE PART NUMBER	TOP-SIDE MARKING(3)
4000 to 0500	COT (CC 70) DCK	Reel of 3000	SN74AUP1T87DCKR	0.1
–40°C to 85°C	SOT (SC-70) – DCK	Reel of 250	SN74AUP1T87DCKT	6J_

- (1) For the most current package and ordering information, see the Package Option Addendum at the end of this document, or see the TI web site at www.ti.com.
- 2) Package drawings, thermal data, and symbolization are available at www.ti.com/packaging.
- (3) The actual top-side marking has one additional character that designates the wafer fab/assembly site.

FUNCTION TABLE

	INPUTS (Lower Level Input)			
Α	В	Υ		
L	L	Н		
L	Н	L		
Н	L	L		
Н	Н	Н		

Supply $V_{CC} = 2.3 \text{ V to } 2.7 \text{ V } (2.5 \text{ V})$

	00	<u>'</u>
INF V _{T+} max V _{T-} min	OUTPUT CMOS	
Α	В	Υ
V _{IH} =	= 1.1 V	V _{OH} = 1.85 V
V _{IL} =	0.35 V	$V_{OL} = 0.45 \text{ V}$


Supply $V_{CC} = 3 \text{ V to } 3.6 \text{ V } (3.3 \text{ V})$

	100 010	(0.0 1)		
INP V _{T+} max V _{T-} min =	OUTPUT CMOS			
Α	В	Υ		
V _{IH} =	V _{IH} = 1.19 V			
V _{IL} =	0.5 V	$V_{OL} = 0.45 \text{ V}$		

LOGIC DIAGRAM (XNOR GATE)



LOGIC-IDENTITY ELEMENT




The output is active (high) if all inputs stand at the same logic level (i.e., A = B).

EVEN-PARITY ELEMENT



The output is active (high) if an even number of inputs (i.e., 0 or 2) are active. ODD-PARITY ELEMENT

ISTRUMENTS



The output is active (low) if an odd number of inputs (i.e., only 1 of the 2) are active.




Figure 1. AUP - The Lowest-Power Family

Figure 2. Excellent Signal Integrity




Figure 3. Typical Design Examples




Figure 4. Switching Thresholds for 1.8-V to 3.3-V Translation



SCES806 – APRIL 2010 www.ti.com

ABSOLUTE MAXIMUM RATINGS(1)

over operating free-air temperature range (unless otherwise noted)

			MIN	MAX	UNIT
V_{CC}	Supply voltage range		-0.5	4.6	V
VI	Input voltage range ⁽²⁾		-0.5	4.6	V
Vo	Voltage range applied to any output in the high-impedance or	power-off state ⁽²⁾	-0.5	4.6	V
Vo	V _O Output voltage range in the high or low state ⁽²⁾				V
I_{IK}	Input clamp current	V _I < 0		-50	mA
I_{OK}	Output clamp current	V _O < 0		-50	mA
Io	Continuous output current			±20	mA
	Continuous current through V _{CC} or GND			±50	mA
θ_{JA}	Package thermal impedance (3)	DCK package		259	°C/W
T _{stg}	Storage temperature range	·	-65	150	°C

⁽¹⁾ Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

RECOMMENDED OPERATING CONDITIONS(1)

			MIN	MAX	UNIT
V_{CC}	Supply voltage		2.3	3.6	V
V_{I}	Input voltage		0	3.6	V
Vo	Output voltage		0	V _{CC}	V
	High lavel autout august	V _{CC} = 2.3 V		-3.1	A
I _{OH}	High-level output current	$V_{CC} = 3 \text{ V}$		-4	mA
	Low lovel output ourrent	V _{CC} = 2.3 V		3.1	A
I _{OL}	Low-level output current	$V_{CC} = 3 V$		4	mA
T _A	Operating free-air temperature		-40	85	°C

⁽¹⁾ All unused inputs of the device must be held at V_{CC} or GND to ensure proper device operation. See the TI application report Implications of Slow or Floating CMOS Inputs, literature number SCBA004.

Submit Documentation Feedback

⁽²⁾ The input negative-voltage and output voltage ratings may be exceeded if the input and output current ratings are observed.

⁽³⁾ The package thermal impedance is calculated in accordance with JESD 51-7.

ELECTRICAL CHARACTERISTICS

over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	V _{cc}	T _A =	25°C	T _A = -40 to 85°0		UNIT	
			MIN	TYP MAX	MIN	MAX		
V _{T+}		2.3 V to 2.7 V	0.6	1.1	0.6	1.1		
Positive-going input threshold voltage		3 V to 3.6 V	0.75	1.16	0.75	1.19	V	
V_{T-}		2.3 V to 2.7 V	0.35	0.6	0.35	0.6		
Negative-going input threshold voltage		3 V to 3.6 V	0.5	0.85	0.5	0.85	V	
ΔV_T		2.3 V to 2.7 V	0.23	0.6	0.1	0.6		
Hysteresis (V _{T+} – V _{T-})		3 V to 3.6 V	0.25	0.56	0.15	0.56	V	
V _{OH}	I _{OH} = -20 μA	2.3 V to 3.6 V	V _{CC} - 0.1		V _{CC} - 0.1			
	$I_{OH} = -2.3 \text{ mA}$	2.3 V	2.05		1.97		V	
	$I_{OH} = -3.1 \text{ mA}$	2.3 V	1.9		1.85			
	$I_{OH} = -2.7 \text{ mA}$	3 V	2.72		2.67			
	$I_{OH} = -4 \text{ mA}$	3 V	2.6		2.55			
	$I_{OL} = 20 \mu A$	2.3 V to 3.6 V		0.1		0.1	0.1 0.33 0.45 V	
	$I_{OL} = 2.3 \text{ mA}$	2.3 V		0.31		0.33		
V_{OL}	I _{OL} = 3.1 mA	2.5 V		0.44		0.45		
	I _{OL} = 2.7 mA	3 V		0.31		0.33		
	I _{OL} = 4 mA	3 V		0.44		0.45	ı	
I _I All inputs	$V_I = 3.6 \text{ V or GND}$	0 V to 3.6 V		0.1		0.5	μΑ	
I _{off}	V_I or $V_O = 0$ V to 3.6 V	0 V		0.1		0.5	μΑ	
ΔI_{off}	V_I or $V_O = 3.6 \text{ V}$	0 V to 0.2 V		0.2		0.5	μΑ	
I _{CC}	$V_I = 3.6 \text{ V or GND}, I_O = 0$	2.3 V to 3.6 V		0.5		0.9	μΑ	
Δ1	One input at 0.3 V or 1.1 V, Other inputs at 0 or V_{CC} , $I_{O} = 0$	2.3 V to 2.7 V				4	4 μΑ	
ΔI _{CC}	One input at 0.45 V or 1.2 V, Other inputs at 0 or V_{CC} , $I_{O} = 0$	3 V to 3.6 V				12		
C _i	V _I = V _{CC} or GND	3.3 V		1.5			pF	
C _o	V _O = V _{CC} or GND	3.3 V		3			pF	

SWITCHING CHARACTERISTICS

over recommended operating free-air temperature range, V_{CC} = 2.5 V ± 0.2 V, V_I = 1.8 V ± 0.15 V (unless otherwise noted) (see Figure 5)

PARAMETER	FROM	TO (OUTPUT)	C _L		T _A = 25°C			T _A = -40°C to 85°C		
	(INPUT)	(OUTPUT)		MIN	TYP	MAX	MIN	MAX		
	A or B	Y	5 pF	1.8	2.3	2.9	0.5	6.8		
			10 pF	2.3	2.8	3.4	1	7.9		
^t pd			15 pF	2.6	3.1	3.8	1	8.7	ns	
			30 pF	3.8	4.4	5.1	1.5	10.8		

Product Folder Link(s): SN74AUP1T87

SCES806 – APRIL 2010 www.ti.com

SWITCHING CHARACTERISTICS

over recommended operating free-air temperature range, V_{CC} = 2.5 V ± 0.2 V, V_I = 2.5 V ± 0.2 V (unless otherwise noted) (see Figure 5)

PARAMETER	PARAMETER	FROM	TO (OUTPUT)		CL	T	. = 25°C		T _A = -	40°C 5°C	UNIT
	(INPUT)	(OUTPUT)		MIN	TYP	MAX	MIN	MAX			
		Y	5 pF	1.8	2.3	3.1	0.5	6			
	A or D		10 pF	2.2	2.8	3.5	1	7.1			
t _{pd} A c	A or B		15 pF	2.6	3.2	5.2	1	7.9	ns		
			30 pF	3.7	4.4	5.2	1.5	10			

SWITCHING CHARACTERISTICS

over recommended operating free-air temperature range, V_{CC} = 2.5 V ± 0.2 V, V_I = 3.3 V ± 0.3 V (unless otherwise noted) (see Figure 5)

PARAMETER	PARAMETER	FROM	TO (OUTPUT)			CL	T,	(= 25°C		T _A = -	40°C 5°C	UNIT
	(INPUT)	(OUTPUT)	-	MIN	TYP	MAX	MIN	MAX				
		Υ	5 pF	2	2.7	3.5	0.5	5.5				
	A == D		10 pF	2.4	3.1	3.9	1	6.5				
t _{pd}	A or B		15 pF	2.8	3.5	4.3	1	7.4	ns			
			30 pF	4	4.7	5.5	1.5	9.5				

SWITCHING CHARACTERISTICS

over recommended operating free-air temperature range, V_{CC} = 3.3 V ± 0.3 V, V_I = 1.8 V ± 0.15 V (unless otherwise noted) (see Figure 5)

PARAMETER	FROM	TO (OUTPUT)	CL	T _A = 25°C			T _A = -	UNIT	
	(INPUT)		_	MIN	TYP	MAX	MIN	MAX	
t _{pd} A or B		A or B Y	5 pF	1.6	2	2.5	0.5	8	
	A D		10 pF	2	2.4	2.9	1	8.5	
	A OF B		15 pF	2.3	2.8	3.3	1	9.1	ns
			30 pF	3.4	3.9	4.4	1.5	9.8	

SWITCHING CHARACTERISTICS

over recommended operating free-air temperature range, V_{CC} = 3.3 V ± 0.3 V, V_I = 2.5 V ± 0.2 V (unless otherwise noted) (see Figure 5)

PARAMETER	FROM (INPUT)	TO (OUTPUT)		CL	T	λ = 25°C		T _A = -	40°C 5°C	UNIT
				MIN	TYP	MAX	MIN	MAX		
	A or B	Y	5 pF	1.6	1.9	2.4	0.5	5.3		
			10 pF	2	2.3	2.7	1	6.1		
^t pd			15 pF	2.3	2.7	3.1	1	6.8	ns	
			30 pF	3.4	3.8	4.2	1.5	8.5		

Submit Documentation Feedback



SWITCHING CHARACTERISTICS

over recommended operating free-air temperature range, V_{CC} = 3.3 V ± 0.3 V, V_I = 3.3 V ± 0.3 V (unless otherwise noted) (see Figure 5)

PARAMETER	FROM	TO (OUTPUT)	CL	T,	λ = 25°C		T _A = -40°C to 85°C		UNIT			
	(INPUT)	(OUTPUT)	_	MIN	TYP	MAX	MIN	MAX				
t _{pd}		Y	5 pF	1.6	2.1	2.7	0.5	4.7				
	A or D		10 pF	2	2.4	3	1	5.7	20			
	A or B		1	r	ĭ	15 pF	2.3	2.7	3.3	1	6.2	ns
					30 pF	3.4	3.8	4.4	1.5	7.8		


OPERATING CHARACTERISTICS

 $T_A = 25^{\circ}C$


PARAMETER		TEST CONDITIONS	V _{CC} = 2.5 V TYP	V _{CC} = 3.3 V TYP	UNIT
C _{pd}	Power dissipation capacitance	f = 10 MHz	4	5	pF



PARAMETER MEASUREMENT INFORMATION



	V _{CC} = 2.5 V ± 0.2 V	V_{CC} = 3.3 V \pm 0.3 V
C _L	5, 10, 15, 30 pF	5, 10, 15, 30 pF
V _{MI}	V _I /2	V _I /2
V _{MO}	V _{CC} /2	V _{CC} /2



VOLTAGE WAVEFORMS
PROPAGATION DELAY TIMES
INVERTING AND NONINVERTING OUTPUTS

NOTES: A. C_L includes probe and jig capacitance.

- B. All input pulses are supplied by generators having the following characteristics: PRR \leq 10 MHz, $Z_0 = 50 \ \Omega$, slew rate \geq 1 V/ns.
- C. The outputs are measured one at a time, with one transition per measurement.
- D. t_{PLH} and t_{PHL} are the same as t_{pd} .

Figure 5. Load Circuit and Voltage Waveforms

Submit Documentation Feedback

11-Nov-2025 www.ti.com

PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS	Lead finish/	MSL rating/	Op temp (°C)	Part marking
	(1)	(2)			(3)	Ball material	Peak reflow		(6)
						(4)	(5)		
SN74AUP1T87DCKR	Active	Production	SC70 (DCK) 5	3000 LARGE T&R	Yes	NIPDAU SN	Level-1-260C-UNLIM	-40 to 85	(6J5, 6JF)
SN74AUP1T87DCKR.B	Active	Production	SC70 (DCK) 5	3000 LARGE T&R	Yes	SN	Level-1-260C-UNLIM	-40 to 85	(6J5, 6JF)
SN74AUP1T87DCKRG4	Active	Production	SC70 (DCK) 5	3000 LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	(6J5, 6JF)
SN74AUP1T87DCKRG4.B	Active	Production	SC70 (DCK) 5	3000 LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	(6J5, 6JF)

⁽¹⁾ Status: For more details on status, see our product life cycle.

- (3) RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.
- (4) Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.
- (5) MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.
- (6) Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

PACKAGE MATERIALS INFORMATION

www.ti.com 18-Jun-2025

TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN74AUP1T87DCKR	SC70	DCK	5	3000	180.0	8.4	2.3	2.5	1.2	4.0	8.0	Q3
SN74AUP1T87DCKRG4	SC70	DCK	5	3000	178.0	9.0	2.4	2.5	1.2	4.0	8.0	Q3

www.ti.com 18-Jun-2025



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
SN74AUP1T87DCKR	SC70	DCK	5	3000	210.0	185.0	35.0
SN74AUP1T87DCKRG4	SC70	DCK	5	3000	180.0	180.0	18.0



SMALL OUTLINE TRANSISTOR



NOTES:

- 1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
 2. This drawing is subject to change without notice.
 3. Reference JEDEC MO-203.

- 4. Support pin may differ or may not be present.5. Lead width does not comply with JEDEC.
- 6. Body dimensions do not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.25mm per side



SMALL OUTLINE TRANSISTOR



NOTES: (continued)

7. Publication IPC-7351 may have alternate designs.8. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SMALL OUTLINE TRANSISTOR



NOTES: (continued)

- 9. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
- 10. Board assembly site may have different recommendations for stencil design.



IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale, TI's General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025