







CSD17382F4 SLPS562C - APRIL 2016 - REVISED FEBRUARY 2022

CSD17382F4 30-V N-Channel FemtoFET MOSFET

1 Features


- Low on-resistance
- Low Q_a and Q_{ad}
- Low threshold voltage
- Ultra-small footprint (0402 case size)
 - 1.0 mm × 0.6 mm
- · Ultra-low profile
 - 0.36-mm height
- Integrated ESD protection diode
 - Rated > 3-kV HBM
 - Rated > 2-kV CDM
- Lead and halogen free
- RoHS compliant

2 Applications

- Optimized for load switch applications
- Optimized for general purpose switching applications
- Single-cell battery applications
- Handheld and mobile applications

3 Description

This 30-V, 54-mΩ, N-Channel FemtoFET™ MOSFET technology is designed and optimized to minimize the footprint in many handheld and mobile applications. This technology is capable of replacing standard small signal MOSFETs while providing at least a 60% reduction in footprint size.



Typical Part Dimensions

Product Summary

T _A = 25°	С	TYPICAL VA	UNIT				
V _{DS}	Drain-to-Source Voltage 30						
Qg	Gate Charge Total (4.5 V)	2.1	2.1			2.1	
Q _{gd}	Gate Charge Gate-to-Drain	p-Drain 0.63					
	Drain-to-Source On-Resistance	V _{GS} = 1.8 V	110	mΩ			
B		V _{GS} = 2.5 V	67	mΩ			
R _{DS(on)}		V _{GS} = 4.5 V	56	mΩ			
		V _{GS} = 8.0 V	54	mΩ			
V _{GS(th)}	Threshold Voltage	0.9		V			

Device Information


DEVICE ⁽¹⁾	QTY	MEDIA	PACKAGE	SHIP
CSD17382F4	3000	7-Inch	Femto (0402) 1.0-mm ×	Tape and
CSD17382F4T	250	Reel	0.6-mm SMD Lead Less	Reel

For all available packages, see the orderable addendum at the end of the data sheet.

Absolute Maximum Ratings

	/ toooiato maximum rtatingo							
T _A = 25	°C	VALUE	UNIT					
V _{DS}	Drain-to-Source Voltage	30	V					
V _{GS}	Gate-to-Source Voltage	10	V					
I _D	Continuous Drain Current ⁽¹⁾	2.3	Α					
I _{DM}	Pulsed Drain Current ⁽²⁾	14.8	Α					
P _D	Power Dissipation ⁽¹⁾		mW					
ESD	Human Body Model (HBM)	3000	V					
Rating	Charged Device Model (CDM)	2000	V					
T _J , T _{stg}	Operating Junction, Storage Temperature	-55 to 150	°C					
E _{AS}	Avalanche Energy, Single Pulse I_D = 6.5 A, L = 0.1 mH, R_G = 25 Ω	2.1	mJ					

- Typical $R_{\theta JA} = 245^{\circ} \text{C/W} \text{ on } 1 \text{-in}^2 (6.45 \text{-cm}^2), 2 \text{-oz.}$ (0.071-mm) thick Cu pad on a 0.06-in (1.52-mm) thick FR4
- Pulse duration ≤100 µs, duty cycle ≤1%.



Top View



Table of Contents

1 Features1	6.2 Receiving Notification of Documentation Updates7
2 Applications 1	6.3 Trademarks7
3 Description1	6.4 Electrostatic Discharge Caution7
4 Revision History2	6.5 Glossary7
5 Specifications3	7 Mechanical, Packaging, and Orderable Information 8
5.1 Electrical Characteristics3	7.1 Mechanical Dimensions8
5.2 Thermal Information3	7.2 Recommended Minimum PCB Layout9
5.3 Typical MOSFET Characteristics4	7.3 Recommended Stencil Pattern9
6 Device and Documentation Support7	
6.1 Support Resources7	·

4 Revision History

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

Changes from Revision B (October 2021) to Revision C (February 2022)	Page
Changed ultra-low profile bullet from 0.35 mm to 0.36 mm in height Updated ultra-low profile image height from 0.35 mm to 0.36 mm	1
Changed ultra-low profile image height from 0.35 mm to 0.36 mm. Added FemtoFET Surface Mount Guide note	
Changes from Revision A (December 2016) to Revision B (October 2021)	Page
• Updated the numbering format for tables, figures, and cross-references throughout the doct	ument1

C	hanges from Revision * (April 2016) to Revision A (December 2016)	Page
•	Changed the TEST CONDITIONS for g_{fs} Transconductance From: V_{DS} = 15 V To: V_{DS} = 3 V in the Section 1.5 Condition	on
	5.1 section	3
•	Added Section 6.2 in the Section 6 section.	7
•	Updated all mechanical drawings.	8



5 Specifications

5.1 Electrical Characteristics

 $T_A = 25^{\circ}C$ (unless otherwise stated)

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
STATIC	CHARACTERISTICS					
BV _{DSS}	Drain-to-source voltage	V _{GS} = 0 V, I _{DS} = 250 μA	30			V
I _{DSS}	Drain-to-source leakage current	V _{GS} = 0 V, V _{DS} = 24 V			1	μΑ
I _{GSS}	Gate-to-source leakage current	V _{DS} = 0 V, V _{GS} = 10 V			5	μΑ
V _{GS(th)}	Gate-to-source threshold voltage	V _{DS} = V _{GS} , I _{DS} = 250 μA	0.7	0.9	1.2	V
		V _{GS} = 1.8 V, I _{DS} =0.5 A		110	180	mΩ
D	Drain-to-source on-resistance	V _{GS} = 2.5 V, I _{DS} = 0.5 A		67	82	mΩ
R _{DS(on)}	Dialii-to-source on-resistance	V _{GS} = 4.5 V, I _{DS} = 0.5 A		56	67	mΩ
		V _{GS} = 8.0 V, I _{DS} = 0.5 A		54	64	mΩ
9 _{fs}	Transconductance	V _{DS} = 3 V, I _{DS} = 0.5 A		5.9		S
DYNAMI	C CHARACTERISTICS					
C _{iss}	Input capacitance			267		pF
C _{oss}	Output capacitance	$V_{GS} = 0 \text{ V, } V_{DS} = 15 \text{ V,}$ f = 1 MHz		31.0	40.3	pF
C _{rss}	Reverse transfer capacitance	J		15.0	19.5	pF
R _G	Series gate resistance			220		Ω
Q _g	Gate charge total (4.5 V)			2.1	2.7	nC
Q _{gd}	Gate charge gate-to-drain	V = 15 V L = 0.5 A		0.63		nC
Q _{gs}	Gate charge gate-to-source	V _{DS} = 15 V, I _{DS} = 0.5 A		0.41		nC
Q _{g(th)}	Gate charge at V _{th}			0.12		nC
Q _{oss}	Output charge	V _{DS} = 15 V, V _{GS} = 0 V		1.53		nC
t _{d(on)}	Turn on delay time			59		ns
t _r	Rise time	V _{DS} = 15 V, V _{GS} = 4.5 V,		111		ns
t _{d(off)}	Turn off delay time			279		ns
t _f	Fall time		270			ns
DIODE O	CHARACTERISTICS	'				
V _{SD}	Diode forward voltage	I _{SD} = 0.5 A, V _{GS} = 0 V		0.7	1.0	V

5.2 Thermal Information

T_A = 25°C (unless otherwise stated)

		THERMAL METRIC	TYPICAL VALUES	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance ⁽¹⁾	85	°C/W	
	Junction-to-ambient thermal resistance ⁽²⁾	245	°C/W	


⁽¹⁾ Device mounted on FR4 material with 1-in² (6.45-cm²), 2-oz. (0.071-mm) thick Cu.


⁽²⁾ Device mounted on FR4 material with minimum Cu mounting area.




5.3 Typical MOSFET Characteristics

T_A = 25°C (unless otherwise stated)









Submit Document Feedback

Copyright © 2022 Texas Instruments Incorporated

www.ti.com







6 Device and Documentation Support

6.1 Support Resources

TI E2E[™] support forums are an engineer's go-to source for fast, verified answers and design help — straight from the experts. Search existing answers or ask your own question to get the quick design help you need.

Linked content is provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

6.2 Receiving Notification of Documentation Updates

To receive notification of documentation updates, navigate to the device product folder on ti.com. In the upper right corner, click on *Alert me* to register and receive a weekly digest of any product information that has changed. For change details, review the revision history included in any revised document.

6.3 Trademarks

FemtoFET™ is a trademark of Texas Instruments.

TI E2E™ is a trademark of Texas Instruments.

All trademarks are the property of their respective owners.

6.4 Electrostatic Discharge Caution



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

6.5 Glossary

TI Glossary


This glossary lists and explains terms, acronyms, and definitions.




7 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

7.1 Mechanical Dimensions








- All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
- B. This drawing is subject to change without notice.
- C. This package is a Pb-free bump design. Bump finish may vary. To determine the exact finish, refer to the device datasheet or contact a local TI representative.

Submit Document Feedback


Copyright © 2022 Texas Instruments Incorporated

7.2 Recommended Minimum PCB Layout



- A. All dimensions are in millimeters.
- B. For more information, see FemtoFET Surface Mount Guide (SLRA003D).

7.3 Recommended Stencil Pattern





SOLDER PASTE EXAMPLE

- A. All dimensions are in millimeters.
- B. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.



7.4 CSD17382F4 Embossed Carrier Tape Dimensions





A. Pin 1 is oriented in the top-right quadrant of the tape enclosure (quadrant 2), closest to the carrier tape sprocket holes.

www.ti.com 9-Nov-2025

PACKAGING INFORMATION

Orderable part number	Status	Material type	Package Pins	Package qty Carrier	RoHS	Lead finish/	MSL rating/ Peak reflow	Op temp (°C)	Part marking
	(1)	(2)			(3)	Ball material	(5)		(6)
						(4)	(5)		
CSD17382F4	Active	Production	PICOSTAR (YJC) 3	3000 LARGE T&R	Yes	NIAU	Level-1-260C-UNLIM	-55 to 150	HM
CSD17382F4.B	Active	Production	PICOSTAR (YJC) 3	3000 LARGE T&R	Yes	NIAU	Level-1-260C-UNLIM	-55 to 150	HM
CSD17382F4T	Active	Production	PICOSTAR (YJC) 3	250 SMALL T&R	Yes	NIAU	Level-1-260C-UNLIM	-55 to 150	НМ
CSD17382F4T.B	Active	Production	PICOSTAR (YJC) 3	250 SMALL T&R	Yes	NIAU	Level-1-260C-UNLIM	-55 to 150	НМ

⁽¹⁾ Status: For more details on status, see our product life cycle.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

⁽²⁾ Material type: When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

⁽³⁾ RoHS values: Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

⁽⁴⁾ Lead finish/Ball material: Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

⁽⁵⁾ MSL rating/Peak reflow: The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

⁽⁶⁾ Part marking: There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you fully indemnify TI and its representatives against any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale, TI's General Quality Guidelines, or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products. Unless TI explicitly designates a product as custom or customer-specified, TI products are standard, catalog, general purpose devices.

TI objects to and rejects any additional or different terms you may propose.

Copyright © 2025, Texas Instruments Incorporated

Last updated 10/2025